THE SYM USERS' GROUP NEWSLETTER

VOLUME IV, NUMBER 3 (ISSUE NO. 17) - MINTER 1983 (SEP/OCT/NOV/DEC)

SYM-PHYSIS was a serial publication of the SYM Users' Group. SYM-PHYSIS and the SYM Users' Group (SUG) are in no way associated with Synertek Systems Corporation (SSC), and SSC has no responsibility for the contents of SYM-PHYSIS. SYM is a registered trademark of SSC. SYM-PHYSIS, from the Greek, means the state of growing together, to make grow, to bring forth.

We welcomed for publication all articles dealing with any aspect of the SYM-1, and its very close relatives. Authors retain all commercial copyrights. Portions of SYM-PHYSIS may be reproduced by clubs and educational institutions, and adaptations of programs for other computers may be freely published, with full credit given and complimentary copies provided to SYM-PHYSIS and the original author(s). Please include a self-addressed stamped envelope with all correspondence.

Editor/Publisher: Business/Circulation: Office Staff: H. R. "Lux" Luxenberg Jean Luxenberg Joyce Arnovick, Denny Hall

SUBSCRIPTION RATES:

This is the FAREWELL ISSUE of SYM-PHYSIS, and subscriptions for future issues are no longer being accepted. Only Back Issues, in complete volumes, are available, as noted below. Make checks payable in US dollars to "SYM Users" Group", 20 Sunland Drive, Chico, CA 95926, Telephone (916) 895-8751.

BACK ISSUES:

Issues Ø through 6 (Volume I, 1979/8Ø), are available for \$12.00, US/Canada, and \$16.00, First Class/Airmail, elsewhere.

Issues 7 through 10 (Volume II, 1981), are available for \$10.50, US/Canada, and \$14.00, First Class/Airmail, elsewhere.

Issues 11 through 14 (Volume III, 1982), are available for \$10.50, US/Canada, and \$14.00, First Class/Airmail, elsewhere.

Issues 15 through 17 (Volume IV, 1983), are available for \$10.50, US/Canada, and \$14.00, First Class/Airmail, elsewhere.

L'ENVOI

Our original KIM-1, mounted on a large masonite panel, with an added 4 K of RAM, and a few assorted add-ons, is languishing in a dark corner of the garage. A second KIM-1, which was inoperative when we traded a new SYM-1 to a student for it, has been repaired, and now sits neatly boxed on a shelf. Also on the shelf is an odd lot of miscellaneous single board computers: an AIM-65, a SYM-69, a Sinclair ZX81, some RCA COSMAC VIPs, etc. None of these occupied the places in our minds and hearts that the SYM-1 did.

While the KIM-1 got us started, with the help of the 6502/KIM-1 Users' Group, it was the SYM-1, with the help of so many members of the SYM Users' Group, that really taught us how computers actually do work, deep down inside the operating system.

The KIM-1, so named after its 2 K ROM operating system, the Keyboard Interface Monitor (or Module) made a good entry level system, but the SYM-1, nee VIM-1 after its 4 K ROM operating system, the Versatile Interface Monitor (or Module), taught us all at a much more sophisticated level, thanks to all of the capabilities packed into MON 1.1, and RAE-1, which we still consider to be the very best full-featured 6502 Conditional/Macro Resident Assembler Editor around for the 6502, despite of, or perhaps even because of, its use of non-(continued to page 17-6)

SYM-PHYSIS 17-1

A 3-D GRAPHICS PACKAGE

Here is the BASIC portion of a 3-Dimensional Manipulation Package developed over a year ago as a class project by a former student, Tim Calhoun. We saw it demonstrated, and it worked very well, indeed, but we cannot now use it as it is, or provide sample graphic printouts, because our MTU Visible Memory SYM-1 system has been much too reconfigured to permit its easy use (BAS is now in RAM, VM is relocated, no cassette interface, etc.) with this program.

Even though very few readers may have Visible Memories on their SYM-1 systems (our main reason for not publishing it earlier), we are publishing it at this late date for three reasons:

One is the valuable collection of 4 x 4 matrix manipulation subroutines; second is its adaptability to 40×24 (80×48) graphics on the KTM-2 or 80×24 (160×48) graphics on the KTM-2/80. Third is the adaptability to the CDM-64 in either the low resolution or the high resolution graphics modes. We'll provide copies of this listing to several of our friends (we no longer have students, since our retirement; they are now friends!) with CDM-64s, to see what they can do with it.

In this connection, we should point out that the Visible Memory uses a direct linear mapping of its 320×192 pixels to RAM, while the COM-64 uses a mapping compatible with an 8 x 8 Character Generator Matrix. The Apple II/IIe uses a more "indirect" mapping (with 280×192 grid), while dot matrix printers in their graphics modes require an additional "remapping" to accomodate the vertical stacking of the printing "pins".

All of these remappings could easily be accomplished, if desired, by adding subroutines to the published program. We needed an Apple to Visible Memory remapping when we uploaded the public domain Apple SLIDE SHOW to our SYM-1, and will be needing a Visible Memory to COM-64 remapping when we download SLIDE SHOW to our COM-64.

	147	

	REM	
.3	REM	PROGRAM: SYM-1 3-DIMENSIONAL MANIPULATION PACKAGE
4.1	REM	PROGRAMMER: TIM CALHOON
5	REM	DATE: 12-6-82
6	REM	
7	REM	FUNCTION: TO ALLOW THE USER TO CREATE, MANIPULATE, DISPLAY,
8	REM	AND SAVE THREE-DIMENSIONAL OBJECTS.
9	REM	
10	REM	A HARDWARE NEEDED: SYM-1 WITH 8K MEMORY, MTU VISIBLE MEMORY,
11	REM	AND KTM TERMINAL.
	REM	EXTERNAL SOFTWARE: HUGH E. CRISWELL'S BASIC SAVE AND LOAD
13	REM	SUBROUTINES AND SYNERTEK'S TRIG-PATCH
14	REM	
15	REM***	· · · · · · · · · · · · · · · · · · ·
	REM	
51	REM	
52	REM	
53	REM***	- ************************************
54	REM	
55	REM	MAIN LINE ROUTINE:
56	REM	FIRST IT INITIALIZES SOME ESSENTIAL VALUES AND THEN IT
57	REM	SETS TEMP AND HOLD TO IDENTITY MATRICES.
58	REM	SECOND IT DISPLAYS THE MENU AND ASKS THE USER FOR
59	REM .	A CHOICE.
60	REM	LASTLY IT BRANCHES TO THE APPROPRIATE SUBROUTINE, THEN
	REM	LOOPS AROUND AND RE-DISPLAYS THE MENU.

```
100 DIM PROD(4,4):PI=3.1415
105 DIMHOLD(4,4), TEMP(4,4), D(7,30), MM(4), C(2,4)
1Ø7 LGTH=Ø
110 GOSUB600
120 FORA=1T04:FORB=1T04:HOLD(A,B)=TEMP(A,B):NEXT:NEXT
150 PRINTCHR$(27)+"E";:FORP=1T09:PRINT:NEXT
170 PRINT"1. DISPLAY", "2. ADD FILE", "3. LOAD FILE"
180 PRINT"4. SAVE FILE", "5. ROTATE", "6. SHIFT"
190 PRINT"7. SCALE", "8. DRIGINAL", "9. CLEAR"
200 PRINT"10. DELETE", "11. LIST FILE", "12. EXIT"
205 PRINT: INPUT INPUT NUMBER NEXT TO CHOICE ";A
210 IFA<10RA>12THEN205
220 ONAGOSUB300,700,1800,1900,1000,1490,1520,110,1700,800,900,2000
23Ø GOT015Ø
250 REM*****************************
251 REM
          PERSPECTIVE SUBROUTINE:
252 REM
           GOES THROUGH FILE CREATING PERSPECTIVE X AND
253 REM
           Y VALUES FROM 3-D COORDINATE FILE USING A DIVISION OF
254 REM
           SIMILAR TRIANGLES METHOD WITH VIEWPOINT ON THE Z-AXIS
255 REM
           AND SENDING THOSE X,Y VALUES TO A DDA ROUTINE.
256 REM
257 REM
300 INPUT"INPUT DISTANCE FROM ORIGIN "; DST:MM(4)=1
310 FORR=1TOLGTH:Q=1:FORS=1TO4STEP3
330 MM(1)=D(S,R):MM(2)=D(S+1,R):MM(3)=D(S+2,R)
335 IFS=4THENQ=2
340 FORJ=1TO4:C(Q.J)=0:FORK=1TO4
350 C(Q,J)=C(Q,J)+MM(K)+HOLD(K,J):NEXT:NEXT:NEXT
390 Y1=(C(1,2)*DST)/(DST+C(1,3)):Y2=(C(2,2)*DST)/(DST+C(2,3))
400 \text{ X}_{1}=(C(1,1)*DST)/(DST+C(1,3)):X2=(C(2,1)*DST)/(DST+C(2,3))
4Ø2 REM
          DDA LINE DRAWING SUBROUTINE:
4Ø3 REM
4Ø4 REM
          THIS ROUTINE USES THE SIMPLE DDA ALOGRITHM FOR DRAWING
405 REM
          A LINE BETWEEN TWO GIVEN POINTS DEFINED BY X1, X2 AND
4Ø6 REM
4Ø7 REM
          Y1, YZ.
4Ø8 REM
410 LNTH=ABS(X2-X1): IFABS(Y2-Y1) >LNTHTHENLNTH=ABS(Y2-Y1): X=X1:Y=Y1
415 X=INT(X1+159);Y=INT(Y1+99)
42Ø GOSUB 5ØØ
44Ø IFLNTH=ØTHENNEXT
45Ø DX=(X2-X1)/LNTH:DY=(Y2-Y1)/LNTH
455 XA=X1+.5:YA=Y1+.5
46Ø FORB=1TOLNTH
465 XA=XA+DX: YA=YA+DY: X=INT (XA+159): Y=INT (YA+99)
48Ø GOSUB5ØØ
490 NEXT: NEXT: RETURN
5@0 VM=8192+((199-Y)*40+INT(X/8)):BIT=((X/8)-INT(X/8))*8:DOT=2^BIT
5Ø5 IFVM<81920RVM>16383THENRETURN
51Ø MASK=PEEK(VM):DOT=128/DOT:DOT=MASKORDOT:POKEVM,DOT:RETURN
551 REM
552 REM
          TEMP = IDENTITY SUBROUTINE
553 REM
          THIS ROUTINE SETS THE TEMP MATRIX TO THE IDENTITY MATRIX.
554 REM
558 REM
600 FORI=1TO4:FORJ=1TO4:TEMP(I.J)=0:NEXT:NEXT
610 FORI=1TO4: TEMP(I, I)=1: NEXT: RETURN
```

```
ADD FILE SUBROUTINE:
652 REM
          THIS ROUTINE ACCEPTS COORDINATE VALUES FROM THE USER
653 REM
          AND ADDS THEM INTO THE FILE AT ITS END. IF A -999
654 REM
655 REM
          IS FOUND IN THE X1 POSITION THE RETURN IS EXECUTED.
656 REM
700 LGTH=LGTH+1:PRINT"INPUT -999 IN X1 POSITION AND 0 IN REST TO RETURN
71Ø PRINT"VECTOR "SLGTH
72Ø PRINT"INPUT X1, Y1, Z1, X2, Y2, Z2"
73Ø INPUTD(1.LGTH),D(2.LGTH),D(3.LGTH),D(4.LGTH),D(5,LGTH),D(6,LGTH)
735 IFD(1.LGTH)=-9990RLGTH>30THEN750
740 D(7,LGTH)=LGTH:GOTO700
750 D(1.LGTH)=0:LGTH=LGTH-1:RETURN
761 REM
762 REM
          DELETE SUBROUTINE:
763 REM
          THIS ROUTINE DELETES THE LINES BETWEEN THE STARTING AND
764 REM
          ENDING LINES VALUES. IT THEN MOVES THOSE LINES ABOVE THE
765 REM
          DELETED AREA DOWN TO FILL THE SPACES LEFT AFTER THE
766 REM
          DELETE.
767 REM
768 REM
800 INPUT"INPUT START AND FINISH OF DELETE ";S,F
81# IFF>3#THENRETURN: IFS>FTHENRETURN
815 IFF>LGTHTHENF=LGTH
82Ø IF F=LGTHTHEN86Ø
83Ø FORI=(F+1) TOLGTH: FORJ=1T07: D(J,S)=D(J,I):NEXT
840 D(7,5)=S:S=S+1:NEXT:LOTH=S-1:RETURN
86# LGTH=LGTH-((F+1)-S):RETURN
870 REM********************************
871 REM
          LIST FILE SUBROUTINE:
B72 REM
873 REM
          THIS ROUTINE LISTS THE RECORDS FROM A GIVEN
874 REM
875 REM
          STARTING RECORD NUMBER TO THE ENDING RECORD NUMBER.
876 REM
877 REM
900 INPUT "INPUT START AND FINISH OF LISTING "; S.F
910 FORI-STOF
915 IFI>LGTHTHEN94Ø
920 PRINTI.D(1,I),D(2,I),D(3,I)
930 PRINT, D(4, I), D(5, I), D(6, I)
935 PRINT: NEXT
946 INPUT"INPUT 1 TO GET MENU "; A
95Ø RETURN
961 REM
962 REM
          ROTATION SUBROUTINE:
963 REM
          THIS ROUTINE FIRST FINDS A CENTER FOR THE OBJECT.
964 REM
          THEN TRANSLATES THE OBJECT TO THE ORIGIN, THEN
965 REM
966 REM
          BRANCHES TO THE APPOPRIATE SUBROUTINE TO EXECUTE
967 REM
          A ROTATION ABOUT THE X,Y OR Z AXIS, AND FINALLY
          TRANSLATES THE OBJECT BACK AGAIN.
968 REM
969 REM
97Ø REM***************************
1000 XGT=D(1,1):XLT=XGT:YGT=D(2,1):YLT=YGT:ZGT=D(3,1):ZLT=ZGT
1010 FORI=1TOLGTH:FORJ=1TO4STEP3:
1020 IFXGT<D(J, I)THENXGT=D(J, I):IFXLT>D(J, I)THENXLT=D(J, I)
1936 IFYGT<D(J+1, I) THENYGT=D(J+1, I): IFYLT>D(J+1, I) THENYLT=D(J+1, I)
1040 IFZGT<D(J+2, I) THENZGT=D(J+2, I): IFZLT>D(J+2, I) THENZLT=D(J+2, I)
```

1050 NEXT: NEXT

```
1060 DX=-(((XGT-XLT)/2)+XLT):DY=-(((YGT-YLT)/2)+YLT)
1061 DZ=-(((ZGT-ZLT)/2)+ZLT)
1065 GOSUB600
1070 GOSUB1497
1080 INPUT INPUT 1,2,3 FOR ROTATION ABOUT X,Y,ORZ AXIS ";B
1085 IFB<10RB>3THEN1080
1086 INPUT INPUT ANGLE OF ROTATION "; ANG
1087 ANG=ANG*PI/180
1090 ONBGOSUB1200,1300,1400
1100 DX=-DX:DY=-DY:DZ=-DZ:GOSUB600
11Ø5 GOSUB1497
111Ø RETURN
1150 REM****************************
1151 REM
          X,Y, AND Z ROTATION SUBROUTINES:
1152 REM
1153 REM
          THESE ROUTINES SET VALUES IN 4 X 4 MATRICES AND
1154 REM
          CONCATENATE THEM, THROUGH MULTIPLICATION INTO
1155 REM
          A RESULTANT MATRIX TO BE USED TO SET TRANSFORMED
1156 REM
          X,Y,Z VALUES IN THE PERSPECTIVE ROUTINE.
1157 REM
1158 REM
1159 REM****************************
1160 REM
1161 REM
1162 REM**********************************
         X-ROTATE
1164 REM********************
1200 GOSUB600
1210 TEMP(2,2)=COS(ANG):TEMP(2,3)=SIN(ANG):TEMP(3,2)=-SIN(ANG)
1220 TEMP (3,3) = COS (ANG): GOSUB1600
123Ø RETURN
1250 REM**************************
1251 REM
1252 REM**********************************
1310 TEMP(1,1)=COS(ANG):TEMP(1,3)=-SIN(ANG):TEMP(3,1)=SIN(ANG)
132Ø 60T0122Ø
1350 REM****************************
1351 REM
          Z-ROTATE
1410 TEMP(1,1)=COS(ANG):TEMP(2,1)=-SIN(ANG):TEMP(1,2)=SIN(ANG)
1420 TEMP (2,2) = COS (ANG): GOSUB1600
143Ø RETURN
SHIFT SUBROUTINE:
1492 REM
           SETS UP 4 X 4 MATRIX FOR A GIVEN SHIFT ALONG X,Y, DR Z
1493 REM
1494 REM*********************************
1495 INPUT"INPUT SHIFT IN X,Y,Z ";DX,DY,DZ
1497 TEMP (4,1)=DX: TEMP (4,2)=DY: TEMP (4,3)=DZ
1500 GOSUB1600
151Ø RETURN
1520 GOSUB600
1521 REM**********************
1522 REM
           SCALE SUBROUTINE:
1523 REM
           SETS UP A 4 X 4 MATRIX FOR SCALE ON GIVEN X,Y, AND Z
1524 REM
1526 REM**********************************
1530 INPUT AMOUNT OF SCALE IN X,Y,Z ";TEMP(1,1),TEMP(2,2),TEMP(3,3)
1540 GOSUB1600
155Ø RETURN
```

```
1552 REM
          4 X 4 MATRIX: MULTIPLICATION TO CONCATENATE A FUNCTION
1553 REM
1554 REM
          INTO THE HOLD MATRIX.
1555 REM*********************************
1600 FORA=1T04:FORB=1T04:PROD(A,B)=0:FORK=1T04
1610 PROD (A, B) = PROD (A, B) + HOLD (A, K) * TEMP (K, B) : NEXT: NEXT: NEXT
1620 FORA=1TO4:FORB=1TO4:HOLD(A,B)=PROD(A,B):NEXT:NEXT:RETURN
1700 FORI=8192T016383:POKEI, Ø:NEXT:RETURN
CALL TO CRISWELLS DATA LOAD ROUTINE
1752 REM**********************************
1800 INPUT"SET UP FOR CASSETTE LOAD AND INPUT FILE NUMBER "; ID
1810 X=USR (7807, 256*ID): RETURN
1900 PRINT"FILE WILL BE SAVED 3 TIMES"
1901 REM****************************
          CALL TO CRISWELLS DATA SAVE ROUTINE
1910 INPUT"SET UP FOR CASSETTE SAVE AND INPUT FILE NUMBER "; ID
1920 FORI=1T03: X=USR(7718,256*ID):NEXT:RETURN
2000 END
```

L'ENVOI (continued from page 17-1)

standard MOS Technology pseudo op-codes (this may be the longest non-stop one sentence paragraph we've ever written!).

We'll never forget all we learned from the SYM, or from the many fine SYMmers we met by mail, telephone, or personal contacts on past and future visits to us, or travels to them. Thanks to everyone from both of us.

RAM-BLINGS

In the B. C. (Before Computer) era, our home had a number of leisure-and/or pleasure-type rooms, including, among others, a guest room, a family room with a magnificent fireplace and the main TV ("telly"), and a combination den/study where our SYM-1 setup lived on a corner of our desk. Jean suggested that the SYM system be set up on a card table in the family room so that there could be some "togetherness", with her watching the TV while we watched the KTM-2 monitor.

Today the guest room is now Jean's cluttered office, the study/den is now a cluttered warehouse/storeroom, and the family room is now a cluttered computer laboratory/workshop, with desks, workbenches, book shelves, and filing cabinets along all four walls (effectively blocking the fireplace), and a custom made 4' x 8' computer table in the center of the room. And the elegant darkroom in one corner of the garage is now unuseable, having become a catch-all storeroom.

Thus the SYM has very strongly affected our way-of-life, as well as our standard of living. By chance, or whatever, we and the SYM are retiring simultaneously, but it will probably take several years for our home to return to "normal", if ever. We won't even begin to think about it till our European trip is over!

Being a SYMmer almost implied being a "loner", somewhat akin to the "loneliness of the long distance runner", since very few of us were in a position to be able to work closely with other SYMmers, and to swap hardware, software, and, most importantly, ideas, either in a one-on-one or on a "live" group basis. There have never been more than two or three SYMmers in or near Chico, at any given time, with whom we could work closely. That, in fact, was why the Users' Group was started! At no time, however, were there more than 2000 members.

There were many times when we almost envied our Apple owning friends, and we did think occasionally of switching. It was not the cost that stopped us, it was the realization of how little we actually would be getting for our money, compared with what the SYM was giving us. But, even more importantly, we had made so many new friends, by mail, telephone, and personal contacts, and thus were receiving so much more personal satisfaction from being a SYMmer then we could ever have gotten from the Apple.

Our five "main" SYMs are now mostly idle. One is used by Jean to handle the cassette and FODS diskette software duplication, the mailing list, and the accounts payable records. That one still gets the most use, but its active days are nearly over. Another one is used only as a test bed for KTMs. It comes up in the 2 K Synertek FORTH ROM, with a .J Ø, and a simple one line FORTH definition "checks" out the KTMs before they are shipped. This gets very little useage.

A third system supports both FODS and FDC-1 (modified, and in RAM) DOSes, and is used only for making distribution copies of Wharrie's FDC-1 FORTH (which ALL FDC-1 owners SHOULD own, it's great!). The CODOS/Visible Memory SYM is used only to demonstrate the high resolution graphics, and Jack Brown's CODOS FORTH to the occasional visitor. It is turned on so seldom that the NiCad backup batteries on Jeff Lavin's hardware real time clock never really get a full charge. Its major use in the near future will be to download its graphics images to the COM-64.

The CODOS/VM SYM is truly impressive in both demonstrations, because the disk drives can transfer 8 K in either direction in a matter of a second or so, making animated graphics sequences easily possible. Also, when using the standard virtual memory management built into FORTH, only the clicking sounds from the 8-inch drives give away the secret that the screens being requested were not already resident.

Our own "personal" SYM is used for an occasional demonstration of the MTU Advanced Music Software Package (truly astounding), and is being used to prepare this final issue of SYM-PHYSIS only because we have not yet become truly proficient in the uses of any one of the half-dozen or so word processors we now have on the COM-64 (we also have two, including Quick Brown Fox, for the VIC=20).

There are modest amounts of test gear, hand tools, miscellaneous spare parts and components, all useful on other systems. But there are literally hundreds of "used" cassettes and diskettes neatly filed away, some of which we are beginning to "recycle" for use with the 1541 drives, since we see very little future use for the data they now hold.

What's to become of all of this stuff? That we'll leave to the future to decide. We had thought of giving the stuff to students, but it has been our sad experience that such "gifts" were not always useful to the recipients. Unless they themselves had put up some of their own hard earned cash to get started, there was too little motivation to continue. In the old days, several students started with the SYM-1, and as they showed that they were finding the time to learn how to use what they already had, they got "good deals" on RAEs, BASes, KTMs, etc. Today they are much smarter to start out with the VIC=28, the COM-64, the Timex-Sinclair, etc.

And that brings us up to our known plans for the foreseeable near future: to learn as much as we can about the inner workings of the VIC=20 and the COM-64, so that we can help students and others to get the most out of their systems. To that effect we've been putting as much time on these systems (or even more, since they are so much more versatile, and there is so much more to learn) as we once did on the SYM-PHYSIS 17-7

SYMs! We did build up a valuable skill during the process. We can now switch from one system or DOS to another, and our mind automatically shifts to the proper memory bank which contains the "smarts" for that system or DOS; we no longer become schizophrenic at each shift!

OPEN LETTER TO THE SYM COMMUNITY FROM JEFF LAVIN

AND

ANNOUNCEMENT OF SYMDOS2 BY KIN-PING KWOK

26 January 1984

ALTERNATIVE ENERGY PRODUCTS P.O. Box 329 6000 Running Springs Road Ukiah, California 95482 707:462-9244

Members of the SYM community:

In this, the last issue of SYM-PHYSIS, we would like to thank all the people who have made the SYM USER'S GROUP the spawning ground for such a preponderance of ideas and energy. We especially want to thank those of you who have purchased products from us. And we proudly announce our plans for the future.

First of all, don't worry, we will continue to offer our products for as long as current supplies hold out. We will also continue to repair SYMs, FDCs, etc. (NO KTMs) Please direct all future orders directly to AEP at the above address.

Secondly, we are very happy to announce a new DOS written for the FDC by Kin-ping Kwok. Those of you familiar with Kwok's previous work need no further assurance regarding the quality of his programs. I would like to say, though, that he has outdone himself. We have excerpted the introduction and list of commands from the SYMDOS2 manual (they are reproduced following this article). In addition to the features mentioned here, the DOS defaults to a 32K system. Also, there is no longer the IRQ bug to worry about when doing interrupt driven programming, and a very extensive directory search routine is included. Those of you familiar with FLEX (trademark of TSC) will recognize the three character filename extensions; the protocol is to name your file according to type e.g. .RAE .COM .OBJ .TXT etc.

A very useful and important feature of SYMDOS2 is the creation of a "cold-start sector". Upon cold start, the DOS will read the first sector of track zero into memory and test for an "IDMARK". If the mark exists, the DOS will transfer control to a user program. Can anyone think of a use for this?!!!

SYMDOS2 will be available by the time you read this and will consist of: a 5.25° floppy disc, a 2732 EPROM to replace the one on the FDC and a documentation manual. Although SYMDOS2 will support 8° drives, we will only be supporting 5.25° drives for two reasons: One, 5.25° drives are the defacto standard for personel computers; two, only a few people using the FDC are known to use 8° drives AND we aren't one of them! The price is \$180 U.S. (shipping included). Please specify if you desire the disc I/O located anywhere besides \$F800 and \$F180; that is where they will be if you do not specify elsewhere.

Those of you who do not yet own FDCs, and desire to, may still have an opportunity to purchase one. As of this writing we have 17 boards left. These may be purchased as assembled and tested units, as kits, or as bare boards. Call or write for information.

The preceeding information about SYMDOS2 leads us into our last bit of news. We are going to start a special interest group/newsletter for the FDC/SYMDOS2. We will be publishing a newsletter, probably on a quarterly basis, devoted to programs written for the SYM/FDC combination. There will in all likelihood also be included things of general interest from time to time, but the starting intention is as stated. We hope to include hardware and software improvements and tutorials, shopping guide (maybe to include advertisements) and, of

course, programs. We will also distribute SYMDOS2 compatible programs on a royalty basis for any interested parties. The newsletter will cost \$15 in the United States and Canada, \$18.58 elsewhere per 4 issue volume. Make checks payable in U.S. funds to Alternative Energy Products, P.O. Box 329, Ukiah, CA 95482. To those of you who implored us to continue the SYM USER'S GROUP, we are sorry, but this is the best we can do. We do not have the time or energy to devote that Lux did. Most of our articles will be written by readers, and programs will not be edited as much - only checked to insure they at least run and seem to do what the author says they will do. We will have a smaller, and it is hoped closer, user's group than SUG; hence the higher per member cost. We are doing this in the hopes that the SYM community will continue.

After the SYM-PHYSIS has gone to press, we will be mailing a letter to all FDC owners. To the rest of you, this is probably our last contact UNLESS YOU WRITE (or phone)! I have enjoyed these past 2 1/2 years immensely.

Peace.

/s/ Jeff Lavin

INTRODUCTION to SYMDOS2 Copyright August 1983 - by Kin-ping Kwok

The FDC-1 is a disk controller for the SYM with a 4K DOS on board. However, there are bugs in the DOS. The undeletable file format is very inconvenient. The user has to reformat a diskette very often. The design of the DOS also limits its expansion. For the above reasons, I have written a new DOS for the FDC-1 to replace the original one.

SYMDOS2 directly replaces the original DOS. It can operate with either a 5" or 8" dual drive system. See the FDC-1 manual for the configuration required. It can also operate up to four single sided drives with a little hardware modification. When using the on-board Keyboard, you have to change the vectors yourself as in the origional DOS.

SYMDOS2 can operate in as small as a 1K system. The default is for a 32K system. The diskette format defaults to 5° single density 128 bytes/sector or 5" double density 256 bytes/sector. See ALTERATION for change of defaults. Diskettes formatted by the original DOS may be used by SYMDOS2. However, the directory format is not compatible.

SYMDOS2 has been carefully checked to eliminate bugs. you find any bugs, please drop me a note.

Finally I hope you like SYMDOS2.

Kin-ping Kwok

SUMMARY of COMMANDS

SUPERMON

BAS-1

RAE-1

FUNCTION: Link to SYMDOS2

.G 9886

X=USR(&"9000",0)

>RU \$9883

FUNCTION: Save to disc

. 53

SAVE us "filename"

>EN filename u

filename,u,sa,ea

FUNCTION: Load from disc

.1.3

LOAD us"filename"

>LO filename u

filename, u

FUNCTION: Load and relocate or append

LOAD usA, "filename" .13

>LO filename u A

filename, u, sa

FUNCTION: Delete files

. 54

filename, u

>DC KILL filename u

FUNCTION: Rename file

newname, oldname, u

FUNCTION: List directory

.L7 u

.L7

>DC DIR u

>DC DIR filename u

filename, u

FUNCTION: Continue to disc

>nnnn .CT filename u

This is an example of the two types of directory listing:

XRF : FORMAT RAE : FORMAT XRF XRF :DDI2 RAE :DDI2 RAE :FIO3 XRF11A RAE :XRF11A DOC :

or you can have it this way:

XRF 8288-3AC6 :DDI2 RAE 8208-1E4C : F103 RAE 8208-4F17 :FIO3 XRF 0200-1A0F :FORMAT RAE 0200-12F0 :FORMAT XRF 0200-104E : DDI2 XRF11A RAE 0200-3489 :XRF11A DOC 0200-49D5 :

MORE ON FDC-1

Reprinted below is a letter from Alan Foster, whom we very much enjoyed meeting during our visit to Australia. He is offering some enhancements for FDC-1 users. In a handwritten postcript he asked two questions, which we will answer here:

First, he asked our opinion regarding a fair price for the package; we feel that \$25.00 U.S., postage prepaid anywhere, should cover his handling and shipping costs, and give him a little extra to pay for more equipments. So, write him directly, if interested.

Second, he asked if there would be any copyright problems, in excerpting so heavily from the object code in the FDC-1 EPROM. The answer is not at all, for the following reason: The SYM Users' Group, was given, in writing, all software, firmware, and hardware rights to the FDC-1. We hereby, officially, surrender all software and firmware rights to the FDC-1 into the public domain.

28 GAVIN PLACE, KINGS LANGLEY, NSW, AUSTRALIA, 2147

12 NOVEMBER 1983

Dear Lux,

Received your letter re FDC-1 and am enclosing details of my version. Having disassembled and reassembled the FDC-1 firmware I believe I now have a completely bug free version as well as a number of enhancements. Some of the changes are listed below.

Fixes for all firmware bugs mentioned in SYM-PHYSIS have been incorporated. This includes a fix for the "File Save Bug" mentioned in Issue #15 (no solution available at that time).

I have also included a fix for the fact that Supermon's execute command will not work in conjunction with FDC commands. This also allows XRAY's execute command to work with FDC. The execute commands can now be used for copying disks.

This version also includes a power on reset routine which, among other things, initialises the DOS.

On initialising FDC, an expandable table of vectors to FDC routines is moved into RAM. This means that no matter what changes I make to the DOS, or even if I am running an experimental version in RAM, it will always look the same to RAE, FORTH, BASIC etc. The alternative would require that these systems be changed every time the DOS is changed.

DOS memory usage is now as follows:

9000-97FF RAM for DOS variables and buffers 9800-98FF SYMDOS DISK DRIVE INTERFACE F000-F1FF CONTROL PORT & 1791 F800-FFFF SYMDOS INTERFACE, AND POR ROUTINE

SYSRAM is no longer used by the DOS

If a file is saved with a name which already exists on the disk, the user is prompted with the following options:

Choose a new name (to avoid smudging the existing file). Smudge the old file.

Overwrite the old file (new file must fit in the space available).

As a separate package I have written a RAE interface which corrects several bugs and deficiencies in the original firmware.

I have also written several disk copy and associated routines as one package. These provide the following:

SYM-PHYSIS 17-11

1. List the directory of the disk to be copied and prompt for selections from this list (up to 20). Selected files will then be copied to a second disk.

- 2. As above, but files are copied to tape in "named format" with a header file which contains the file name.
- 3. Copy selected files from tape to disk.
- 4. Read one tape in named format into memory.
- 5. Re-initialise a previously initialised disk. (Much faster as it only writes a zero to the first byte in the directory.)

The source code for all of the above plus details of hardware changes for the POR routine are available on 5 1/4" diskette at nominal cost, and may be obtained by writing to me at the above address.

Regards.

A.L.Foster:

MISCELLANEA

BORIS GOLDOWSKY, 23 Culver Hill, Southampton, NY 11968, sent us the object code for an "Etch-a-Sketch" (tm) type program using the MTU y Visible Memory and a joystick (analog-type, we believe). We have not yet been able to test the program, since our VM is not at the same location as his. Those of you with Visible Memories may wish to contact him directly for a copy.

We are definitely a creature of habit, and find it hard to adapt to new ways of doing things. Although we have three different Assemblers and five different Word Processors for the Commodore 64, we still use RAE-1 and SWP 2.5 on the "good ol' SVM" for most of our serious work.

We have been comparing all of the assemblers available for the COM-64, and MAE (for Macro Assembler Editor, a variant of RAE, for Resident Assembler Editor) is the only one we have found in which the Editor portion and the Assembler portion are co-resident. In all others the Editor prepares the text file which must then be dumped to mass storage. The Assembler must then be loaded, and it must recall the text file from mass storage for assembly, etc. This back-and-forth switching is inconvenient, to say the least.

MAE also comes with an improved SWP, and an extended Machine Language Monitor (with even more useful commands than SYM's SUPERMON). The ATU6 (ASM/TED Users' Group — MAE also goes by the name of ASseMbler/TExt eDitor) provides a (public domain) disassembler into MAE format of the same high level as Dessainte's Disassembler into RAE. It even has the additional convenience feature that it can be advised NOT to attempt to disassemble certain ranges which the simple disassembler built into the ML monitor has "advised" you contain text, tables and/or vectors; it treats these ranges as being composed of easily edited ".BY" pseudo-opcodes.

This means that when we really get going seriously on the COM-64 we'll not have to break too many old habits! And, too, we hope to be able to swap RAE and MAE files between the SYM and the COM-64 when we get our 1541 Drive interfaced to the SYM.

AN FDC-1 BASIC PATCH

BILL CRAMER, 5609 N. Colony Blvd., The Colony, TX 75056, sent along an FDC-1 diskette with the RAE source code for a BASIC DATA SAVE/LOAD routine which permits data files to be passed between BASIC programs, and permits BASIC programs to access multiple files.

The ability to access multiple files is a particularly valuable feature, since otherwise the data files would be size-limited by RAM availability.

It is based on the cassette versions published in previous issues, but is fully linked to the FDC-1 system. We suggest that you contact Bill directly for a copy.

An alternative approach to saving data files which we have been investigating lately is the concept of "sequential" files (and the related concept of "relative" files), as implemented in the various Commodore systems.

In this approach, the data is (are?) dumped to disk as "text" files, and read back in the inverse fashion. The disk system is, in effect, treated as an alternate ASCII terminal interfaced through an IEEE (or serial equivalent) bus. The Commodore disk drives are "intelligent", handling their own buffering and file management. The SYM-1 would have to handle these two tasks, either for FDC-1 or FODS, but this capability is already built into CODOS.

CHEAP RAM FOR SYM AND HAIR-LINE CRACKS

RALPH TEICHEL, P.O. Box 426, Elsternwick 3185, Melbourne, Victoria, Australia, had problems with RAE not storing data past \$2000. We advised him that the fault was probably not with RAE, but with his RAM (others have reported similar problems with both RAE and BAS, "fixed" by getting their RAM to work correctly). Sure enough, he found hair-line cracks on his RAM board. One seldom suspects such faults, but we have run into them ourselves.

How to find them? First isolate the problem to the particular board, based on the "behaviour" of the error, and then good luck! This is one of the reasons we recommend "flexing" the boards. This will either close the crack, or break it wide open. In the first case, great!; in the second case you have replaced an intermittent failure with a steady-state one, which is much easier to find.

The main reason for publishing this brief note, is Ralph's suggestion that VIC=20 RAM expansion boards work well with the SYM also. He got his free from a friend(?) who had used them briefly, and then gave them away (Ralph now understands why!).

Ralph calls his SYM "F.R.E.D.", for reasons "not too polite". Since he was too polite to tell us, can anyone else explain the acronym?

AN INTERESTING OFFER AND AN OBJECT CODE TRANSFER PROGRAM

As you know, object code (and BASIC programs as stored in tokenized form) cannot be transmitted directly, byte for byte, since ASCII format handles only seven of the eight bits per byte. Instead, each byte must be broken into two nibbles, and the value of each nibble, corresponding to hex digits Ø through F, is sent as the corresponding ASCII character. Some protocol is required concerning message length, load address, check sums, etc. One such protocol appears in Appendix D of the SYM-1 Reference Manual, as the Paper Tape Format.

An alternate protocol is the Intel Hex Format, mentioned in the letter reproduced below. The letter is published for general interest, and for the interesting offer. A program for the SYM-1 to receive Intel Hex Format follows. We have not yet had the time to try it, although we have a Modem Program for the COM-64 which both sends and receives this format. Our lag in testing this program is that we have never installed a modem "permanently" on any of our SYMs; besides we will be transfering object code from SYM-1 to COM-64 (but not the other way) via 1541 diskettes.

10-29-B3

Dear Lux:

I enjoyed our conversation on the telephone regarding hex file transfer from an assembler using the paper tape read function on the SYM-1. I never did get that mode to work, but wound up writing a ML program for the sym to accomplish this. Since I was writing the program myself, I chose to use the more standard Intel Hex Format instead of the KIM format as we discussed. I enclose the source code for the program as an attachment to this letter. I will be glad to supply the program in SYM tape form to anyone sending a tape and a SASE large enough to return the tape and with sufficient postage. The program is written in RAE-1 format. Use of this program allows one to assemble 6502 source code using the AVOCET 6502 assembler on either an IBM-PC or on a CPM based computer and then to transfer the resulting HEX file to the SYM-1. This makes a very nice development system.

The main reason that I'm writing, however, is to tell you about some exciting products I've been developing for MWM Electronics. MWM Electronics is and Atlanta based firm specializing in electronic circuit development for third party manufacturing and sales (usually onder brand names). They started out several years ago manufacturing accessories for satellite television receivers and I have acted as their chief engineer since 1981.

About two years ago we decided to develop a general purpose controller for a satellite receiving station, allowing IR remote control of the entire system (antenna, polarization, channel, etc) from one's easy chair in any room in the house. To accomplish this, we used a Motorola 6802 microprocessor, primarily because we had a large inventory of these chips at the time. Since that time we have designed and built an number of types of controllers for microwave receiving systems and to control test equipment, etc. Each time, we have had to design a new printed circuit board from scratch, requiring several iterations for debugging and modifications.

Another problem we had was that of assembling M6800 source code. For one thing, I was much more familiar with the 6502, having been a long time SYM-1 and Commodore Pet owner (8032, 4032, 4040, 4022, etc). For another thing, I had no computer which employed a M6800 microprocessor as its CPU. At first we hand assembled (ugh!). Later, we wrote a crude assembler in basic (it took 12 hours to assemble 4 K of code). All things considered, I became very frusterated with the M6800 and wanted to change processors, but the momentum was directed against it.

One day, I decided to develop a general purpose mother board, with an eight connector bus which was oriented toward control applications, and with almost nothing else but the processor, bus drivers, a boot ROM and zero page RAM on the mother board, thereby allowing maximum flexibility of configuration. In laying out the board, one of my engineers mentioned that by offsetting

another 40 pin socket slightly, he could arrange the PC board to accomidate either a M6802 or a 6502....WOW!!! Thus was born the SYSTEM-6000.

By way of brief description, the MWM Electronics SYSTEM-6000 mother board consists of the following:

Microprocessor (6502 or 6802)

Crystal

One EPROM (2716 or 2532) at top of memory

One (optional) 6116 2K RAM chip located at \$0000

One 6522 VIA located at \$A000

A power supply with +5 Volts at 2 Amps

+15 Volts at 0.5 Amps

-15 Volts at 0.5 Amps +5 Volt back up battery

A 16 key keypad (optional) connected to PAO-PA7 of the VIA An eight digit HEX display driven by PBO-PB7 of the VIA An eight slot BUS with using 0.1 in spaced dual 22 pin

connectors with the following pinputs: 1 BAO A Bround 2 BA1 B NOT D400-D7FF C NOT DOOG-D3FF 3 BA2 4 BA3 D NOT DBOO-DBFF 5 BA4 E NOT C400-C7FF 6 BA5 F NOT CBOO-CBFF 7 BA6 H NOT CCOO-CFFF B BA7 J NOT RESET 9 BA8 K PHASE 2 CLOCK 10 BA9 L NOT IRQ 11 BA10 M BD7 12 BA11 N BD6 13 BA12 P BD5 14 BA13 R BD4 15 BA14 S BD3 16 BA15 T BD2 17 NOT NMI U BD1 18 READY V BDO W -15 VOLTS 19 R/W X +15 VOLTS 20 +8 VOLTS UNREG 21 +5 VOLTS STBY Y +5 VOLTS REG

In addition to the SYSTEM-6000 Mother Board, we have developed a number of plug-in cards for the bus. The cards which are wither finished or in various stages of development are as follows:

MEMORY BOARD (holds four either 2716's or 6116's)

Z GROUND

6522 BOARD

22 GROUND

6532 BOARD

8 BIT D/A CONVERTER BOARD

TMS-9918A SPRITE VIDEO BOARD

RESOLVER/SYNCHRO INTERFACE (ANGULAR POSITION)

IR SENSOR INTERFACE

RELAY BOARD (8 DIP RELAYS OR OPEN COLLECTORS)

STEPPER MOTOR CONTROLLER BOARD

RS232 INTERFACE

IEEE 488 INTERFACE

WIRE WRAP PLUG-IN

LED DISPLAY BOARD

Also, there will be available a Mother Board with a wire wrap section replacing the processor and its associated electronics. but including the power supply and the eight slot bus. This would greatly simplify those wanting to build a unique computer. I have used one of these (Called the BB-6000) to provide power and a bus for my SYM-1, giving me a real RS-232 port, more

SYM-PHYSIS 17-15

memory, etc available by using the plug-in's. I am in the process of interfacing one to my Commodore 8032 for the same reasons. I hope to develop interface cards and cables for the SYM-1. Commodore 8032/4032, the Commodore 64, and perhaps the VIC-20.

We have written a small monitor for the SYSTEM-6000, called MONDEC19. It incorporates many control oriented functions, however it is not as powerful as the SYM Monitor. We hope to enhance it in the future (we will be looking for help on that), but we also plan on writing a patch to allow the sym monitor to be used, providing we are successful in our endeavors to acquire rights to do that (we are in the process of negotiating for the SYNNERTEK SYSTEMS). In any case, I think an individual could plug his/her copy of the sym monitor into the SYSTEM-6000 and modity it to have a super sym system.

One last comment. We are interested in finding some competant SYM-1 owners who would like to be BETA test sites for the SYSTEM-6000. They would receive a SYSTEM-6000 in consideration for certain reporting responsibilities to MWM Electronics. Interested parties should write to:

SYSTEM-6000 HWM ELECTRONICS, INC

2555 CLIMBERLAND PARKWAY **BUITE 280**

ATLANTA, GEORGIA 30339

Even if you aren't interested in becomming a BETA sight, write us and we'll put you on our mailing list for future products and/or a possible newsletter.

I'm sorry to hear of SYMPHYSIS ending, but I guess all 8000 things must come to an end sometime, and SYMPHYSIS certainly has been a good thing. Goodby and good luck with your future endeavors. 73.

/Battle

c/o MWM Electronics, Inc

Suite 280

2555 Cumberland Pkwy Atlanta, GA 30339

ASSEMBLE LIST

	0010	.08
0200- OD OA 46		BY SOD SOA 'FORMAT ERROR' SOD SOA
0203- 4F 52 4D	0020 111	IDI TOD TON PORTEN LIMON TOD TON
0206- 41 54 20		
0209- 45 52 52		
020C- 4F 52 0D		
020F- 0A		
0210- OD OA 43	0030 M2	.BY \$0D \$0A 'CHECKBUM ERROR' \$0D \$0A
	0030 HZ	. BY YOU YOU CHECKBON ENRUM YOU YOU
0213- 48 45 43		
0216- 4B 53 55		
0219- 4D 20 45		
021C- 52 52 4F		
021F- 52 0D 0A		
	0040 DUTCHR	.DE \$8A47
	0050 TECHO	.DE \$A653
	OOAO CBUM	DE \$00F2
	OVEC COUNT	AME FOOTA

.DE \$00F3

.DE \$00F4

0070 PBMADH

0080 PGMADL

				0090	ADRL	. DE	\$00F0		
				0100	ADRH	. DE	#00F1		
					INCHR		\$BA1B		
					INBYTE	. DE	\$81D9		
					BEEP		\$8972		
0222-	20	1 0	RΔ		DLOAD		INCHR		
0222	20	70		0150			##3A		CHECK FOR COLON
0225-	E4	2H					DLOAD	•	
0227-				0160			# \$ 00		
0229-				0170			CSUM		
022B-			00						
022E-	DO	F2		0190			DLOAD	_	INPUT NUMBER OF BYTES
0230-		D9	81	0200			INBYTE	ş	THE OF HOUSEN OF BLIES
0233-	AA			0210		TAX			
0234-	FΟ	55		0220	•		FINISH		
0236-	18			0230		CLC			
0237-	6D	F2	00	0240			CSUM		
023A-	8D	F2	00	0250		STA	CSUM		
023D~	20	D9	81	0260		JSR	INBYTE	ŧ	LOAD HIGH ADDRESS BYTE
0240-				0270		STA	ADRH		
0243-				0280		CLC			
0244-			00	0290		ADC	CSUM		
0247-				0300		8TA	CSUM		
024A-				0310			INBYTE		LOAD LOW ADDRESS BYTE
024D-				0320		STA	ADRL	•	
		FU	•	0330		CLC			
0250-			~~				CSUM		
0251-				0340			CSUM		
0254-				0350					LOAD UNUSED BYTE
0257-			81	0360			INBYTE MSG1		CHECK FOR \$00
025A-				0370				,	CHECK I DIT 400
025C-					START		#\$00		
025E-					SAVE		INBYTE		
0261-	91	FO		0400			(ADRL),Y		
0263-	08			0410		PHP			
0264-	18			0420		CLC			
0265-	6D	F2	00	0430		ADC	CSUM		
0268-	8D	F2	00	0440		STA	CSUM		
026B-				0450		PLP			
026C-				0460		INY			
026D-				0470		DEX			
026E-				0480		BNE	SAVE		
0270-				0490			CSUM		TWO'T COMPLEMENT
0273-				0500			##FF	•	., .,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,
				0510		CLC			• • '
0275-							#\$01		
0276-				0520			CSUM		
0278-				0530			INBYTE		LOAD CHECKSUM (CSUM)
0278~					CHECK		CSUM	•	LOND CHECKSON (CSON)
027E-				0550			MS62		
0281-				0560					
0283-				0570			#\$0A		
0285-				0580			OUTCHR		
0288-	40	22	02	0590			DLOAD		
028B-	20	D9	81	0600	FINISH	JSR	INBYTE	ŧ	GET HIGH BYTE OF
028E-	BD	F3	00	0610)	STA	PGMADH		PGM START ADR
0291-	20	D9	81	0620)	JSR	INBYTE	,	GET LOW BYTE OF
0294-	BD	F4	00	0630)	STA	PGMADL		PGM START ADR
0297-				0640		BRK			
0298-			•	-	MSG1	LDY	#\$00		
027A-) L1		MI.Y		
027H-				0670			OUTCHR		
024D-			U H	0680		INY			
02AU-				0690			##10		
						BNE			
02A3-			,	0700		BRK			
02A5-				0710			#\$00		
02A6-					MSG2				
02AB-	89	10	02	0/30	, L2	LDF	M2,Y		SYM-PHYSIS 17-17

.DE #OOFO

ADRI ADRI

02AB- 20 47 BA 02AE- CB 02AF- CO 12 02B1- DO F5 02B3- 00	0740 0750 0760 0770 0780 0790	JSR OUTCH INY CPY #\$12 BNE L2 BRK .EN
--	--	---

USE OF NULL STRING IN RAE

Often we have wished to enter a ".BY" ASCII string with leading spaces. This cannot be entered as .BY 'STRING' (in this example we assume that five leading spaces are desired), since RAE will accept at most one leading space in any ASCII string immediately following the .BY pseudo-op, as in line 20 below, because of the way in which FOrmat is implemented.

We have been getting around this by entering the first space as \$20 or $^{\circ}$, and entering one less leading space than desired in the actual string, as in lines 30 and 40 below.

By rereading (for at least the tenth time!) the manual which came with our MAE for the PET systems (including the COM-64), we discovered that we could use a null string, instead, as in line 50 below.

Incidentally, when Carl Moser lent us a copy of the RAE-1 source code to study, he sent us an annotated copy which he had marked up in red (we are giving up here a golden opportunity to use the word "rubric" in a sentence!) to indicate where he would "upgrade" RAE-1 into a RAE-2 version if Synertek Systems ever so requested. The COM-64 version of MAE incorporate these modifications.

Again, incidentally, for SYMmers going to a COM-64 as their "second" system, MAE actually supports dual 1541 drives, since these are addressable as D8 and D9, instead of by the Ø: and 1: used in so much other PET derived software. This is because MAE was actually designed to support TWO dual drive systems on the PETs!

>FORMAT SET

>ASSEMBLE LIST	ØØ1Ø	.LS	
Ø2ØØ- 2Ø 53 54	0020	.BY STRING	FIVE SPACES ENTERED HERE
Ø2Ø3- 52 49 4E			
Ø2Ø6- 47	26.		
Ø2Ø7- 2Ø 2 Ø 2 Ø	ØØ 3Ø	.BY \$20 '	STRING' ; FOUR SPACES ENTERED HER
Ø2ØA- 2Ø 2Ø 53			
Ø2ØD- 54 52 49			
Ø21Ø- 4E 47			THE PROPERTY OF THE PERSON OF
Ø212- 2Ø 2Ø 2Ø	ØØ4Ø	.BY ' '	STRING' ; FOUR SPACES ENTERED HER
Ø215- 2Ø 2Ø 53			
Ø218- 54 52 49			•
Ø21B- 4E 47			COACES ENTERED HER
#21D- 20 20 20	ØØ5Ø	.BY '' '	STRING' ;FIVE SPACES ENTERED HER
Ø22Ø- 2Ø 2Ø 5 3			
Ø223- 54 52 49			
Ø226- 4E 47			
//0000,0228,022	28		

WARNING NOTICE

If you have entered more than one leading space in the string, your assembly will be different with FO C than with FO S. Here, for your information, is an assembly listing of the very same program as above, but with FO C as the format option. Note that the leading spaces in the string have been assembled into the object code.

```
>FORMAT CLEAR
>ASSEMBLE LIST
                ØØ1Ø
                      .LS
Ø2ØØ~ 2Ø 2Ø 2Ø
                ØØ2Ø .BY '
                                STRING'
                                           FIVE SPACES ENTERED HERE
0203- 20 20 53
Ø2Ø6~ 54 52 49
Ø2Ø9- 4E 47
Ø2ØB- 2Ø 2Ø 2Ø
                ØØ3Ø
                     .BY $2Ø '
                                   STRING' ; FOUR SPACES ENTERED HERE
Ø2ØE- 2Ø 2Ø 53
Ø211- 54 52 49
Ø214- 4E 47
                      .BY ' '
0216- 20 20 20
                0040
                                   STRING' ; FOUR SPACES ENTERED HERE
Ø219- 2Ø 2Ø 53
Ø21C- 54 52 49
Ø21F- 4E 47
Ø221- 2Ø 2Ø 2Ø ØØ5Ø
                     .BY '''
                                   STRING' ; FIVE SPACES ENTERED HERE
Ø224- 2Ø 2Ø 53
Ø227~ 54 52 49
Ø22A- 4E 47
//0000,022C,022C
```

We finally got our first 65002 today. It is an NCR65002A; we specifically indicate the source, NCR, because none of the MOS Technology spec sheets (marked preliminary) we have on hand seem to indicate that their version has the added 27 new instructions and the additional addressing modes of the NCR version. Does anyone have this information on the MOS version?

MORE ON THE 65002

The 65002 may be directly substituted for the 6502 for lower power consumption, but to take full advantage of its extended instruction set an upgraded RAE-1 will be required. Here are some thoughts on the subject from Phil Kohl:

```
9919 : EXTRACTS BY LUX FROM A PROGRAM BY PHIL KOHL
     : File name: RAE2
ØØ3Ø
        Creation date: August 14, 1983
ØØ4Ø
     ; External references deleted: September 3, 1983
0050
     : 65SCØ2 Modifications: October 15, 1983
ØØ6Ø
ØØ7Ø
Ø88Ø
      BB6CA
                 LDA SI.OP.X ;Single byte op codes
ØØ9Ø
                 BNE CHECK CHAR
0100
0110
Ø12Ø
                 LDA RAE.COM.X : RAE commands
Ø13Ø
      BBADØ
                 BNE CHECK. CHAR
Ø14Ø
Ø15Ø
Ø16Ø
Ø17Ø
Ø18Ø
                 .BY ') ' ; Two byte indirect addressing
Ø19Ø
                 .SI IND2
                 .BY $ØØ
9299
Ø21Ø
                 .BY 'A '
                          ;Accumulator addressing
Ø22Ø
                 .SI IMP
                 .BY $ØØ
Ø23Ø
                 .BY ') '
                          ;Three byte indirect addressing
0240
                 .SI IND3
Ø25Ø
Ø26Ø
                 .BY $90
Ø27Ø
                 .BY 'TAX'
Ø28Ø
     S1.0P
                 .BY $AA
Ø29Ø
```

(listing continued to page 17-21, text continued to page 17-23)

SYM-PHYSIS 17-19

A 16-BIT 6502! (AT LONG LAST!)

The extract below, from the Electronic Engineering Times, was sent to us by William Luitje. The clipping on the right, from Sol Libes' BITS & BYTES column in the March 1984 issue of Computers & Electronics, was called to our attention by Dave Wagner.

16-Bit Version of 6502 Announced

Sol Libes in B & P

▶ When Commodore scrapped the 16-bit microprocessor it had been developing for several years in favor of the Zilog Z8000, it left the market wide open for an upward-compatible 16-bit version of the 6502. Sure enough a company has seized the opportunity. Western Design Center Inc., Mesa, AZ, has

announced a 16-bit microprocessor that runs 6502 software in an emulation mode without revision. The CMOS chip can address 16M bytes of memory compared to the 6502's 64K. It has an 8-bit external bus and internal 16-bit bus. The most amazing feature is that it is pin-compatible with the 6502. You just remove the 6502 from its socket and replace it with the W65SC816. Then set the E-bit in the status register and it performs exactly like the 6502. If the bit is off, the device becomes a 16-bit device.

WDC To Market 16-Bit Version Of 6502 μP

By Stan Baker MESA, Ariz. — The biggestselling 8-bit microprocessor, the 6502, will soon have CMOS 16bit family members with 8-bit and 16-bit databus versions.

These parts and several major CMOS peripherals will come from the Western Design Center Inc. (WDC) which developed and owns rights to the CMOS version of the 6502 and its CMOS peripherals.

However, WDC will not license the new 16-bit units for a one-time fee as it has the 8-bit parts. Rather, the design firm has ambitious plans to supply chips for the first time and to provide high-level custom chip design equipment, software and services.

The first chips of the 16-bit version of the 6502 microproces-

sor are due for testing at WDC by the end of January. The first of these CMOS chips, the 65C816, will most likely come from Santa Clara, Calif., where they are being fabricated by American Microdevices Inc. But GTE Microcircuits is also processing the new design in Tempe, Ariz., having bought a license to market the chip. GTE wants to be its first volume producer.

WDC is an IC design operation that has specialized in developing 6502 CMOS parts and licensing them for one-time fees. The n-channel original version has the highest production volume of any 8-bit processor. This is because it is used in many highly successful products, such as Apple computers. Atari games and computers, and Commodore computers. The CMOS 6502 and its CMOS peripherals are now licensed by WDC to Synertek, NCR, Rockwell, Plessey, and Marconi.

[EDITOR'S NOTE: Observe that Commodore is NOT a licensee for the "enhanced" 65CØ2!]

The n-channel 6502 was designed in 1975 at MOS Technology, Valley Forge, Pa., by a group led by William Mensch Jr. Commodore Business Machines bought that firm in 1976 and Mensch left in 1977 for his former home of Phoenix, Ariz., where he had been on the Motorola team that designed the 6800 microprocessor. After spending a short time at Integrated Circuit Engineering Corp., he founded WDC in mid-1978, and is now its president.

Commodore still owns the rights to the n-channel 6502, which is made for the merchant market by Synertek and Rockwell. Commodore now makes it only for in-house use.

Mensch explained that his 20 employees at WDC have designed about 20 chips in the past 18 months and are now embarking on a program to provide 16-bit processors and major new peripherals and to put its design systems and services at customer premises.

In a major change of strategy, the firm will become a chip supplier, rather than a design house, and will not license the designs of its new 16-bit chips. "Western Design Center is going to ship the product, with GTE as second source," Mensch said.

Larger Market Share Sought

GTE Microcircuits is the only licensee of the 65C816 and its 8-bit databus version, the 65C802. Mensch explained, "We are interested in other licensees, but for increasing market share, not just to license people."

He is hoping and expecting to license large systems companies, such as GE, Philips, and IBM, to be their own inhouse alternate sources. Large systems companies could supply themselves and be licensed to use the WDC designs as "super cells" in large chips of their own design, Mensch said.

New Processors

The new 16-bit processors will be in 40-pin packages, with pinouts similar to the 6502. The 8-bit version, 65C802, will be a direct, pin-for-pin replacement for the 65C02. Also, the 65C802 will use the same chip as the 65C816. Only the pinouts will be different.

Mensch noted that the new 8bit unit will emulate the current 6502 without a noticeable change in performance. But it can implement many new capabilities in the old socket, if the customer wishes.

The new processors will have 96 instructions, compared to 56 for the 6502, and 24 addressing modes, while the 6502 has 13. The 24 address bits of the new units will be multiplexed.

In one phase, all 24 address bits will be presented, with eight of them on data lines. In the next phase, the data lines will pass data only.

Shrinking CMOS Process

A critical part of this program is shrinking from the 3micron CMOS process currently used for the new processors, to a 1.5-micron process now in development at GTE Microcircuits. The current process will yield 8-MHz to 10-MHz clockrate parts, with a minimum of 4 MHz, Mensch said. The objective for the 1.5-micron process is not only to reduce the chip size, but to produce a full family of 20-MHz parts.

Mensch is now studying the feasibility of WDC having its own fab facility, based on the 1.5-micron CMOS process. However, he has not made a commitment to a fab facility yet.

Eectronic Engineering Times

Monday, January 9, 1984

				1	
LISTING	(continued from page 17-19)			•	
Ø3ØØ	.BY 'TAY'	0940	.BY \$30	1579	.BY 'LDX'
Ø31Ø	.BY \$AB	Ø95Ø	.BY 'BNE'	1580	.BY \$A5 \$A2
Ø32Ø	.BY 'TSX'	Ø96Ø	.BY \$DØ	159Ø	.BY \$AE \$BE \$A6 \$B6 \$A2
ø33ø	.BY \$BA	Ø97Ø	.BY 'BPL'	1600	.BY 'LDY'
Ø34Ø	.BY 'TXA'	Ø98Ø	.BY \$10	1610	.BY \$C5 \$C2
Ø35Ø	.BY \$BA	0990	.BY *50	162 0 163 0	.BY \$AC \$BC \$A4 \$B4 \$AØ
Ø36Ø	.BY 'TXS'	1000	.BY 'BVS'	1640	
Ø37Ø	.BY \$9A .BY 'TYA'	1010 1020	.BY \$70	1650	.BY 'LSR'
Ø38Ø	.BY \$98	1030	BY 'BRA'	1660	.BY \$C4 \$C1
Ø39Ø	.BY 'CLC'	1040	.BY \$8Ø	1670	.BY \$4E \$5E \$46 \$56 \$4A
Ø4ØØ	.BY \$18	1050	.BY \$00	1689	
Ø41Ø Ø42Ø	BY 'CLD'	1969		169Ø	.BY 'SR' 3 from previous byte
Ø43Ø	.BY \$DB	1070 MU.OP	.BY 'ADC'	1700	.BY \$81 \$00
0440	.BY 'CLI'	1989	.BY \$F9 \$DA	1719	.BY \$20
Ø45Ø	.BY \$58	1070	.BY \$6D \$7D \$79 \$72 \$65 \$75 \$71 \$61 \$69	1720	
Ø46Ø	.BY 'CLV'	1100		1730	BY 'ORA'
Ø47Ø	.BY \$B8	1110	.BY 'AND'	1740	.BY \$F7 \$DA .BY \$ØD \$1D \$17 \$12 \$Ø5 \$15 \$11 \$Ø1 \$Ø9
Ø48Ø	.BY 'SEC'	1120	.BY \$F9 \$DA .BY \$2D \$3D \$39 \$32 \$25 \$35 \$31 \$21 \$29	175Ø	"Bi #80 #10 #14 #15 #80 #19 #11 #21
Ø49Ø	.BY \$38	1130	"BA #5D #2D #24 #25 #52 #27 #21 451 451	1766	.BY 'ROL'
Ø5ØØ	.BY 'SED'	1140	.BY 'ASL'	1770	.BY \$C5 \$C1
Ø51Ø	.BY \$F8	1150	.BY \$C5 \$C1	178Ø 179Ø	.BY \$2E \$3E \$26 \$36 \$2A
Ø52Ø	.BY 'SEI' .BY \$78	116Ø 117Ø	.BY \$ØE \$1E \$Ø6 \$16 \$ØA	1800	
Ø53Ø Ø54Ø	.BY 'NOP'	1180		1810	.BY 'SBC'
Ø55Ø	.BY \$EA	1190	.BY 'BIT'	1820	.RY \$F9 \$DA
Ø56Ø	.BY 'RTI'	1200	.BY \$C5 \$C2	1830	BY \$ED \$FD \$F9 \$F2 \$E5 \$F5 \$F1 \$E1 \$E9
Ø57Ø	.BY \$4Ø	1216	.BY \$2C \$3C \$24 \$34 \$89	1840	
Ø58Ø	.BY 'RTS'	1220		185Ø	.BY 'ROR'
Ø59Ø	.BY \$6 Ø	1230	.BY 'CMP'	1869	.BY \$C5 \$C1
Ø6ØØ	.BY 'DEX'	1240	.BY \$F9 \$DA	1870	.BY \$6E \$7E \$66 \$76 \$6A
Ø61Ø	.BY \$CA	1250	.BY \$CD \$DD \$D9 \$D2 \$C5 \$D5 \$D1 \$C1 \$C9	188Ø 189Ø	.BY 'STA'
Ø62Ø	.BY 'DEY'	1260	.BY 'CPX'	1900	.BY \$F8 \$D8
Ø63Ø	.BY \$88	1270	BY \$83 \$82	1910	BY \$8D \$9D \$99 \$92 \$85 \$95 \$91 \$81
Ø64Ø	.BY 'INX' .BY \$E8	128Ø 129Ø	.BY \$EC \$E4 \$EØ	1920	
Ø65Ø Ø66Ø	.BY 'INY'	1300	101 720 121 121	1930	.BY 'STX'
Ø67Ø	.BY \$C8	1310	.BY 'CPY'	1940	_BY \$83 \$AØ
Ø68Ø	.BY 'PHA'	1320	.BY \$83 \$82	195Ø	.BY \$8E \$86 \$96
Ø69Ø	.BY \$48	133Ø	.BY \$CC \$C4 \$CØ	1969	
Ø7 Ø Ø	.BY 'PHP'	134Ø	*	197Ø	.BY 'STY'
Ø71Ø	.BY \$Ø8	135Ø	.BY 'DEC'	198ø	.BY \$83 \$CØ
Ø72Ø	.BY 'PLA'	1360	.BY \$C5 \$C1	1990	.BY \$8C \$84 \$94
Ø73Ø	.BY \$68	137Ø	BY \$CE \$DE \$C6 \$D6 \$3A	2000	.BY 'STZ'
Ø74Ø	"BY 'PLP'	1380	TV 2EOD?	2010	.BY \$C4 \$CØ
Ø75Ø	.BY \$28	1390	.BY 'EOR'	2020 2030	.BY \$9C \$9E \$64 \$74
Ø76Ø	.BY 'PHY'	1400	.BY \$4D \$5D \$59 \$52 \$45 \$55 \$51 \$41 \$49	2040	191 475 472 421 VV
Ø77Ø	.BY \$5A .BY 'PLY'	141 <i>0</i> 1420	.D1 440 400 407 402 470 100 100	2050	.BY 'TRB'
Ø78Ø Ø79Ø	.BY \$7A	1430	.BY 'INC'	2060	.BY \$82 \$8Ø
Ø8ØØ	.BY 'PHX'	1440	.BY \$C5 \$C1	2070	.BY \$1C \$14
Ø81Ø	.BY \$DA	145Ø	.BY \$EE \$FE \$E6 \$F6 \$1A	2080	
Ø82Ø	.BY 'PLX'	1460		2090	.BY 'TSB'
Ø83Ø	.BY \$FA	1470	.BY 'JMP'	2100	.BY \$82 \$80
Ø84Ø	.BY 'BRK'	148Ø	.BY \$93 \$08	2110	.BY \$ØC \$Ø4
Ø85Ø	.BY \$ØØ	149Ø	BY \$4C \$6C \$7C	2120	DV 4/4/4
Ø86Ø	.BY \$ØØ	1500		2130	.BY \$90
Ø87Ø	.BY 'BCC'	1510	.BY \$ØØ	2140	.CT RAE3
Ø88Ø	.BY \$90	1520	.BY 'LDA'	215Ø	101 THEO
Ø89Ø Ø9ØØ	.BY 'BCS' .BY \$BØ	1530 MU.OP2	BY \$F9 \$DA	Not-	that operator DEA \$3A and
9919	.BY 'BEQ'	154Ø 155Ø	BY \$AD \$BD \$B9 \$B2 \$A5 \$B5 \$B1 \$A1 \$A9		that opcodes DEA, \$3A, and \$1A, are not considered in
Ø92Ø	.BY \$FØ	1560			nove tables
Ø93Ø	.BY 'BMI'	I GAN.	SYM-PHYSIS 17-21	Cité M	SYM-PHYSIS 17-22

What is the above listing all about? Well, it is a portion of the "source code" for an "unoffical RAE-2", sent us by Phil Kohl. As you can see by the "non-mnemonic" labels in lines 3070 and 90130, Phil has disassembled Carl Moser's RAE-1, analyzed and commented it, and then extended it to include the new op-codes for the 65SC02 (apparently an alternate name for the non-CBM 65092). For copyright reasons we cannot make available his source code in its entirety, but we publish the portion above to give those among you who wish to do the same a head start, by showing how and where additional op-codes may be added to RAF-1.

In addition to the 65C02/65SC02, a 65C002 with 95 instructions and 24 addressing modes can be used in place of the 6502 (see the clippings on page 17-20), and some of you will, no doubt want to extend RAE to accompdate that and the 16 bit version, the 65C816, as well. We firmly approve of the type of reverse engineering and modification (for personal use and for limited distribution for non profit research purposes) which is exemplified by Phil's work. Note that, wherever practical. SYM-PHYSIS has always published, and the SYM Users' Broup has always distributed, fully commented source code to save you the time and trouble of disassembly, and to encourage "customization", and to enhance your system understanding.

For those who wish to know more about the new "16-bitter", we reprint the following paragraphs from the February 1984 Issue of the IEEE Philadelphia Section Newsletter, "Update", which we receive thanks to the courtesy of George Bodenstein:

W65SC802 and W65SC816 Microprocessors. These 16-bit microprocessors are CMOS devices designed to replace the 6500 8-bit microcomputer family. They operated in two modes, 6502 emulation and native. They start-up in the 6502 mode so that they can be used to replace the 6502 in any system without having to change software. The 65802 will fit in the same socket as the 6502 and requires NO HARDWARE changes. The 65816 requires moderate hardware changes to fit in a 6502 system. The 65802 and 65816 operating the native mode will execute programs up to 3.5 times faster than the 6502. In the native mode the processors execute all the orginal 56 NMOS and 10 new CMOS 6502 instructions on 8 and 16 bit data. All registers can either be 8 or 16 bit wide. The processors also execute 30 new instructions which include block moves, coprocessor and system control instructions: They have 11 new addressing modes including long branches, program and stack relative. The 65816 can address up to 16 Megabytes of memory in either a linear or segmented mode. These two products, a floating point coprocessor, and operating system will be the subjects of the March Update meeting.

W65SC02 CMOS Microprocessor. Hardware and software compatible with the NMOS 6502. They have 10 new instructions and two new addressing modes. Low power operation.

W65SC21 Peripheral Interface Adapter. Direct replacement for the NMOS 6521 or 6821 PIAs. Low power operation.

W65SC22 Versatile Interface Adapter. Direct low powered replacement for the 6522 VIA.

For additional information, contact: The Western Design Center, Inc., 2166 East Brown Road, Mesa, AZ 85203, (602) 962-4545

SYM-PHYSIS 17-23

50

*>!

2CØ3- A9 3Ø

2CØ8- A9 D6

MORE RAE ENHANCEMENTS

John Mattox sent us a three page listing of a program which "allows RAE to produce and capture files via modem". Since the listing was not easily reproducible, we asked John to send us the program on cassette. He sent us, instead, a cassette containing the much longer program listed below. While such a program would normally be too long for SYM-PHYSIS, we make an exception in this case. As you know, the power of RAE is what attracted us to SYM in the first palce, and any enhancements to RAE are well worth disseminating.

We have not been able to fully test the program because it breaks our disk and printer links, but we have tested several sections, including the "menu" portion, and we feel that it is definitely worth studying and extracting ideas from. Note too, his links to SWP!

The listing is published exactly as submitted, with no editing on our part to compress the output lines to the 80 character printer limit. We omitted this customary editing step because the listing would have "spilled over" onto a second line in so many places anyway, because of the way John entered his line feeds directly into the .by statements before the final """, rather than externally, as a 15 (or \$5A) following the final "'". This may "louse up" the listing, but it does save keystrokes!

Contact John directly for cassette copies (his address appears in lines 8020 and 0740). Have fun with this one! >PASS2

```
9919 ;A program to extend RAE, written by John Mattox
                0020 ;331 Nova Lane, Menlo Park, CA 94025.
                9939 | The program provides supporting commands accessed by esc.
                9949 ;Lines sensitive to relocaton are indicated with *>! .
                9050 My machine uses tape for storage. To free the zero page di
                0060 (vectors, one can use one zero page vector for the indirect
                9979 ;addressing done in this program, storing the vectors
               0000 jin non zero page ram.
               9999 SWD
                                .de $3736 Beginning of SWP. *>!
               Ø1ØØ techo
                                .de $a653
               Ø110 param
                                .de $a64a
               Ø12Ø inbyte
                                .de $81d9
               Ø13Ø outchr
                                .de $8a47
                                .de $8a58
               Ø14Ø-intchr
                                .de $f4
               Ø15Ø LFflg
                                             :Inhibit LF if not zero
                                .de $f5
               Ø16Ø SPflq
                                             #Add space before CR if not zero
               Ø17Ø chrindex
                                .de $ec index for text output
               Ø18Ø outputdex
                               .de $fØ
               Ø19Ø inputdex
                                .DE $66CA WORKING INDEX
               Ø2ØØ putdex
                                .de $f2
                Ø21Ø predex
                                .de $f6
                Ø22Ø symb
                                .de $e8
               0230 nuprs
                                .de $cc
                Ø24Ø min
                                .de $280 Beginning of buffer for input. *>!
                Ø250 max
                                .de $2fff Maximum value of buffer for input #>!
                Ø26Ø sdbyt
                                .de $a651
                Ø27Ø begin
                                .de $2c00 Address for beginning of prom. *>!
                9289 ram
                                .de $2b00 Beginning of phrase storage ram block.
                Ø29Ø
                                .ba begin
                Ø3ØØ :.os
               0310 initialize jsr $8686 access
2CØØ- 2Ø 86 8B
               Ø32Ø
                                lda #h.outchr@
2CØ5- 8D 65 A6
                                sta $a665
               Ø33Ø
               0340
                                lda #1.outchr@
                                                              SYM-PHYSIS 17-24
```

```
2CØA- 8D 64 A6
                                                                                      2CA7- 2Ø 41 64
                0350
                                 sta $a664
2CØD- A9 2E
                Ø36Ø
                                 lda #h.intchr@
                                                                                      2CAA- 6A 75 73
2CØF- BD 62 A6
                                 sta $a662
                                                                                      2CAD- 74 20 6F
                Ø37Ø
                                                                                      2CBØ- 75 74 7Ø
2C12- A9 ØD
                                 lda #1,intchr@
                Ø38Ø
                                                                                      2CB3- 75 74 ØA
2C14- 8D 61 A6
                Ø39Ø
                                 sta $a661
                                                                                      2CB6- ØD
2C17- A9 ØØ
                0400
                                 lda #00
                                                                                      2CB7- 65 73 63
                                                                                                                        .by 'esc s -
                                                                                                                                      Output text with SWP
2C19- 85 F4
                Ø41Ø
                                 sta *LFflg
2C1B- 85 F5
                                                                                      ' 13
                0420
                                 sta *SPflg
2C1D- 85 CC
                                                                                      2CBA- 20 73 20
                9439
                                 sta *nuprs
2C1F- A9 2D
                                                                                      2CBD- 20 2D 20
                                 lda #chr?
                0440
2C21- 85 EC
                                                                                      2CCØ- 2Ø 4F 75
                Ø45Ø
                                 sta *chrindex
                                                                                      2CC3- 74 7Ø 75
2C23- A9 2C
                Ø46Ø
                                 lda #h.chr?
                                                                                      2006- 74 20 74
2C25- 85 ED
                Ø47Ø
                                 sta *chrindex+1
                                                                                      2CC9- 65 78 74
2C27- 2Ø FB 3Ø
                Ø48Ø
                                 jsr outputchr
                                                                                      2CCC~ 2Ø 77 69
2C2A- A9 ØD
                                lda #13
                Ø49Ø
                                                                                      2CCF- 74 68 2Ø
2C2C- 6Ø
                Ø5ØØ
                                rts
                                                                                      2CD2- 53 57 5Ø
                                 .by 'Welcome to the world of the RAE escape func
2C2D- 57 65 6C
                Ø51Ø chr?
                                                                                      2CD5~ ØA ØD
tion.
                                                                                                                       .by 'esc b - Reset baud rate
                                                                                      2CD7- 65 73 63
                                                                                                      · Ø63Ø
' 13
                                                                                      ' 13
2C3Ø- 63 6F 6D
                                                                                      2CDA- 20 62 20
2C33- 65 2Ø 74
                                                                                      2CDD- 20 2D 20
2C36- 6F 2Ø 74
                                                                                      2CEØ- 2Ø 52 65
2039- 68 65 20
                                                                                      2CE3- 73 65 74
2C3C- 77 6F 72
                                                                                      2CE6- 20 62 61
2C3F- 6C 64 2Ø
                                                                                      2CE9- 75 64 2Ø
2C42- 6F 66 2Ø
                                                                                      2CEC- 72 61 74
2C45- 74 68 65
                                                                                      2CEF- 65 ØA ØD
2C48- 2Ø 52 41
                                                                                                                        .by 'esc i - Input into buffer
                                                                                      2CF2- 65 73 63
                                                                                                      0640
2C4B- 45 2Ø 65
                                                                                      13
2C4E- 73 63 61
                                                                                      2CF5- 20 69 20
2C51- 7Ø 65 2Ø
                                                                                      2CF8- 2Ø 2D 2Ø
2C54- 66 75 6E
                                                                                      2CFB- 2Ø 49 6E
2057- 63 74 69
                                                                                      2CFE- 7Ø 75 74
2C5A- 6F 6E 2E
                                                                                      2DØ1- 2Ø 69 6E
2C5D- ØA ØD
                                                                                      2DØ4- 74 6F 2Ø
2C5F- 65 73 63 Ø52Ø
                                 .by 'esc ? - Print menu
                                                                                      2DØ7- 62 75 66
' 13 $ff
                                                                                      2DØA- 66 65 72
2C62- 2Ø 3F 2Ø
                                                                                      2DØD- ØA ØD
2C65- 2Ø 2D 2Ø
                                                                                      2DØF- 65 73 63
                                                                                                                       .by 'esc d - Define symbol
2068- 20 50 72
                                                                                      13
2C6B- 69 6E 74
                                                                                      2D12- 2Ø 64 2Ø
2C6E- 2Ø 6D 65
                                                                                      2D15- 2D 2Ø 44
2C71- 6E 75 ØA
                                                                                      2D18- 65 66 69
2C74- ØD FF
                                                                                      2D1B- 6E 65 2Ø
2C76- A9 84
                Ø53Ø menu
                                 lda #chr^
                                                                                      2D1E- 73 79 6D
2C78- 85 EC
                0540
                                 sta *chrindex
                                                                                      2D21- 62 6F 6C
2C7A- A9 2C
                Ø55Ø
                                 lda #h.chr^
                                                                                      2D24- ØA ØD
2C7C- 85 ED
                Ø56Ø
                                 sta *chrindex+1
                                                                                                       0660 ;User enter symbol and phrase into ram block.
2C7E- 2Ø F8 3Ø
                Ø57Ø
                                 isr outputchr
                                                                                                                       .by 'esc esc # - Produce text for symbol #
                                                                                      2D26- 65 73 63
                                                                                                      Ø67Ø
2C81- A9 ØD
                Ø58Ø
                                 lda #13
                                                                                      1.3
2083- 69
                Ø59Ø
                                 rts
                                                                                      2D29- 2Ø 65 73
2C84- 65 73 63
                                 .by 'esc c - RAE cold start
                0600 chr^
                                                                                      2D2C- 63 20 23
' 13
                                                                                      2D2F- 2Ø 2D 2Ø
2087- 20 63 20
                                                                                      2D32- 5Ø 72 6F
2C8A- 2Ø 2D 2Ø
                                                                                      2D35~ 64 75 63
2C8D- 2Ø 52 41
                                                                                      2D38- 65 2Ø 74
2099- 45 20 63
                                                                                      2D3B- 65 78 74
2C93- 6F 6C 64
                                                                                      2D3E- 2Ø 66 6F
2096- 20 73 74
                                                                                      2D41- 72 2Ø 73
2099- 61 72 74
                                                                                      2D44- 79 6D 62
2090- ØA ØD
                                                                                      2D47- 6F 6C 2Ø
2C9E- 65 73 63 Ø61Ø
                                 .by 'esc a - Adjust output
                                                                                      2D4A- 23 ØA ØD
' 13
                                                                                                       0680 ; First searches prom(assembled) block and then ram block.
2CA1- 2Ø 61 2Ø
                                                                                      2D4D- 65 73 63
                                                                                                                       .by 'esc q - delete a symbol
                                                                                                     Ø69Ø
2CA4- 2Ø 2D 2Ø
                                                             SYM-PHYSIS 17-25
                                                                                      ' 13
                                                                                                                                                    SYM-PHYSIS 17-26
```

2D5Ø- 2Ø 71 2Ø			2	DFB- 33 FF				
			4	DEB- 33 II			4-4	-
2D53- 2D 2Ø 64			_				statements for Sk	
2D56- 65 6C 65				DFD- 70 2E 6)	.by 'p.m Ø 73 1000	3" \$11
2D59- 74 65 2Ø			2	EØØ- 2Ø 3Ø 2	Ø			
2D5C- 61 20 73			21	EØ3- 37 33 2	ø			
2D5F- 79 6D 62			2	EØ6- 31 3Ø 3	ø			
				EØ9- 3Ø 2Ø 3				
2D62-6F6C ØA					3			
2D65- ØD				EØC- FF				
2D66- 65 73 63	Ø7ØØ .by	'esc p - print symbols and text	2:	EØD- 2Ø 58 8	A Ø78Ø	intchr@	jsr intchr	
' 13			2	E10- 29 7F	Ø79Ø		and #\$7f	
2D69- 2Ø 7Ø 2Ø			2	E12- C9 1B	Ø8ØØ		cmp #\$1b ?escape	
				E14- FØ Ø1	Ø81Ø		beg escape	
2D6C- 2D 20 70								
2D6F- 72 69 6E				E16- 6Ø	Ø82Ø		rts	
2D72- 74 20 73				E17- 20 58 8		escape	jsr intchr	
2D75- 79 6D 62			2	E1A- 29 7F	Ø84Ø	i	and #\$7f	
2D78- 6F 6C 73			2	E1C- C9 63	Ø85Ø		cmp #'c	
2D7B- 2Ø 61 6E			21	E1E- FØ 36	Ø86Ø	,	beg alpha	
				E2Ø- C9 61	Ø87Ø		cmp #'a	
2D7E- 64 20 74				E22- FØ 35			. •	
2D81- 65 78 74					Ø88Ø		ped gamma	
2D84- ØA ØD				E24- C9 73	Ø892		cmp #'s	
2D86- 65 73 63	Ø71Ø .by	'esc e - Echo input buffer to RAE	-	E26- FØ 2B	Ø7ØØ		bed sb	
' 13 \$ff			2	E28- C9 62	9 910		cmp #'b	
2D89- 2Ø 65 2Ø			21	E2A- FØ 36	Ø 92Ø		beq baud	
2D8C- 2Ø 2D 2Ø			2	E2C- C9 69	Ø93Ø		cmp #'i	• 1
2D8F- 2Ø 45 63				E2E- FØ 2C	9949		beg epsilon	. 1
				E3Ø- C9 65	Ø95Ø		cmp #'e	
2D92- 68 6F 2Ø							•	
2D95- 69 6E 7Ø				E32- FØ 13	Ø96Ø		beq lamda	
2D98- 75 74 20				E34- C9 71	Ø9 7Ø		cwb #,d	
2D9B- 62 75 66			21	E36- FØ 12	Ø78Ø		beq quit	
2D9E~ 66 65 72			2:	E38- C9 64	Ø99Ø		cmp #'d	
2DA1- 20 74 6F			2	E3A- FØ 11	1999		beg define	
2DA4- 2Ø 52 41				E3C- C9 1B	1010		cmp #\$1b ?escape	
				E3E- FØ 1Ø	1020		beg dbl.esc	
2DA7- 45 ØA ØD								
2DAA- FF				E4Ø- C9 7Ø	1939		CWD #,b	
	Ø72Ø ;Storage table	for prom symbols and text		E42- FØ 1B	1949		beq print	
		t-1 than shears than 4ff	2	CAA AC 76 7				
	Ø73Ø ;format is sym	DOI, then piirase, then arr		E44- 4C 76 2	C 1Ø5Ø		jmp menu	
2DAB- 71 4A 6F	9730 ;format is symi			E47- 4C 9E 3		lamda	jmp menu jmp echo	
2DAB- 71 4A 6F	Ø74Ø prom .by	oot, then purase, then *** 'qJohn Mattox' \$ff 'w331 Nova Lane,	Menlo Pa 2		Ø 1 <i>0</i> 69			
rk, CA 94 025' \$	Ø74Ø prom .by		Henlo Pa 2	E47- 4C 9E 3 E4A- 4C AØ 3	Ø 1 <i>0</i> 60 1 1 <i>0</i> 70	lamda quit	jmp echo jmp Quit	
rk, CA 94025'\$ 2DAE- 68 6E 20	Ø74Ø prom .by		Henlo Pa 2:	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3	Ø 1960 1 1970 1 1980	lamda quit define	jmp echo jmp Quit jmp Define	
rk, CA 94025'\$ 2DAE- 68 6E 20 2DB1- 4D 61 74	Ø74Ø prom .by		Henle Pa 2 2 2 2 2 2	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E5Ø- 4C ØD 3	Ø 1060 1 1070 1 1080 1 1090	lamda quit define dbl.esc	jmp echo jmp Quit jmp Define jmp Dbl.esc	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78	Ø74Ø prom .by		Menio Pa 2 2 2 2 2 2 2 2	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E5Ø- 4C ØD 3 E53- 4C 36 3	Ø 1060 1 1070 1 1080 1 1090 7 1100	lamda quit define dbl.esc	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp	
rk, CA 94025'\$ 2DAE- 68 6E 20 2DB1- 4D 61 74	Ø74Ø prom .by		Henlo Pa 2 2 2 2 2 2 2 2 2 2 2	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E5Ø- 4C ØD 3 E53- 4C 36 3 E56- 4C 9E 2	Ø 1060 1 1070 1 1080 1 1090 7 1100 F 1110	lamda quit define dbl.esc sp alpha	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78	Ø74Ø prom .by		Henlo Pa 22 22 22 23 24 25 26 27 27 27 27	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E5Ø- 4C ØD 3 E53- 4C 36 3 E56- 4C 9E 2 E59- 4C C9 2	Ø 1060 1 1070 1 1080 1 1090 7 1100 F 1110 E 1120	lamda quit define dbl.esc sp alpha gamma	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33	Ø74Ø prom .by		Henlo Pa 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E5Ø- 4C ØD 3 E53- 4C 36 3 E56- 4C 9E 2 E59- 4C C9 2 E5C- 4C 63 3	Ø 1060 1 1070 1 1080 1 1090 7 1100 F 1110 E 1120 0 1130	lamda quit define dbl.esc sp salpha gamma epsilon	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76	Ø74Ø prom .by		Henlo Pa 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E5Ø- 4C ØD 3 E53- 4C 36 3 E56- 4C 9E 2 E59- 4C C9 2	Ø 1060 1 1070 1 1080 1 1090 7 1100 F 1110 E 1120 0 1130	lamda quit define dbl.esc sp alpha gamma	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E5Ø- 4C ØD 3 E53- 4C 36 3 E56- 4C 9E 2 E59- 4C C9 2 E5C- 4C 63 3	Ø 1060 1 1070 1 1080 1 1097 7 1109 F 1110 E 1120 Ø 1130 2 1140	lamda quit define dbl.esc sp alpha gamma epsilon print	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 23 24 22 22 22 22 22 22 22 23 24 24 25 26 26 27 27 28 28 28 28 28 28 28 28 28 28 28 28 28	E47- 4C 9E 3 E4A- 4C AØ 3 E50- 4C ØD 3 E53- 4C 36 3 E56- 4C 9E 2 E59- 4C C9 2 E55- 4C 63 3 E55- 4C 14 3 E62- A9 8E	Ø 1969 1 1979 1 1989 1 1997 7 1199 F 1119 E 1129 Ø 1139 2 1149	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr]	•
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D	Ø74Ø prom .by		Henlo Pa 22 22 22 23 24 24 25 26 27 27 28 28 28 29 29 20 20 20 20 21 21 22 22 22 23 24 26 26 27 27 28 28 29 29 29 29 29 29 29 29 29 29 29 29 29	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E59- 4C ØD 3 E53- 4C 9E 2 E59- 4C C9 2 E55- 4C 63 3 E55- 4C 63 3 E62- A9 8E E64- 85 EC	Ø 1969 1 1979 1 1989 1 1979 7 1199 F 1119 6 1139 2 1149 1159	lamda quit define define sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chrl sta *chrindex	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E50- 4C ØD 3 E53- 4C 36 3 E53- 4C 9E 2 E59- 4C C9 2 E55- 4C 63 3 E55- 4C 14 3 E62- A9 8E E64- 85 EC E66- A9 2E	9 1969 1 1979 1 1989 1 1999 7 1109 F 1119 6 1129 9 1139 2 1149 1150 1160	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr]	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E50- 4C ØD 3 E55- 4C 9E 2 E59- 4C 9E 2 E59- 4C 9E 2 E55- 4C 43 3 E5F- 4C 14 3 E62- A9 BE E66- A9 2E E68- B5 ED	Ø 1969 1 1079 1 1080 1 10970 7 1100 F 1110 E 1120 Ø 1130 2 1140 1150 1150 1170	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex ta *chrindex+1	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E54D- 4C 36 3 E55- 4C 36 3 E55- 4C 63 3 E55- 4C 63 3 E55- 4C 14 3 E62- A9 8E E64- 85 ED E66- A9 EE	Ø 1969 1 1079 1 1089 1 10979 7 1109 F 1110 E 1129 Ø 1139 2 1149 1150 1170 1180	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E59- 4C 0D 3 E55- 4C 9E 2 E59- 4C 63 3 E55- 4C 14 3 E62- A9 8E E64- 85 EC E66- A9 2E E68- 85 EC E66- 2Ø F8 3 E60- 2Ø 58 8	Ø 1969 1 1079 1 1089 1 1079 1 1109 F 1110 E 1120 Ø 1139 2 1140 1150 1170 1170	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex ta *chrindex+1	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E54D- 4C 36 3 E55- 4C 36 3 E55- 4C 63 3 E55- 4C 63 3 E55- 4C 14 3 E62- A9 8E E64- 85 ED E66- A9 EE	Ø 1969 1 1079 1 1089 1 10979 7 1109 F 1110 E 1129 Ø 1139 2 1149 1150 1170 1180	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC7- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4D- 4C 36 3 E59- 4C 0D 3 E55- 4C 9E 2 E59- 4C 63 3 E55- 4C 14 3 E62- A9 8E E64- 85 EC E66- A9 2E E68- 85 EC E66- 2Ø F8 3 E60- 2Ø 58 8	Ø 1968 1 1078 1 1088 7 1108 7 1109 7 1110 6 1113 2 1148 1150 1168 1170 A 1208	lamda quit define dbl.esc sp alpha agamma gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Define jmp befine jmp swp jmp cold jmp alter jmp input jmp Print lda #chrl sta *chrindex lda #h,chrl sta *chrindex+1 jsr outputchr jsr intchr	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 45 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC7- 65 6E 6C 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DD8- 34 30 32	Ø74Ø prom .by		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØD 3 E55- 4C 9E 2 E59- 4C C9 2 E55- 4C 14 3 E62- A9 BE E64- 85 EC E66- A9 2E E68- 85 ED E6A- 2Ø F8 3 E79- C9 B1 E72- DØ Ø5	Ø 1968 1 1978 1 1988 1 1998 7 1198 7 1118 Ø 1138 2 1148 1150 1118 Ø 1178 A 1208 1218	lamda quit define dbl.esc sp alpha gamma gensma epsilon print baud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda *chr] sta *chrindex lda *h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DD8- 34 30 32 2DDB- 35 FF	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E54D- 4C 36 3 E55- 4C 36 3 E55- 4C 63 3 E55- 4C 14 3 E62- A9 8E E64- 85 EC E66- A9 EE E66- A9 EE E66- A9 EE E66- B5 ED E66- B5 ED E67- C9 B1 E77- DØ Ø5 E74- A9 4C	Ø 1968 1 1978 1 1988 7 1198 7 1198 6 1138 2 1148 1158 1158 8 1178 8 1288 1218 1228 1238	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda *chrindex lda *chrindex lda *h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$bl bne two lda #\$4c	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD8- 34 30 32 2DD8- 35 FF 2DDD- 75 2E 6D	Ø74Ø prom .by ff		Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØD 3 E55- 4C 9E 2 E59- 4C 63 3 E55- 4C 14 3 E62- A9 8E E64- 85 EC E66- A9 EE E66- A9 EE E66- B5 ED E66- B5 ED E6A- 2Ø F8 3 E6D- 2Ø 58 8 E70- C9 81 E72- DØ Ø5 E74- A9 4C E74- A9 4C	Ø 1968 1 1978 1 1988 7 1198 7 1198 6 1118 8 1158 1158 1158 1178 Ø 1218 Ø 1228 E 1248	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Define jmp Define jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DD8- 34 30 32 2DD8- 35 FF 2DDD- 75 2E 6D	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henle Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E55- 4C Ø 3 E55- 4C 9E 2 E55- 4C 63 3 E55- 4C 14 3 E55- 4C 14 3 E62- A9 BE E64- 85 EC E66- A9 2E E6A- 2Ø F8 3 E70- C9 B1 E72- DØ Ø5 E74- AP 8B 2 E74- AP 8B 2 E74- C9 B2	Ø 1068 1 1078 1 1098 1 1099 7 1109 7 1119 6 1119 0 1150 1170 1170 1170 0 1210 1220 1230 E 1250	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda *chr] sta *chrindex lda *th,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp *th bne two lda **4c jmp setbaud cmp **b2	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD8- 34 30 32 2DD8- 35 FF 2DDD- 75 2E 6D	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E5A- 4C AØ 3 E55- 4C ØD 3 E55- 4C 63 3 E55- 4C 14 3 E55- 4C 14 3 E62- A9 BE E64- 85 ED E6A- 2Ø F8 3 E6A- 2Ø F8 3 E7A- A9 4C E7A- 4C 88 2 E7A- A9 4C E7A- 4C 88 2 E7A- A9 4C E7A- 4C 88 2 E7A- A9 6C	Ø 1968 1 1978 1 1988 1 1998 7 1198 6 1118 Ø 1150 1150 1170 1188 Ø 1298 1228 1238 E 1248	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DD8- 34 30 32 2DD8- 35 FF 2DDD- 75 2E 6D	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØB 3 E59- 4C 9E 2 E59- 4C 63 3 E56- 4C 14 3 E62- A9 8E E64- 85 EC E66- A9 EE E66- A9 EE E66- B5 ED E66- 2Ø 58 E E6A- 2Ø 58 E E79- C9 B1 E72- DØ Ø5 E74- A9 4C E76- 4C 88 E E79- C9 B2 E78- DØ Ø5 E79- C9 B5 E79- C9 B5 E79- C9 B7 E79- C9 B7 E77- A9 10	Ø 1060 1 1070 1 1070 7 1100 7 1100 7 1110 6 1120 1150 1150 1170 1160 1170 1170 1180 0 1200 1210 1220 1230 E 1240 1250 1270	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda %chr] sta *chrindex lda %h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$10	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DD8- 34 30 32 2DD8- 35 FF 2DDD- 75 2E 6D ' \$ff 2DE0- 20 30 20 2DE3- 37 33 FF	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henle Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØD 3 E55- 4C G 3 E55- 4C 14 3 E62- A9 8E E64- 85 ED E66- A9 EE E66- A9 EE E66- A9 EE E66- B5 ED E66- B9 EB E79- C9 B1 E79- C9 B2 E79- C9 B2 E78- DØ Ø5 E77- AC B8 2 E77- AC B8 2	Ø 1060 1 1070 1 1080 7 1100 7 1100 7 1110 8 1130 2 1140 1150 1150 1160 1170 0 1210 1220 1220 1250 1250 1260 1260	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Define jmp Define jmp befine jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$10 jmp setbaud	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 46 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC7- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD8- 34 30 32 2DD8- 35 FF 2DDD- 75 2E 6D ' \$ff 2DE0- 20 30 20 2DE3- 37 33 FF 2DE6- 69 2E 6D	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henle Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØB 3 E59- 4C 9E 2 E59- 4C 63 3 E56- 4C 14 3 E62- A9 8E E64- 85 EC E66- A9 EE E66- A9 EE E66- B5 ED E66- 2Ø 58 E E6A- 2Ø 58 E E79- C9 B1 E72- DØ Ø5 E74- A9 4C E76- 4C 88 E E79- C9 B2 E78- DØ Ø5 E79- C9 B5 E79- C9 B5 E79- C9 B7 E79- C9 B7 E77- A9 10	Ø 1060 1 1070 1 1080 7 1100 7 1100 7 1110 8 1130 2 1140 1150 1150 1170 0 1220 1220 1220 1250 1250 1250	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda %chr] sta *chrindex lda %h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$10	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD8- 35 FF 2DD8- 35 FF 2DD0- 75 2E 6D ' \$ff 2DE0- 20 30 20 2DE3- 37 33 FF 2DE0- 20 35 20	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henle Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØD 3 E55- 4C G 3 E55- 4C 14 3 E62- A9 8E E64- 85 ED E66- A9 EE E66- A9 EE E66- A9 EE E66- B5 ED E66- B9 EB E79- C9 B1 E79- C9 B2 E79- C9 B2 E78- DØ Ø5 E77- AC B8 2 E77- AC B8 2	Ø 1060 1 1070 1 1080 7 1100 7 1100 7 1110 8 1130 2 1140 1150 1150 1170 0 1220 1220 1220 1250 1250 1250	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Define jmp Define jmp Define jmp befine jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$10 jmp setbaud	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DD8- 35 FF 2DDD- 75 2E 6D 7 \$ff 2DE0- 20 30 20 2DE3- 37 33 FF 2DE6- 69 2E 6D 2DE9- 20 35 20 2DEC- 36 33 FF	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E55- 4C Ø 3 E55- 4C 9E 2 E59- 4C 63 3 E55- 4C 14 3 E55- 4C 14 3 E62- A9 BE E64- 85 ED E66- A9 2E E6A- 2Ø F8 3 E74- A9 BE E74- A9 BE E74- A9 BE E74- A9 BE E74- A9 BB E75- AC BB	### 1968 1 1978 1 1988 1 1988 1 1988 7 1108 F 1112 Ø 1138 Ø 1150 1170 Ø 1210 Ø 1220 1230 E 1250 1250 E 1270 E 1270	lamda quit define dbl.esc sp alpha gamma epsilon print baud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda *chr] sta *chrindex lda *th,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #*b1 bne two lda #*4c jmp setbaud cmp #*b2 bne three lda #*19 jmp setbaud cmp #*b3	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DD8- 34 30 32 2DD8- 35 FF 2DDD- 75 2E 6D ' \$ff 2DE0- 20 35 20 2DE9- 20 35 20 2DE9- 20 35 20 2DE9- 36 33 FF 2DE6- 6F 2E 6D	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØD 3 E59- 4C 9E 2 E59- 4C 63 3 E56- 4C 14 3 E62- A9 BE E64- 85 ED E66- A9 2E E66- A9 2E E66- B9 E79- C9 B1 E72- DØ Ø5 E74- AP B2 E74- AP B2 E75- 4C B8 2 E77- C9 B1 E77- C9 B1 E77- AC B8 2 E77- AP B2 E77- AP B2 E77- AP B2 E77- AP B2 E77- AP B3 E84- DØ Ø5 E77- AP B3 E84- DØ DC E86- AP Ø1	Ø 1060 1 1070 1 1080 1 1080 7 1100 7 1110 6 1120 1150 1150 1160 1170 1180 0 1200 1210 1220 1230 1230 1240 1250 1270 1300 1310	lamda quit define dbl.esc sp alpha gamma epsilon print baud two	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input lda %chr] sta *chrindex lda %h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$10 jmp setbaud cmp #\$b3 bne baud lda #\$01	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DCF- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DDB- 35 FF 2DDD- 75 2E 6D ' \$ff 2DE0- 20 30 20 2DE7- 20 35 20 2DE7- 20 35 20 2DE7- 67 2E 6D 2DE7- 20 35 20 2DEF- 6F 2E 6D 2DF2- 20 36 20	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØB 3 E59- 4C G 2 E59- 4C C 3 E55- 4C 14 E62- A9 BE E64- 85 ED E66- A9 EE E66- A9 EE E66- B9 EB E79- C9 B1 E72- DØ Ø5 E74- AC B8 2 E79- C9 B2 E79- AC B8 2 E79- AC B8 2 E79- AC B8 2 E79- AC B8 2 E82- C9 B3 EB4- DØ D1 E88- BD 51 A	### 1968 1 1978 1 1978 1 1988 7 1198 7 1119 6 1138 2 1149 1158 1168 1178 1178 1129 1229 1238 1258 1258 1258 1258 1258 1258 1258 125	lamda quit define dbl.esc sp alpha gamma epsilon print baud two	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$10 jmp setbaud cmp #\$b3 bne baud lda #\$01 sta *dbyt	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DDB- 35 FF 2DDD- 75 2E 6D ' \$ff 2DE0- 20 30 20 2DE7- 69 25 60 2DC5- 69 25 60 2DC6- 69 25 60 2DC6- 20 30 20 2DE7- 69 25 60 2DE7- 69 35 20 2DE7- 67 2E 6D 2DE7- 67 2E 6D 2DE7- 20 35 20 2DEF- 6F 2E 6D 2DF7- 20 30 20 2DF7- 37 33 20	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Henle Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E5A- 4C 36 3 E55- 4C 36 3 E55- 4C 63 3 E55- 4C 14 3 E55- 4C 14 3 E62- A9 BE E64- 85 ED E66- A9 2E E6A- 2Ø F8 3 E74- A9 8E E74- A9 8E E74- A9 8E E74- A9 8E E74- A9 8B E74- A9 8B E74- A9 8B E74- A9 8B E75- 4C 83 8 E75- C9 B1 E75- AC 88 2 E86- AP 90 AC E88- AC E8	### 1968 1 1978 1 1988 1 1988 1 1988 7 1108 7 1118 Ø 1118 Ø 1150 1118 Ø 1219 1228 E 1250 1250 1270 Ø 1330 Ø 1330 6 1330	lamda quit define dbl.esc sp alpha gamma epsilon print baud two three setbaud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$19 jmp setbaud cmp #\$b3 bne baud lda #\$#01 sta #dbyt lda #13	
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4C 2DC3- 61 6E 65 2DC6- 2C 20 4D 2DCF- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DDB- 35 FF 2DDD- 75 2E 6D ' \$ff 2DE0- 20 30 20 2DE7- 20 35 20 2DE7- 20 35 20 2DE7- 67 2E 6D 2DE7- 20 35 20 2DEF- 6F 2E 6D 2DF2- 20 36 20	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Menlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E59- 4C ØB 3 E59- 4C G 2 E59- 4C C 3 E55- 4C 14 E62- A9 BE E64- 85 ED E66- A9 EE E66- A9 EE E66- B9 EB E79- C9 B1 E72- DØ Ø5 E74- AC B8 2 E79- C9 B2 E79- AC B8 2 E79- AC B8 2 E79- AC B8 2 E79- AC B8 2 E82- C9 B3 EB4- DØ D1 E88- BD 51 A	### 1968 1 1978 1 1978 1 1988 7 1198 7 1119 6 1138 2 1149 1158 1168 1178 1178 1129 1229 1238 1258 1258 1258 1258 1258 1258 1258 125	lamda quit define dbl.esc sp alpha gamma epsilon print baud two three setbaud	jmp echo jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$10 jmp setbaud cmp #\$b3 bne baud lda #\$01 sta *dbyt	G/M_DLIV
rk, CA 94025' \$ 2DAE- 68 6E 20 2DB1- 4D 61 74 2DB4- 74 6F 78 2DB7- FF 77 33 2DBA- 33 31 20 2DBD- 4E 6F 76 2DC0- 61 20 4D 2DC9- 65 6E 6C 2DCC- 6F 20 50 2DCF- 61 72 6B 2DD2- 2C 20 43 2DD5- 41 20 39 2DDB- 35 FF 2DDD- 75 2E 6D ' \$ff 2DE0- 20 30 20 2DE7- 69 25 60 2DC5- 69 25 60 2DC6- 69 25 60 2DC6- 20 30 20 2DE7- 69 25 60 2DE7- 69 35 20 2DE7- 67 2E 6D 2DE7- 67 2E 6D 2DE7- 20 35 20 2DEF- 6F 2E 6D 2DF7- 20 30 20 2DF7- 37 33 20	Ø74Ø prom .by ff	'qJohn Mattox' \$ff 'w331 Nova Lane,	Menlo Pa 22 22 22 22 22 22 22 22 22 22 22 22 22	E47- 4C 9E 3 E4A- 4C AØ 3 E4A- 4C AØ 3 E5A- 4C 36 3 E55- 4C 36 3 E55- 4C 63 3 E55- 4C 14 3 E55- 4C 14 3 E62- A9 BE E64- 85 ED E66- A9 2E E6A- 2Ø F8 3 E74- A9 8E E74- A9 8E E74- A9 8E E74- A9 8E E74- A9 8B E74- A9 8B E74- A9 8B E74- A9 8B E75- 4C 83 8 E75- C9 B1 E75- AC 88 2 E86- AP 90 AC E88- AC E8	### 1968 1 1978 1 1988 1 1988 1 1988 7 1108 7 1118 Ø 1118 Ø 1150 1118 Ø 1219 1228 E 1250 1250 1270 Ø 1330 Ø 1330 6 1330	lamda quit define dbl.esc sp alpha gamma epsilon print baud two three setbaud	jmp echo jmp Quit jmp Quit jmp Define jmp Dbl.esc jmp swp jmp cold jmp alter jmp input jmp Print lda #chr] sta *chrindex lda #h,chr] sta *chrindex+1 jsr outputchr jsr intchr cmp #\$b1 bne two lda #\$4c jmp setbaud cmp #\$b2 bne three lda #\$19 jmp setbaud cmp #\$b3 bne baud lda #\$#01 sta #dbyt lda #13	SYM-PHY

, partinge.

```
2F38~ 65 72 2Ø
                                 .by 'alter baud rate: enter 1 for 300, 2 for 120
2E8E~ 61 6C 74 135Ø chr]
                                                                                      2F3B- 5Ø 41 44
Ø. '
                                                                                      2F3E- 42 49 54
2E91- 65 72 20
                                                                                      2F41- 2Ø 76 61
2E94- 62 61 75
                                                                                      2F44- 6C 75 65
2E97- 64 20 72
                                                                                      2F47- 2Ø 2Ø 2B
2E9A- 61 74 65
                                                                                      2F4A- 41 3Ø 2Ø
2E9D- 3A 20 65
                                                                                      2F4D- 66 6F 72
2EAØ- 6E 74 65
                                                                                      2F5Ø- 2Ø 6D 6F
2EA3- 72 20 31
                                                                                      2F53- 64 65 6D
2EA6- 20 66 6F
                                                                                      2F56- 2C 2Ø 3Ø
2EA9- 72 20 33
                                                                                      2F59- 31 2Ø 66
2EAC- 3Ø 3Ø 2C
                                                                                      2F5C- 6F 72 2Ø
2EAF- 20 32 20
                                                                                      2F5F- 73 63 72
2EB2- 66 6F 72
                                                                                       2F62- 65 65 6E
2EB5- 2Ø 31 32
                                                                                      2F65- 2C
2EB8- 3Ø 3Ø 2C
                                                                                                                        .by '20 for printer)
                                                                                      2F66- 32 30 20
                                 .by ' 3 for 4800
2EBB- 2Ø 33 2Ø
                136Ø
                                                                                      ' 13 $ff
13 $ff
                                                                                      2F69- 66 6F 72
2EBE- 66 6F 72
                                                                                      2F6C- 2Ø 7Ø 72
2EC1- 2Ø 34 3B
                                                                                      2F6F- 69 6E 74
2EC4- 3Ø 3Ø ØA
                                                                                      2F72- 65 72 29
2EC7~ ØD FF
                                                                                      2F75- ØA ØD FF
2EC9- A9 DC
                 137Ø alter
                                 lda #chr3
                                                                                                                        jsr inbyte
                                                                                      2F78- 2Ø D9 81
                                                                                                       149Ø brnØ
2ECB- 85 EC
                 1380
                                 sta *chrindex
                                                                                                                        sta SPflg
                                                                                                       1500
                                                                                      2F7B- 8D F5 ØØ
                                 lda #h,chr3
2ECD- A9 2E
                 1390
                                                                                                                        lda $a
                                                                                      2F7E- AD ØA ØØ
                                                                                                       1510
                                 sta *chrindex+1
                 1400
2ECF- 85 ED
                                                                                                                        isr outchr
                                                                                                       1520
                                                                                      2F81- 2Ø 47 BA
                                 isr outputchr
2ED1- 20 F8 30
                1410
                                                                                                                        jsr inbyte
                                                                                                       1530
                                                                                      2F84- 2Ø D9 B1
                                 lda #$8Ø
                1420
2ED4- A9 8Ø
                                                                                                                        sta LFflg
                                                                                                       1540
                                                                                      2F87- 8D F4 ØØ
                                 sta techo
2ED6- 8D 53 A6
                1439
                                                                                                                        lda $a
                                                                                      2F8A- AD ØA ØØ
                                                                                                       1550
2ED9- 4C 78 2F
                1440
                                 jmp brnØ
                                                                                                                        jsr outchr
                                                                                      2F8D- 2Ø 47 8A
                                                                                                       1569
2EDC- ØA 54 59
                1450 chr3
                                 .by '
                                                                                                                        jsr inbyte
                                                                                                       1579
                                                                                      2F9Ø- 2Ø D9 81
                for inserion of space before CR
TYPE 00 or 01
                                                                                                                        sta $a650 padbit #
                                                                                      2F93- 8D 5Ø A6
                                                                                                       1580
' 13
                                                                                                                        1da #Ø
                                                                                       2F96- A9 ØØ
                                                                                                       1599
2EDF- 5Ø 45 2Ø
                                                                                                                        sta techo
                                                                                      2F98- 8D 53 A6
                                                                                                       1600
2EE2- 30 30 20
                                                                                                                        lda #13
                                                                                       2F9B- A9 ØD
                                                                                                       1619
2EE5- 6F 72 20
                                                                                                       1620
                                                                                                                        rts
                                                                                       2F9D- 60
2EE8- 30 31 20
                                                                                                                        1dv #00
                                                                                                       163Ø cold
                                                                                       2F9E- AØ ØØ
2EEB- 20 20 66
                                                                                                                        lda #chr>
                                                                                       2FAØ- A9 D7
                                                                                                       1640
2EEE- 6F 72 20
                                                                                                                        sta *chrindex
                                                                                       2FA2- 85 EC
                                                                                                       1650
2EF1- 69 6E 73
                                                                                                                        lda #h,chr>
                                                                                       2FA4- A9 2F
                                                                                                       1660
2EF4- 65 72 69
                                                                                                                        sta *chrindex+1
                                                                                       2FA6- 85 ED
                                                                                                       1679
2EF7- 6F 6E 2Ø
                                                                                                                        jsr outputchr
                                                                                                       1689
                                                                                       2FA8- 2Ø F8 3Ø
2EFA- 6F 66 2Ø
                                                                                                                        isr intchr
                                                                                       2FAB- 2Ø 58 8A
                                                                                                       1699
2EFD- 73 70 61
                                                                                                                        and #$7f
                                                                                       2FAE- 29 7F
                                                                                                        1700
2FØØ- 63 65 2Ø
                                                                                                                        cmp #'y
                                                                                       2FBØ- C9 79
                                                                                                        171Ø
2FØ3- 62 65 66
                                                                                                                        beg rptcold
                                                                                       2FB2- FØ Ø3
                                                                                                       1720
2FØ6- 6F 72 65
                                                                                                                        jmp menu
                                                                                       2FB4- 4C 76 2C
                                                                                                       1730
2FØ9- 2Ø 43 52
                                                                                                       1740 rptcold
                                                                                                                        1da #chr2
                                                                                       2FB7- A9 FD
2FØC- ØA ØD
                                                                                       2FB9- 85 EC
                                                                                                                        sta *chrindex
                                                                                                        1750
                                 .by 'TYPE 00 or 01 for inhibit line-feeds
2FØE- 54 59 5Ø
                 1460
                                                                                                                        1da #h,chr2
                                                                                       2FBB- A9 2F
                                                                                                       1760
 ' 13
                                                                                                                        sta chrindex+1
                                                                                       2FBD- 8D ED ØØ
                                                                                                       1770
2F11- 45 20 30
                                                                                                       178Ø
                                                                                                                        lda (chrindex), y
                                                                                       2FCØ- B1 EC
2F14- 3Ø 2Ø 6F
                                                                                                        1790
                                                                                                                        tax
                                                                                       2FC2- AA
2F17- 72 2Ø 3Ø
                                                                                                                        lda #min
                                                                                                        1800
                                                                                       2FC3- A9 8Ø
2F1A- 31 20 20
                                                                                       2FC5- 85 EC
                                                                                                                         sta *chrindex
                                                                                                        1810
2F1D- 66 6F 72
                                                                                                                        lda #h.min
                                                                                       2FC7- A9 Ø2
                                                                                                        1829
2F2Ø- 2Ø 69 6E
                                                                                                                        sta chrindex+1
                                                                                                       1839
                                                                                       2FC9- 8D ED ØØ
2F23- 68 69 62
                                                                                       2FCC- BA
                                                                                                                         txa
                                                                                                        1840
2F26- 69 74 2Ø
                                                                                                        1859
                                                                                                                         iny
                                                                                       2FCD- C8
                                                                                                                        cmp ##ff
2F29- 6C 69 6E
                                                                                       2FCE- C9 FF
                                                                                                        1860
                                                                                                                        beg brn7
2F2C- 65 2D 66
                                                                                       2FDØ- FØ 7D
                                                                                                        1879
                                                                                                                         sta (chrindex), y
2F2F- 65 65 64
                                                                                                        1880
                                                                                       2FD2- 91 EC
                                                                                                                         jmp rptcold
2F32- 73 ØA ØD
                                                                                       2FD4- 4C B7 2F
                                                                                                       1890
                                                                                                                         .by 'Type y to execute a cold start to RAE' $ff
                                  .by 'Enter PADBIT value (AØ for modem, Ø1 for s
2F35-- 45 6E 74 147Ø
                                                                                       2FD7- 54 79 7Ø
                                                                                                       1900 chr>
                                                                                                                                                     SYM-PHYSIS 17-30
creen,'
                                                              SYM-PHYSIS 17-29
```

```
sta *inputdex
                                                                                      307B- 85 CA
                                                                                                      2160
2FDA- 65 2Ø 79
                                                                                                       2170
                                                                                                                       LDA #H, min
                                                                                      3Ø7D- A9 Ø2
2FDD- 2Ø 74 6F
                                                                                                                       STA *inputdex+1
                                                                                      307F- 85 CB
                                                                                                       2180
2FEØ- 2Ø 65 78
                                                                                                                       isr intchr
                                                                                                      219Ø rpt1
                                                                                      3Ø81- 2Ø 58 8A
2FE3- 65 63 75
                                                                                      3Ø84- 91 CA
                                                                                                                       sta (inputdex),y
                                                                                                       2200
2FE6- 74 65 2Ø
                                                                                                       2219
                                                                                                                       inc *inputdex
                                                                                      3Ø86- E6 CA
2FE9- 61 2Ø 63
                                                                                                                       bne goon
                                                                                                       2220
                                                                                      3Ø88- DØ Ø2
2FEC- 6F 6C 64
                                                                                                                       inc *inputdex+1
                                                                                                       2239
                                                                                      3Ø8A- E6 CB
2FEF- 2Ø 73 74
                                                                                                                       lda *inputdex
                                                                                      3Ø8C- A5 CA
                                                                                                       2240
                                                                                                           goon
2FF2- 61 72 74
                                                                                                                       CMD #L.max
                                                                                      3Ø8E- C9 FF
                                                                                                      225Ø
2FF5- 2Ø 74 6F
                                                                                                                       bne rpti
                                                                                                      2260
                                                                                      3090- DØ EF
2FF8- 2Ø 52 41
                                                                                                       2270
                                                                                                                       lda *inputdex+1
                                                                                      3Ø92- A5 CB
2FFB- 45 FF
                                                                                                       2280
                                                                                                                       cmp #H, max
                                                                                      3094- C9 2F
                                  .by Ø3 'm3' 13 '20' '002c' '4c03b0' 13
2FFD- Ø3 6D 33
                1910 chr2
                                                                                                       229Ø
                                                                                                                       bne rpt1
                                                                                      3Ø96- DØ E9
3000- 0D 32 30
                                                                                                                       jsr $8972 BEEP-TO MUCH
                                                                                      3098- 20 72 89
                                                                                                      2300
3003- 30 30 32
                                                                                                                       1da #13
                                                                                      3Ø9B- A9 ØD
                                                                                                       2310 stop
3006- 63 34 63
                                                                                                                       rts
                                                                                      309D~ 60
                                                                                                       2320
3009- 30 33 62
                                                                                      309E- A9 BØ
                                                                                                       233Ø echo
                                                                                                                       LDA #min
3ØØC- 3Ø ØD
                                                                                                                       STA *outputdex
                                                                                      3ØAØ- 85 FØ
                                                                                                       2349
                 1920 ;Change 0030 to be consistent with the beginning of this pr
                                                                                                       235@
                                                                                                                       LDA #H, min
                                                                                      3ØA2- A9 Ø2
ogram. *>!
                                                                                                                       sta *outputdex+1
                                                                                      3ØA4- 85 F1
                                                                                                       2369
                                 .by 'gb003' 13 'set $200 $2eff' 13 'fo c' 13 'a
300E- 67 62 30
                193Ø
                                                                                                       237Ø
                                                                                                                       LDA #yec Change invec to get input from buffer.
                                                                                      30A6- A9 B0
u 10' 13
                                                                                                      2389
                                                                                                                       STA $A661 invec
                                                                                      3ØA8- 8D 61 A6
3011- 30 33 ØD
                                                                                                       2390
                                                                                                                       LDA #H, vec
                                                                                      30AB- A9 30
3014-73 65 74
                                                                                                                       STA $A662
                                                                                                       2400
                                                                                      3ØAD- 8D 62 A6
3017- 20 24 32
                                                                                                                       LDY #Ø
                                                                                                       241Ø vec
                                                                                      30B0- A0 00
3Ø1A- 3Ø 3Ø 2Ø
                                                                                                                       LDA (outputdex),Y
                                                                                                       2420
                                                                                      3ØB2- B1 FØ
3Ø1D- 24 32 65
                                                                                                       2430
                                                                                                                       TAY
                                                                                      3ØB4- A8
3020- 66 66 ØD
                                                                                                       2449
                                                                                                                       inc *outputdex
                                                                                      3ØB5- E6 FØ
3023- 66 6F 20
                                                                                                                       bne cont3
                                                                                                       2450
                                                                                      3ØB7-- DØ Ø2
3026- 63 0D 61
                                                                                                                       inc *outputdex+1
                                                                                                       2460
                                                                                      3ØB9- E6 F1
3029- 75 20 31
                                                                                                                       lda *outputdex
                                                                                                       247Ø cont3
                                                                                      3ØBB- A5 FØ
3Ø2C- 3Ø ØD
                                                                                                                       cmp inputdex
                                                                                                      2480
                                                                                      3ØBD- CD CA ØØ
                 1940 ;Change 2eff to be ram-1 *>!
                                                                                                       2490
                                                                                                                       bne QUIT
                                                                                      3ØCØ- DØ 12
                                 .by '10.rr' 13 '.m 0 73 1003 3' 13 '.p 1 5' 13 '
302E- 31 30 2E 1950
                                                                                      3ØC2- AD F1 ØØ
                                                                                                       25ØØ
                                                                                                                       lda outputdex+1
.t' 13
                                                                                      30C5- CD CB 00
                                                                                                       2510
                                                                                                                       cmp inputdex+1
3Ø31- 72 72 ØD
                                                                                                       252Ø
                                                                                                                       BNE QUIT
                                                                                      3ØC8- DØ ØA
3Ø34- 2E 6D ØØ
                                                                                      3ØCA- A9 ØD
                                                                                                       2530
                                                                                                                       LDA #intchr@
3037- 20 30 20
                                                                                                                       sta $a661 invec
                                                                                                       2540
                                                                                      3ØCC- BD 61 A6
3Ø3A- 37 33 2Ø
                                                                                                       2559
                                                                                                                       LDA #h.intchr@
                                                                                      3ØCF- A9 2E
3Ø3D- 31 3Ø 3Ø
                                                                                      30D1- 8D 62 A6
                                                                                                       256Ø
                                                                                                                        STA $A662
3Ø4Ø- 33 2Ø 33
                                                                                      3ØD4~ 9B
                                                                                                                       TYA
                                                                                                       257Ø QUIT
3Ø43- ØD 2E 7Ø
                                                                                                                       RTS
                                                                                      3ØD5- 6Ø
                                                                                                       2589
3046- 20 31 20
                                                                                                                        jsr $8188 saver
                                                                                      3ØD6- 2Ø 88 81
                                                                                                       2590 outchre
3Ø49~ 35 ØD 2E
                                                                                                                        ldx SPflg If SPflq set then output space before
                                                                                      3ØD9~ AE F5 ØØ
                                                                                                       2699
3Ø4C- 74 ØD
                                                                                      c/r. Some systems
3Ø4E- FF
                 1960
                                  .by $ff
                                                                                                            istop input upon receiving c/r at the beginning of a line.
                                                                                                       2610
                                 clc
3Ø4F- 18
                 1970 brn7
                                                                                                                        beg cont4
                                                                                      3ØDC- FØ ØB
                                                                                                       2620
                 1980
                                  tya
3050- 98
                                                                                      3ØDE- C9 ØD
                                                                                                       263Ø
                                                                                                                        cmp #13 ?CR
3051- 69 80
                 1990
                                  adc #min
                                                                                      3ØEØ- DØ Ø7
                                                                                                       2640
                                                                                                                       bne cont4
3Ø53- 8D CA ØØ
                 2000
                                  sta inputdex
                                                                                      3ØE2- A9 2Ø
                                                                                                       265Ø
                                                                                                                        lda #32 spc
                                 LDA #ØØ
3056- A9 00
                 2010
                                                                                      3ØE4- 2Ø AØ 8A
                                                                                                       2660
                                                                                                                        isr $8aaØ tout
                                  ADC #H.min
3058- 69 02
                 2020
                                                                                      3ØE7- A9 ØD
                                                                                                       267Ø
                                                                                                                        1da #13
                                                                                                                        ldx LFflg If LFflg set then inhibit the output o
3Ø5A- BD CB ØØ
                 2030
                                  STA inputdex+1
                                                                                      3ØE9- AE F4 ØØ
                                                                                                       268Ø cont4
                                  JSR echo
3Ø5D- 2Ø 9E 3Ø
                 2040
                                                                                      f linefeeds,
                                  jmp $6000 Cold Start
3060- 4C 00 B0
                 2050
                                                                                                       2690 jas needed for SYM-1 transfer to other systems.
                                  ldy #ØØ
3Ø63- AØ ØØ
                 2060 input
                                                                                                       2700
                                                                                                                        beg conti
                                                                                      3ØEC- FØ Ø4
                 2070
                                  lda #71
3065- A9 47
                                                                                      3ØEE- C9 ØA
                                                                                                       271Ø
                                                                                                                        cmp #10 ?LF
                                  jsr outchr
                 2080
                                                                                                                        beg cont
3Ø67- 2Ø 47 8A
                                                                                      3ØFØ- FØ Ø3
                                                                                                       2728
                                  1da #79
306A- A9 4F
                 2090
                                                                                                                        jsr $8aaØ tout
                                                                                      3ØF2- 2Ø AØ BA
                                                                                                       273Ø cont1
306C- 20 47 BA
                 2100
                                  isr outchr
                                                                                                                        jmp $8168 resxaf
                                                                                      3ØF5- 4C BB 81
                                                                                                       274Ø cont
                                  lda #10
306F- A9 ØA
                 2110
                                                                                                                        ldx #ØØ
                                                                                      3ØF8- A2 ØØ
                                                                                                       2750 outputchr
                                  jsr outchr
3Ø71- 2Ø 47 BA
                 2120
                                                                                                       276Ø rpt
                                                                                                                        lda (chrindex.x)
                                                                                      3ØFA- A1 EC
3Ø74- A9 BØ
                                  lda #$8Ø
                 2130
                                                                                      3ØFC- C9 FF
                                                                                                                        cmp #$ff
                                                                                                       2770
                                  sta techo
                 2140
3076- BD 53 A6
                                                                                      3ØFE- DØ Ø1
                                                                                                       2780
                                                                                                                        bne brn1
                                  LDA #min INITIALIZE WORKING INDEX
3Ø79- A9 BØ
                 2150
                                                                                      3100- 60
                                                                                                       2790
                                                                                                                        rts
                                                                                                                                                     SYM-PHYSIS 17-32
                                                               SYM-PHYSIS 17-31
```

····

1)

```
3101- 20 47 BA
                2800 brn1
                                  jsr outchr
                                                                                   3198- 74 2C 65
                                                                                   319B- 73 63 ØA
31Ø4- E6 EC
                 281Ø
                                  inc *chrindex
                                                                                   319E- ØD FF
                 2829
                                  bne rpt
31Ø6- DØ F2
                                                                                                    3400 Quit
                                                                                                                     lda #chr@
                                  inc *chrindex+1
                                                                                   31AØ- A9 ED
31Ø8- E6 ED
                 2830
                                                                                                                     sta *chrindex
                                                                                   31A2- 85 EC
                                                                                                    3410
                                  jmp rpt
                 284Ø
310A- 4C FA 30
                                                                                                                     lda #h,chr@
                                                                                                    3420
                2850 Dbl.esc
                                                                                   31A4- A9 31
                                  isr intchr
310D- 20 58 8A
                                                                                                                     sta *chrindex+1
                                                                                   31A6- 85 ED
                                                                                                    3430
3110- 29 7F
                 2860
                                  and #$7f
                                                                                                                      jsr outputchr
                                                                                   31A8- 20 FB
                                                                                                    3440
                                  sta *symb
3112- 85 E8
                 287Ø
                                                                                                                      jsr intchr
                                                                                   31AB- 20 58 BA
                                                                                                    3450
                                                inumber of prom phrases *>!
                                  1dx #6
                 288Ø
3114- A2 Ø6
                                                                                                                     and #$7f
                                                                                   31AE- 29 7F
                                                                                                    3460
                                  lda #prom
3116- A9 AB
                 2890
                                                                                                                     cmp #'y
                                                                                   31BØ~ C9 79
                                                                                                    347Ø
                                  sta *prsdex
3118-85 F6
                 2900
                                                                                                                     beg CoNt
                                                                                   31B2- FØ Ø3
                                                                                                    3480
                 2910
                                  lda #h.prom
311A- A9 2D
                                                                                                                      jmp menu
                                                                                                    3490
                                                                                   31B4- 4C 76
311C- 85 F7
                 2920
                                  sta *prsdex+1
                                                                                   3187- C6 CC
                                                                                                    3500 CoNt
                                                                                                                      dec #nuprs
                 2930
                                  jsr phrase
311E- 2Ø 4A 32
                                                                                                                     lda #begin-1
                                                                                                    351Ø
                                                                                   31B9- A9 FF
                 2940
                                  ldx nuprs
3121- AE CC ØØ
                                                                                   31BB- BD 4A A6
                                                                                                                      sta param
                                                                                                    3520
                                  beq Beep
                 295Ø
3124- FØ ØD
                                                                                                                     lda #h,begin-1
                                                                                   31BE- A9 2B
                                                                                                    353Ø
                                  lda #ram
                 2960
3126- A9 ØØ
                                                                                                                      sta param+1
                                                                                                    3540
                                                                                   31CØ- 8D 4B A6
                                  sta *prsdex
3128- 85 F6
                 2970
                                                                                                                     lda *inputdex
                                                                                   31C3- A5 CA
                                                                                                    3550
                 298Ø
                                  lda #h,ram
312A- A9 2B
                                                                                                                      sta *prsdex
                                                                                                    3560
                                                                                   3105- 85 F6
312C- 85 F7
                 2990
                                  sta *prsdex+1
                                                                                                                      lda #inputdex+1
                                                                                                    357Ø
                                                                                   31C7- A5 CB
                 3000
                                  jsr phrase
312E- 20 4A
                                                                                   31C9- 85 F7
                                                                                                     358Ø
                                                                                                                      sta *prsdex+1
                                  lda #$2Ø
                 3010
3131- A9 2Ø
                                                                                   31CB- 2Ø 88 32
                                                                                                     3590
                                                                                                                      jsm inc.prsdex
                                  jmp $8972 Beep
3133- 4C 72
                 3020 Beep
                                                                                   31CE- A5 F6
                                                                                                     3600
                                                                                                                      lda *prsdex
                 3030 Define
                                  ldy #Ø
3136- AØ ØØ
                                                                                                                      sta param+2
                                                                                    31DØ- 8D 4C A6
                                                                                                     3610
                 3040
                                  inc *nuprs
3138- E6 CC
                                                                                                                      lda *prsdex+1
                                                                                                     3620
                                                                                    31D3- A5 F7
313A- A6 CC
                 3050
                                  ldx *nuprs
                                                                                                    3630
                                                                                                                      sta param+3
                                                                                   31D5-- 8D 4D A6
                 3969
                                  lda #ram
313C- A9 ØØ
                                                                                    31D8- A5 F2
                                                                                                     3640
                                                                                                                      lda *putdex
313E- 85 F6
                 3070
                                  sta *prsdex
                                                                                                                      bne hope
                                                                                   31DA- DØ Ø2
                                                                                                     3650
                                  lda #h,ram
                 3080
314Ø- A9 2B
                                                                                                                      dec *putdex+1
                                                                                                     366Ø
                                                                                    31DC- C6 F3
                                  sta *prsdex+1
3142- 85 F7
                 3090
                                                                                                                      dec *putdex
                                                                                    31DE- C6 F2
                                                                                                     367Ø hope
                 3100 Alpha
                                  dex
3144- CA
                                                                                                                      lda *putdex
                                                                                    31EØ- A5 F2
                                                                                                     368ø
                                  beg charac
                 3110
3145- FØ ØB
                                                                                                                      sta param+4
                                                                                                     3690
                                                                                    31E2- 8D 4E
                                  lda #$ff
3147- A9 FF
                 3120
                                                                                                                      lda *putdex+1
                                                                                                     3700
                                                                                    31E5- A5 F3
3149- 20 80 32
                                  isr ff?
                 3130
                                                                                                     3710
                                                                                                                      sta param+5
                                                                                    31E7- 8D 4F A6
                                  jsr inc.prsdex
314C- 2Ø 88 32
                 3140
                                                                                                                      jmp $8740 block move
                                                                                    31EA- 4C 4Ø 87
                                                                                                     3729
                                  jmp Alpha
314F- 4C 44 31
                 3150
                                                                                                                      .by 'Type y to delete last phrase retreived' $ff
                                                                                    31ED- 54 79 7Ø
                                                                                                     373Ø chr@
                                  lda #\chr
3152- A9 89
                 3160 charac
                                                                                    31FØ-- 65 20 79
3154- 85 EC
                 3170
                                  sta *chrindex
                                                                                    31F3- 20 74 6F
                 3180
                                  lda #h.\chr
3156~ A9 31
                                                                                    31F6- 2Ø 64 65
                                  sta *chrindex+1
3158- 85 ED
                 3190
                                                                                    31F9~ 6C 65 74
                                  jsr outputchr
315A- 20 F8 30
                 3200
                                                                                    31FC- 65 20 6C
                                  jsr limit?
315D- 20 8F 32
                 3210
                                                                                    31FF- 61 73 74
3160- 20 58 BA
                 3220
                                  jsr intchr
                                                                                    3202- 20 70 68
                                  jsr outchr
                 3230
3163- 2Ø 47 BA
                                                                                    3205-72 61 73
                                  and #$7f
                 3240
3166- 29 7F
                                                                                    3208- 65 20 72
                 325Ø
                                  sta (prsdex), y
3168- 91 F6
                                                                                    32ØB- 65 74 72
                                  1da #'-
316A- A9 2D
                 3260
                                                                                    32ØE- 65 69 76
                                  isr outchr
316C- 2Ø 47 BA
                 3270
                                                                                    3211- 65 64 FF
316F- 2Ø 88 32
                 3280 beta
                                  jsr inc.prsdex
                                                                                                                      1dy #Ø
                                                                                    3214- AØ ØØ
                                                                                                     374Ø Print
3172- 20 BF 32
                 3290
                                  jsr limit?
                                                                                                                      ldx *nuprs
                                                                                    3216- A6 CC
                                                                                                     3750
                 3300
                                  jsr intchr
3175- 2Ø 58 8A
                                                                                                     3760
                                                                                                                      inx
                                                                                    3218- E8
                                  jsr outchr
                 331Ø
3178- 2Ø 47
                                                                                                     377Ø
                                                                                                                      lda #ram
                                                                                    3219- A9 ØØ
                                  cmp #$9b ?escape
317B- C9 9B
                 3320
                                                                                                     378Ø
                                                                                                                      sta *prsdex
                                                                                    321B- 85 F6
                                  bed Stop
317D- FØ Ø5
                 333Ø
                                                                                                                      lda #h,ram
                                                                                                     3790
                                                                                    321D- A9 2B
                                  sta (prsdex),y
                 3340
317F- 91 F6
                                                                                                                      sta *prsdex+1
                                                                                    321F- 85 F7
                                                                                                     3800
                 3350
                                  imo beta
3181- 4C 6F 31
                                                                                                     3810
                                                                                                                      dex
                                                                                    3221- CA
                                                                                                          gone
                 336Ø Stop
                                  lda #$ff
3184- A9 FF
                                                                                                                      beg StOp
                                                                                                     3820
                                                                                    3222- FØ 23
                                  sta (prsdex),y
3186- 91 F6
                 337Ø
                                                                                                                      lda (prsdex),y
                                                                                                     3830
                                                                                    3224- B1 F6
3188- 60
                 3380
                                  rts
                                                                                                                      jsr outchr
                                                                                                     384Ø
                                                                                    3226- 20 47
                                  .by 'Type symbol, text, esc
3189- 54 79 70
                 339Ø \chr
                                                                                                                      lda #'-
                                                                                    3229- A9 2D
                                                                                                     3850
 , 13 $ff
                                                                                                                      isr outchr
                                                                                    322B- 2Ø 47 8A
                                                                                                     3860
                                                                                                          going
318C- 65 20 73
                                                                                                     387Ø
                                                                                                                      isr inc.prsdex
                                                                                    322E- 2Ø 88
31BF- 79 6D 62
                                                                                    3231- B1 F6
                                                                                                                      lda (prsdex),y
                                                                                                     3880
3192- 6F 6C 2C
                                                                                                                      cmp #$ff
                                                                                    3233- C9 FF
                                                                                                     389Ø
3195- 74 65 78
                                                                                                                                                     SYM-PHYSIS 17-34
                                                                                                                      bne going
                                                            SYM-PHYSIS 17-33
                                                                                    3235- DØ F4
                                                                                                     3900
```

```
323A- A9 ØD
                3920
                                 lda #13
323C- 2Ø 47 BA
                3930
                                 jsr outchr
323F- A9 ØA
                3940
                                 1da #10
3241- 2Ø 47 BA
               3950
                                 isr outchr
3244- 4C 21 32 396Ø
                                 jap gone
3247- A9 ØD
                397Ø StOp
                                 lda #13
                3980
                                 rts
3249- 60
324A- AØ ØØ
                3990 phrase
                                 1dy #ØØ
324C- B1 F6
                4000
                                 lda (prsdex),y
324E- C5 E8
                4010
                                 cmp *symb
3250- FØ ØC
                4020
                                 bea Output
3252- A9 FF
                4030
                                 lda #$ff
3254~ 20 80 32
                4049
                                 isr ff?
3257- 20 88 32
               4050
                                 jsr inc.prsdex
325A- CA
                4060
                                 dex
3258- DØ ED
                4979
                                 bne phrase
                4080
                                 rts
325D- 6Ø
325E- 2Ø 88 32
               4090 Output
                                 isr inc.prsdex
3261- A5 F6
                4100
                                 lda *prsdex
                                 sta *putdex
3263- 85 F2
                4110
3265- 85 FØ
                4129
                                 sta *outputdex
3267- A5 F7
                4130
                                 lda *prsdex+1
                                 sta #putdex+1
3269- 85 F3
                4140
                                 sta #outputdex+1
                4150
326B- 85 F1
                                 lda #$ff
326D- A9 FF
                4160
326F- 20 80 32 4170
                                 isr ff?
3272- 68
                4180
                                 pla
                4190
                                 pla
3273- 68
3274- A5 F6
                4200
                                 lda *prsdex
                                 sta *inputdex
3276- 85 CA
                4210
                                 1da #prsdex+1
3278- A5 F7
                4220
                423Ø
                                 sta inputdex+1
327A- 8D CB ØØ
                                 imo echo+8
327D- 4C A6 3Ø
                4240
328Ø- 2Ø 88 32 425Ø ff?
                                 isr inc.prsdex
3283- D1 F6
                4260
                                 cmp (prsdex),y
                                 bne ff?
3285- DØ F9
                4270
3287~ 60
                428Ø
                                 rts
3288- E6 F6
                4290 inc.prsdex inc *prsdex
                4300
                                 bne indend
328A- DØ Ø2
                                 inc *prsdex+1
328C- E6 F7
                4310
328E- 6Ø
                432Ø ipdend
                                 rts
                433Ø limit?
328F- A5 F6
                4340
                                 lda *prsdex
                4350
                                 cmp #begin
3291- C9 ØØ
                4360
                                 bne QuIt
3293- DØ 15
3295- AD F7 ØØ
                4370
                                 lda prsdex+i
3298- C9 2C
                 438Ø
                                 cmo #h.begin
329A- DØ ØE
                 4390
                                 bne QuIt
                                 1da #chr<
329C- A9 AB
                 4499
                4419
                                 sta *chrindex
329E- 85 EC
                                 1da #h.chr<
32AØ- A9 32
                 4420
                                 sta #chrindex+1
                 4430
32A2- 85 ED
                                 isr outputchr
                4440
32A4- 20 FB 30
32A7- 68
                                 pla
                 4450
32A8- 68
                 4460
                                 pla
32A9- 6Ø
                 447Ø
                                 rts
32AA- 60
                 448Ø QuIt
32AB- 45 78 63 4490 chr<
                                 .by 'Exceeding RAM allocation, entry not retaine
d' $ff
32AE- 65 65 64
                     32BD- 63 61 74
                                          32CC~ 6F 74 2Ø
32B1- 69 6E 67
                     32CØ- 69 6F 6E
                                          32CF- 72 65 74
32B4- 2Ø 52 41
                     32C3- 2C 2Ø 65
                                          32D2- 61 69 6E
                                          32D5- 65 64 FF
                                                              4500
                                                                               . 60
3287- 4D 2Ø 61
                     32C6- 6E 74 72
32BA- 6C 6C 6F
                     32C9- 79 20 6E
                                                               SYM-PHYSIS 17-35
```

jsr inc.prsdex

3237- 20 88 32

3910

UBING MAE/STP ON THE COM-64

Since we'll soon be doing much of our work in the future on the COM-64, we thought we'd give MAE/STP a try. STP, for Simplified Text Processor, is MAE's equivalent of RAE's SWP. Our first thoughts are these: We find the 40 column screen with its larger characters easier to read, but it will take a while to get used to the narrower display, and the screen editing features available on the -64 sure do beat the CTRL-F ED function used in RAE.

STP has a macro ".RU \$xxxx", where \$xxxx is the address of any machine language subroutine. The macro is used to call subroutines for intelligent printer control. This was not needed in SWP, where escape sequences and control codes could be entered directly from the terminal; this cannot be done on most CBM machines. These subroutines will be an early order of business.

Please see that this is the only part of any issue of SYM~PHYSIS which we did NOT do on a SYM. We feel slightly guilty about this so it's back to SYM for the rest of this last issue!

COM-64/KTM-2 COMPATIBILITY

Judging by our incoming mail, many of you out there are getting Commodore 64s as second computers. This is part of the reason so much of this issue is devoted to the compatibility between SYM and -64. For those of you who are into RAE and SWP and like the 8 \emptyset column display of the KTM-2/8 \emptyset for your program development (with long ";" comments in your source code) and for word processing), here is some really good news, reproduced from the MAE manual:

MAE Macro Assembler/Text Editor for Commodore Computers

19. CONNECTION OF A SERIAL DEVICE

A serial device may be connected to your PET and controlled by MAE software. MAE generates data in TTY (or RS232) data format on the USER port (bit 7 pin L = output, bit 6 pin K = input). The data format consists of one start, seven data, and two stop bits. Since these signals on the user port are TTL levels, circuitry may be required to provide a proper electrical interface. We have found, though, that RS232 terminals such as the Synertek KTM-80 can be connected directly to the user port. If you do provide interface circuitry, you should not invert the signals as they are in positive true state.

The commands]TI and]TO are provided to direct MAE to input or output on this serial port.

18. CONTROL CODES (for Serial Device)

The following applies to the optional serial device connected to the PET. Ascii characters whose hex values are between hex 00 and 20 are normally non-printing characters. With a few exceptions, these characters will be output in the following manner: c where c is the associated printable character if hex 40 was added to its value. For example, ascii 03 will be output as C, and 18 as X, etc.

ENOTE: STP does not support the printing of the "^", so these were added
"by hand". Printing of the "^" can be provided by substitution of some
other seldom used character, such as "\", for the "symbolic space". We
have a special version of SWP for just this purpose!]

In addition, some of these control codes have special functions in MAE.

Control codes which have special functions are:

CODE		DESCRIPTION
6		Null (hex 00)
В		Restore zero page and go to Basic
С		Restore zero page and go to Monitor
G	*	Bell
H	*	Backspace (delete previously entered char.)
I	*	Horizontal tab to next 8-th char, position
J	*	Line feed
H	*	Carriage return
0		Continue processing but no output (same as DEL)
Q	*	Continue after stop via break key
Ì		Delete entrire line altered
Y		Restore zero page and jump to location \$0000.
-		(you may reenter at \$5003)
Z		Terminate processing and go to "}" level
ĺ	*	Escape character

* - Non-printing control character.

[NOTE: Compare this with page 8-1 of the RAE-1 Reference Manual.]

Copyright 1982 by Eastern House PAGE 63

The manual was written for the PETs, with 6502 and VIAs, but the MAE 64 version has been modified to work with 6510 and CIAs. The major changes are these:

- 1) 6502 Microsoft BASIC has its USR JMP at \$0000. Since the 6510 uses addresses \$00 and \$01 for its internal control port, the 6510 version of Microsoft BASIC puts the USR JMP at \$0310, instead. This implies a modification in the CTRL Y jump location.
- 2) The USER port on the COM-64 differs from that on the PET, using PA2 pin M = output, FLAG* pin B = input. Only a three wire cable is needed; all the software is there, already.

Once this newsletter is out we'll add a KTM-2/80 to our COM-64, and then, as far as RAE and SWP (MAE/STP) are concerned, it'll be as if we were still on a SYM, giving us the best of all possible worlds. Incidentally, MAE is the only 6502 assembler we have found where the Editor and Assembler are co-resident, and which is so beautifully integrated and co-resident with both BASIC and a very powerful, much extended ML monitor.]

WHAT TO DO WITH YOUR OLD SYM(S)

We have received so many letters of thanks and commendation that it almost makes us blush to think of them, and we are much too modest to even consider printing any of them. We make an exception in this one case, because of the extremely good suggestion of what one might do with his "retired" SYM.

Incidentally, in our four years with SYM-PHYSIS, we have received only two really harsh criticisms, and these were answered by advising the writer and the telephoner to re-read the documentation (of course, they had not yet even given it a first reading), to find out where they had failed.

SYM-PHYSIS 17-37

Dear Lux, Jean, and company:

I'm sorry to hear that the SYM line in coming to a halt, but I guess that's progress. I am especially sorry to hear the next issue will be the last, but I know (and you especially know) you've done a super job and it's probably best to quit while you're ahead. JUST WANTED YOU TO KNOW YOUR FOUR YEARS OF WORK HAVEN'T GONE UNNOTICED!!!! I still have all of my back issues, and someday when I give my grandkid my antique SYM-1, it will have a complete set of documentation and especially the entire set of user notes. Thanks for all of the good work. I look forward to the "farewell" issue. You have truly been involved in a pioneering effort and have set a standard for "interactive" user groups. So long.

Jon D. Jackson
Jon B. Jackson

205 Tapoco Drive Eglin AFB, FL 32542

A NOTE TO JON'S GRANDKID(S)

Your grandfather wrote that note above. He really thought about you often, even way back then! And best wishes from us, too. /s/ Lux & Jean

LISP, ANYONE?

NICK VRTIS sent the request for help with his SYM version of LISP on the postal card reproduced here. We enjoyed his TINY PILOT for SYM, and are looking forward to trying his finished LISP. We suggest that LISPers get in touch with Nick and take him up on his offer of a preliminary version.

Nick has been quite prolific with his SYM. He also sent along a copy of his SYM/CBM-1541 disk drive software.

Dear Rux

Dear Rux

Do you know anything about LISP? On can

you give me the rane of somebody with a

Sym who does. I have almost flinished on

version, but have written it from a discription of
the language and don't have weens to a "real" version

to comme against. I would be hoppy to exchange
a copy of the some for comments four postions additions

NICK VETTISEC S.E.

KENTWOOD, MI 29508

WHY THE SWITCH FROM SYM?

While there are "loners" in the computer field, as in any other hobby/profession, even loners feel the occasional need of an "audience" to whom they can proudly display what they have done, are doing, and are going to do. Thus, it can be much more ego-satisfying being associated with a computer with a large user base; such popularity tends to breed greater sales, and hence even more popularity, etc.

We have often felt quite frustrated when friends and/or acquaintances asked us about our personal computer, of which they had never before heard, and certainly had never seen advertised on television. Have any of you ever felt the same? It is, of course, much different with the Commodore! And how much great software is now becoming available!

We could recommend the SYM-1 only to our technically oriented friends, but the Commodore 64 is the ideal beginner's system, at a really low budget cost, for those who have not been deluded by the much over-rated sales talk of IBM or CP/M or S-100 compatibility, or the need for 16-bits, or more than 64 K of RAM. And that is why we switched our loyalty. Our only regret is that Synertek really missed out on a truly golden opportunity here.

We suggested to Synertek Systems, over three years ago, that they had a real "sleeper" in the SYM-1/KTM-2 combination, and that if they combined these two items on a single board, and threw in BAS-1 and RAE-1 FREE, at a price of, say, \$795, they might be able to compete quite seriously with Apple, etc. Such a system would have been far more useful than Rockwell's AIM-65, and could very well have become the "VW", or "Model T", or "Jeep", "work-horse" of the computer field. Instead Commodore filled the void, first with the VIC=20, then the Commodore 64.

Synertek Systems management decided to go for the OEM market instead, and leave the educational/hobbyist market to others. Commodore's success in keeping costs low has been attributed, in part, at least, to their "vertical integration", since they were in a position to make the majority of their own LSI chips. Synertek is certainly in the same position, and the parent corporation, Honeywell, does have some expertise in mass marketing.

Although we offered our services as a "Beta" test site to Synertek, we were never advised of any of their new products in advance. The first we ever heard of any of their new products, such as the SYM-2, Mod-69, KTM-3, etc., was by receiving a brochure, often long after their availability.

One product we did not even learn about until just this week, was the SYM-2/69, which uses the 6809 instead of the 6502. This would have been an ideal way to get started in the 6809 field, far less expensive than retrofitting the SYM-1 with the Mod-69 "upgrade" kit. This we think might have been a viable product, if anyone outside Synertek (and very few inside even knew) had known about it. We discovered its existence only when a former student told us that a friend had purchased one at a very low price, somewhere. He told us that it differed from the SYM-2 mainly in the fact that some of the sockets were in alternate positions on the board. Sure enough we examined a SYM-2, and discovered that alternate socket positions were provided for several chips. We then reexamined a SYM-2 schematic, and, sure enough, the schematic indicated that either the 6502 or 6809 could be installed!

We have the greatest admiration for the engineering which has gone into Synertek Systems products, especially into the versatility aspect. Never before have we seen boards with so many jumper and trace cutting and alternate socket options as in the Synertek Systems product line.

Now that they are switching to a new, non computer, DEM product line, which they are not yet ready to announce publicly, we wish them great SHICCRSS.

Meanwhile, we are very much enjoying helping many of our new friends, especially the teenagers, and the junior/senior high school teachers, get started "right" in the computer field. This is how we'll be spending our retirement.

AN "ALL-BASIC" BASIC DATA SAVER --- ---- ---- ----

We have begun to use BASIC much more frequently then in the past, SYM-PHYSIS 17-39 because so many of the COM-64 and VIC=20 programs we have seen lately are in their "natural" language, BASIC. We are much impressed with the skills which so many BASIC programmers have acquired in the use of PEEKs, POKEs, READs, and DATA statements to get the systems to do their bidding.

This is illustrated in the letter and sample program below, which shows how to modify the starting values of variables so that a SAVEd version of the program will now hold the "updated" starting values. This program is well worth studying to see how it can be done.

The SYM cassette interface is so much faster than that in the various Commodore systems that it might be well worth adapting the Commodore's idea of treating the cassette as an alternate I/O "device". and PRINT#ing and GET#ing variables from an automatically managed "cassette buffer" as SEQuential files. While we have learned a lot from a study of SYM's SUPERMON, there is a lot more to be learned, especially about I/O and data file management, from a study of the Commodore's "KERNAL".

In passing, it should be pointed out that the SYM's implementation of USR is far more powerful than that in any other version of Microsoft BASIC, in that an essentially unlimited number of parameters may be passed. It is even more powerful than the SYSs and CALLs included in other Microsoft BASICs.

Dear Lux,

My sons and I have put several sames into our SYM using BASIC. Some of the games are rather involved and utilize changing variables to make the same "go". Occasionally, usually due to supper or bedtime, a same will have to be interrupted. This results in shutting down the system and reloading and restarting the game at another time. What we needed was a way, to save the same with its current parameters. This requirement led to much experimentation and finally a method for accomplishing the soal. The short program which follows isn't very productive but it does illustrate a method for saving a program with its current parameters by poking the current values into a DATA statement in the beginning of the program.

Hopefully, some SYM user, somewhere, may be able to make use of it. It has proved helpful to us.

7 Enid Road

East Lyme, Ct. 06333

- 10 DATA001,001,001,001,0: REM ENTER THIS LINE WITH NO SPACES !
- 20 READ A, B, C, D, Y: V=10: W=V+2: U=48
- 30 E=A+B+C+D: PRINT A, B, C, D, E: Y=Y+1
- 40 A=A+1: B=B+2: C=C+3: D=D+4
- 50 IF Y=10 THEN Y=0
- 60 FOR F=1 TO 1000: NEXT F: PRINT CHR\$(26)
- 70 INPUT *(S)AVE OR (F)LAY OR (Q)UIT ? *;B\$
- 80 A\$=LEFT\$(B\$,1)
- 90 IF AS="Q" THEN END
- 100 IF A\$="P" THEN 30
- 110 G=INT(A/V):H=INT(A/W):J=A-V*G:K=518:L=519:M=520:GOSUB200
- 120 G=INT(B/V);H=INT(B/W);J=B-V*G:K=522;L=523:M=524:GOSUB200
- 130 G=INT(C/V):H=INT(C/H):J=C-V*G:K=526:L=527:H=528:GOSUB200
- 140 G=INT(D/V):H=INT(D/W):J=D-V*G:K=530:L=531:M=532:GOSUB200
- 150 POKE 534, Y+U: PRINT: PRINT
- 160 PRINT "PUT IN A TAPE AND PUT TAPE RECORDER IN RECORD MODE."
- 170 PRINT: INPUT "READY ? ";C\$: PRINT
- 180 SAVE A: PRINT * PROGRAM SAVED AS *; CHR\$(34); A*; CHR\$(34);
- 190 PRINT *WITH CURRENT PARAMETERS. *: END
- 200 I=G-V*H: POKE K, H+U: POKE L, I+U: POKE M, J+U: RETURN

A FINAL APOLOGY FOR THE UNANSWERED LETTERS

Every letter received here is opened and read by Jean on the same day it arrives. Jean handles the "business" aspects of the letters, usually on the very same day, if at all possible. The letters requesting help go into my "incoming" basket, and it is often several months before they can be read by me. [The truly "emergency" ones are handed to me directly, and Jean gets me to answer those at once.]

The letters average some 15-20 per week, and too many of them would take hours of "research" time to work out an answer. Thus, much too many of them have, of necessity, had to go unanswered. A certain percentage of the requests for help, fortunately, have been "self-answering", in the sense that the answers could be found by re-reading the documentation a little more carefully this time.

We have truly enjoyed working with SYM-PHYSIS; the only painful part was in being unable to keep up with the correspondence, and having to apologize for it in each issue. Again, please accept our apologies. The only time we feel less guilty about our negligence is when we realize that we are not alone (guiltiness loves company, we guess). Here's what Herb Caen, the San Francisco Chronicle columnist, has to say in his (i.e., our!) defense.



San Franciscaena

I DON'T MIND telling you that I get a lot of mail. The reason I don't mind is that I can now apologize publicly for not answering it all. Lordy knows we try, but 1000 or so letters a week pile up fast. Still, every letter deserves a reply. This is not the golden age of letter- writing, and I am still impressed that some friendly stranger in faraway Olema or Paradise will sit down, set pen to paper and unburden his or her thoughts on this subject or that to the friendly stranger

— 'tis I! — at this end of the line. In the age of instant communication — and rather iffy mail service — this is an amazing thing. My guilt increases exponentially with the height of the pile of unanswered mail teetering on the edge of my desk. Now and then, a few letters flutter off and into the wastebasket. It pains me to confess that sometimes I am too bushed to dredge them out.

ONCE, YEARS AGO, on the eve of a vacation, I picked up the entire batch and threw it in the wastebasket. It marked the first time I had seen the top of my desk in at least a decade. The action should have brought me release and relief, but it merely spoiled my vacation. I realize that a lot of letter-writers don't expect replies. It's the world we live in. Many is the time I get a delighted "Hey, you answered my letter! Don't you know nobody answers letters these days?", which gives me another letter to answer.

ULTRA HIGH PERFORMANCE SCOPE LINE DRIVER

As the years have gone by, the programs submitted for publication have grown better and better, but, unfortunately, have also grown much too long for publication in these few pages.

This is particularly true of a program submitted last fall by Leland Goertz. Rather than just letting the program get "lost", we'll print parts of Leland's material, so that those interested can contact him directly for a copy, as suggested in his letter. In "laboratory-type" applications an oscilloscope is frequently more easily available than a full terminal, and we can easily see the utility of his program in such an environment.

The last paragraph of his letter mentions some interesting things he has done with his SYM; some of you may wish to correspond with him on these also! And we really do agree with him on his comparison of SYM-1 vs. VIC=20, in spite of any contrary impression created by our comments elsewhere in this newsletter. We remember when the Commodore PET first appeared how unhappy so many initial purchasers were because there were no ML capabilities built-in, and how Commodore had to provide an ML Monitor (Tiny Mon) on cassette to satisfy them. The VIC=20 does really need a version of MAE in ROM to bring it up to SYM-1 power, but this is highly unlikely to appear. Anyway, we have a strong affection for both.

Dear Lux and SYM-1 users,

I am submitting the enclosed program, ULTRA HIGH PERFORMANCE SCOPE LINE DRIVER, for your consideration of publication in SYM-PHYSIS. If it is worthy of publication, you have my o.k..

The software is roughly based on the scope line driver supplied by SYNERTEK in the SYM REFERENCE MANUAL. All I have done is alter the way SYNERTEK'S driver accesses character data. For a futher inquiry into the differences between the two, I suggest studying the source code of each driver.

For those who have scopes with Z-axis modulation capabilities, there is an added plus (both with this driver and SYNERTEK'S). Connect the Z-axis probe to the base of Q10. This will rid the display of the bright base line and makes a much easier to read display.

SYM-PHYSIS 17-42

Because of my systems current configuation, the program has been assembled at \$C800. This can be altered to \$0200 by changing the following locations: 0246 ± 02 , 0261 ± 02 , 0281 ± 02 , 0286 ± 02 , 0288 ± 02 , $028F\pm02$, $028C\pm02$.

The driver will fit in a bare bones SYM with 2K of memory and still leave room for most programs that will run in 1K of memory.

I am sorry that I can not supply you with RAE source code on tape and hope that the enclosed photocopy is clear enough for publication. I have, however, enclosed a tape with the object code assembled at \$0200. A .G \$028C will start the driver. I will also supply any users' with the same tape for \$6.00. Please write or call the above address for orders.

The software is romable and contains the boot routines. The boot routines may be omitted if they are not going to be used. LOGTAB and CHRTAB can then be moved up to fill the hole that the omitted boot routines left.

I have been following Jeff Lavin's SUPER SYM article with much intrest. However, my SYM at this point in time is a \$50.00 per hour money maker. Thus, I, or my SYM, do not have the time to sit down and study the procedures on how to implement the modifications. I'm sure many other SYMmers are in a simular situation. So, I would like to suggest a step-by-step instruction sheet on how to implement the SUPER SYM. Of course, a fee would be charged, but the advantages of a SUPER SYM are worth such a fee!!!

I am sorry to hear the end of the users' group and to the end of the manufacturing of the SYM. Progress I guess. I do not, however, feel that the VIC 20 can replace the SYM. I have a VIC 20 and don't like it at all. I have used my SYM for a variety of things including a 12 projector multi-media system complete with program editor. a business security system, an automatic telephone dialer, and now in the medical field as a specialized floppy reformatter. I would hate to try to implement these things on a VIC 20. I have been using the SYM since my college days and received a degree in computer science mainly using the SYM. Call me loval to the royal.' Nothing will ever replace my SYM.

Leland Goertz 40573 Road 84 Dinuba, CA 93618 (209) 255-1765

le como Goertz

ISOFTWARE DESCRIPTION IS ON PAGE 17-443

A CALL TO COMPUTER ARTISTS

WALLER "WALLY" GLAB, a long-time SYMmer with a strong background in art, is part of a group of four artists working in the area of Computer Art. He would like to form a Special Interest Group for SYMmers, and, presumably others, working in this field, for the interchange of software and ideas. His address and telephone number are: 2538 N. Wayne, Chicago, IL 60614. (312) 525-7617.

We know that a number of readers have gotten together by mail or phone to exchange ideas and software in their own areas of interest, and hope that this will continue in the future. As you reread your back issues of SYM-PHYSIS, you may wish to contact some of the contributors and others whose addresses and phone numbers were published, for "updates", enhancements, etcetera.

ULTRA HIGH PERFORMANCE SCOPE LINE DRIVER

GENERAL

This software package enables SYM-1 users' to divert there output from the LEO displays to a 32 character oscilloscope display. Display format is the standard 5 \times 7 dot matrix. The driver supports the full 96 character ASCII set of printable characters. Characters may be added (up to 13,011) by writing the starting address of the new character data to PTRLO, and PTRHI.

OPERATION

The "vidio" signal is from the collector of Q10, and is 3 volts peak-to-peak with a cycle time of about 60ms. The sync pulse which begins the line should synchronize all triggered sweep scopes and most recurrent sweep scopes. The sync pulse may be brought out on a separate pin by replacing the code from SYNC to CHAR with a routine that would output a pulse on some other output line.

CONNECTION

Connect the oscilloscope vertical input to pin R on connector AA and connect the scopes ground to pin 1 of AA. For scopes with Z-axis modulation, connect the Z-axis probe to the base of Q10. This will rid the display of the bright base line. If the sync pulse was output on a seperate pin, connect the scopes trigger to this pin.

BOOT

The software may be started 1 of 3 ways. If the software is in a prom, the boot jumpers may be altered so that the system always boots to the scope driver. Using this method, the RST key will start the driver. A .G C88C (028C) will also start the driver. This is the starting address of the scope drivers boot routine. The third way to start the driver is to execute the following: SD C80O (020O)-A67O. This alters SCNVEC to point to the scope driver.

USAGE

Since the scope buffer resides in system ram, a JSR ACCESS must be performed before any writing to the scope buffer can occur. One scan of the scope buffer may be performed by calling LINE (\$C800 [\$020]). Line can be used in the same way that SUPERMON'S SCAND is used.

COMMENTS

This software is roughly based on the scope line driver supplied it the SYM REFERENCE MANUAL. For further information see chapter 7.

THE W65SC802

We have not yet replaced any of our 6502 chips with The Western Design Center's W65SC02 (list price \$9.50). We are doing a "paper study" of the advantages to be gained by switching, instead, to the W65SC002. There was a time when we were (very briefly) thinking of going to the 6809, but gave that idea up because of the complete lack of either hardware or software compatibility with the 6502. On the other hand the W65SC002 is totally compatible; just plug it in and go (list price is \$95.00!).

There will be no advantage in making the switch UNTIL and UNLESS an upgraded RAE is available, but it is still worth looking into the new "dream" chip. Complete specs for the entire WDC product line are available upon request. We are reprinting here some extracts from their Advance Information Data Sheet, so that you can begin to make your own decision on "switching".

I BITS	8 BITS	oming Model
Data Bank Reg. (DBR)	X Register Hi (XH)	X Register Low (X) (XL)
Data Bank Reg. (DBR)	Y Register Hi (YH)	(Y) Y Register Low (YL)
00	Stack Register H (SH)	(S) Stack Reg. Low (SL)
	Accumulator (B)	(C) Accumulator (A)
Program Bank Reg. (PBR)	Program (PCH)	(PC) Counter (PCL)
00	Direct Reg. Hi (DH)	(D) Direct Reg. Low (DL)
tatus Register (Coding	
STATUS REG. (P)	E	ULATION 1 = 6502
LINDE	ZERO -IRQ DISABLE ECIMAL MODE KREG. SELECT Y SELECT	1 = TAUE 1 = RESULT ZERO 1 = DISABLE 1 = TRUE 1 = 8 BIT 0 = 16 BIT 1 = 8 BIT 0 = 16 BIT

Address Mode

_			
1	Immediate	V 244 🗔 1	4G 🖂 RES
2	Absolute	ADY 🚍 2	39 🗀 +5 (OUT)
3	Absolute Long	ν1 (OUT) □ 3	>4 🗀 so
4	Direct	INO 🖂 🔩	37 🗀 🐠 (IN)
5	Accumulator	NC S	36 E NC
6	Implied	NMI 🖯 4	35 PMC
,	Direct Indirect Indexed (IND), Y	SYNC 7	# Pr w
á	• •	V00 🖂 8	33 🖂 👀
-	Direct Indirect Indexed Long (IND), Y Long	% □.	32 🔁 D1
9	Direct Indexed Indirect (IND, X)	A1 🖾 19 u	C80230 02
ю	Direct, X		
11	Direct, Y	A3 🖂 12	29 🗀 04
12	Absolute, X	4 □	28 🗀 05
3	Absolute Long, X	A4 3 14	27 D6 26 D7
14	Absolute, Y		26 D7 25 D A15
15	Relative	~ ∃;	24 HA14
16	Relative Long	~ = i	23 HA13
7	Absolute Indirect (Jump)	A10 19	22 HA12
A	Direct Indirect	A11 20	21 7 Yes
-		7	
9	Direct Indirect Long		
0	Absolute Indexed Indirect (Jump)		
1	Stack		

Casidu sudiuses, Militam C. Meuticu Tr

We are wondering what the future holds for WDC's 16-bitters. While the W65SC802 can be "retrofitted" into Apples, Ataris, SYMs, VICs (but not COM-64s), etc., by hobbyists and experimenters, such as ourselves, we do not see this as a big market, nor do we forsee any new systems being built around this chip.

22 Stack Relative

23 Stack Relative indirect Indexed

24 Block Move X. Y. C (Source, Destination, Block Length)

The 68000, Z-8000, and the 8086/8088 have become so firmly entrenched that the W658C816 will have a tough time getting established, especially since there are no semi-standard DUSse, such as FLEX, CP/M, MS-DOS, PC-DOS, built around the 6502. The strongest advantage it will have is that its instruction set is a superset of the 6502's, so that pre-existing software will only need to be reconfigured for the I/O and DOS peculiar to each system, and this can still be written with 6502 assemblers.

This is similar to what was done for the COM-64 CP/M card. Although a Z-80 chip is installed, the CP/M system software, including the BIOS and BDOS portions, is written in 8080 syntax, and the supplied assembler and debugger/disassembler are also only for the 8080. SYM-PHYSIS 17-45

		W65SC816 Instruc	tions (256 OP C	odes)
A.	The Origin	nal 6502 Instruction Set (151 Op Codes)	8.	New W65	SCXXX instructions (13 Op Codes)
1.	ADC AND	Add Memory to Accumulator with Carry	1	BRA	Branch Relative always
	ASL	"AND" Memory with Accumulator Shift Left One Bit (Memory or Accumulator)		PLX	Pull X from Stack
	BCC	Branch on Carry Clear		PLY	Pull Y from Stack
	BCS	Branch on Carry Set		PHY	Push X on Stack Push Y on Stack
6.	BEQ	Branch on Result Zero		STZ	
7.	BIT	Test Bits in Memory with Accumulator		TRB	Store Zero in Memory (Direct: Direct, X; Abs. Abs. X)
8	ВМІ	Branch on Result Minus	,	INB	Test and Reset Memory Bits Determined by
10	BNE BPI	Branch on Result Not Zero Branch on Result Plus	8	TSB	Accumulator A (Direct and Absolute) Test and Set Memory Bits Determined by
	BBK	Force Break	-		Accumulator A (Direct and Absolute).
12	BVC	Branch on Overflow Clear			
13	BVS	Branch on Overflow Set	C.	New W65	SCXXX Addressing Modes (14 Op Codes)
14	CLC	Clear Carry Flag	2	BIT	Test Bits in Memory with Accumulator (Direct X.
15	CLD	Clear Decimal Mode		050	Absolute, X; Immediate).
16	CLI	Clear Interrupt Disable Bit	_	DEC	Decrement (Accumulator)
17	CLV CMP	Clear Overflow Flag		Group I	Instructions (Direct Indirect (8 Op Codes))
19.	CPX	Compare Memory and Accumulator Compare Memory and Index X	4.	INC	Increment (Accumulator)
	CPY	Compare Memory and Index Y	5	JMP	Jump to New Location (Absolute Indexed Indirect)
21	DEC	Decrement Memory by One		Grown I In	and the second s
	DEX	Decrement Index X by One	U.	Group I II	structions with New Addressing Modes (48 Op Codes)
23.	DEY	Decrement Index Y by One		•	Direct Indirect Long Indexed with Y (8 Op Codes)
24	EOR	"Exclusive-or" Memory with Accumulator		•	Direct Indirect Long (8 Op Codes)
25	INC	Increment Memory by One		•	Absolute Long and Absolute Long Indexed with X
	INX	Increment Index X by One			(16 Op Codes)
27	INY	Increment Index Y by One		•	Stack Relative (8 Op Codes)
28	JMP	Jump to New Location		•	Stack Relative Indirect Indexed Y. (8 Op Codes)
29.	JSR	Jump to New Location Saving Return Address		ADC	Add Memory to Accumulator with Carry
30	LDA	Load Accumulator with Memory		AND	"AND" Memory with Accumulator
	LDX	Load Index X with Memory		CMP	Compare Memory and Accumulator
	LDY	Load Index Y with Memory		EOR	"Exclusive-or" Memory with Accumulator
	LSR	Shift One Bit Right (Memory or Accumulator)	5.	LDA	Load Accumulator with Memory
	NOP	No Operation	6.	ORA	"Or" Memory with Accumulator
35	ARO	"OR" Memory with Accumulator	7.	SBC	Subtract Memory from Accumulator with Borrow
	PHA	Push Accumulator on Stack	8.	STA	Store Accumulator in Memory
37.		Push Processor Status on Stack			·
	PLA PLP	Pull Accumulator from Stack Pull Processor Status from Stack	E.	New Push PEA	and Pull Instructions (7 Op Codes)
	ROL		١.	PEA	Push Effective Absolute Address or Immediate Data Word on Stack
41		Rolate One Bit Left (Memory or Accumulator)	2	PEI	Push Effective Indirect Address or Direct Data Word
	RII	Rotate One Bit Right (Memory of Accumulator) Return from Interrupt	_		on Stack
43	RTS	Acturn from Subroutine	3.	PER	Push Effective Program Counter Relative Indirect Ad-
44.	SBC	Subtract Memory from Accumulator with Borrow	_		dress or Program Counter Relative Data Word on Stack
45.		Set Carry Flag		PLB PLD	Pull Data Bank Register from Stack
	SED	Set Decimal Mode		PHB	Pull Direct Register from Stack Push Data Bank Register on Stack
47. 48.	·	Set Interrupt Disable Status		PHD	Push Direct Register on Stack
	STA	Store Accumulator in Memory Store Index X in Memory	8.	PHK	Push Program Bank Register on stack
	STY	Store Index Y in Memory	_		
51	TAX	Transfer Accumulator to Index X	٠,	REP	gister Instructions (2 Op Codes) Reset Status Bits Defined by
	TAY	Transfer Accumulator to Index Y	•	ner	Immediate Byte 1 = Reset
53.	TSX	Transfer Stack Pointer to Index X			0 = Do not change
54.		Transfer Index X to Accumulator	2	SEP	Set Status Bits Defined by
	TXS	Transfer Index X to Stack Register	-	02.	Immediate Byte 1 = Set
56.	TYA	Transfer Index Y to Accumulator			0 * Do not change
G.	New Regis	iter Transfer Instructions (8 Op Codes)	2	MVP	Move Block from Source (A Addressed) to Destination
1	TCD	Transfer C Accumulator to Direct Register D	_		(Y Addressed) Block Length Defined by C.
2	TDC	Transfer Direct Register D to C Accumulator			X, Y are Decremented.
	TCS TSC	Transfer C Accumulator to Stack Register			
5	TXY	Transfer Stack Register to Accumulator C Transfer X to Y	J.	New Co-P	rocessor Operations (1 Op Code)
6	TYX	Transfer Y to X	1.	COP	Co-Processor Instruction with Associated COP Vector
7	XBA	Exchange B and A			and ABORT Input Supports Co-Processing Function Le., Floating Point Processors, etc.
8	SCE	Exchange Carry Bit C with Emulation Bit E.			16., Floating Point Processors, atc
			K.	New Syste	m Control Instructions (3 Op Codes)
H.	New Brand	h, Jump and Return Instructions (6 Op Codes)	1.	STP	Stop-the-clock Instruction Stops the Oscillator Input
1	BRL	Branch Helative Long Always (16 Bit Relative — 32768			(or 02 Input) During 02 = 1. This Mode is Released When
		to + 32767) (Addressing Mode)			RES Goes to a Zero. System Initialization May Be Desired; However, if After RESET One Performed an
	JML	Jump Indirect Long			RTI, Program Execution Begins With the Instruction
	JMP JSL	Jump Absolute Long			Following the STP Op Code in Program Sequence
	JSR	Jump to Subroutine Long (Uses RTL for Return) Jump to Subroutine (Indexed Indirect)	2	WAI	Wait for Interrupt Pulls RDY Low and Is Cleared by IRQ
	RTL	Return from Subroutine Long			or NMI Active Input.
U.		Heront Hom Gabroume Cong	3.	MDM	There is One Reserved Op Code Defined as WDM Which
å.	New Block	(Move Instructions (2 Op Codes)			Will Be Used For Future Systems. The W65SC816
	MVN	Move Block from Source (X Addressed) to Destination			Performs a No-Operation.
		(Y Addressed), Block Length Defined by C.			

(Y Addressed), Block Length Defined by C.

X Y are incremented.

TAXAN MONITOR PROBLEM AND FIX

ART WILLIAMSON sent along the following note for users of Taxan monitors:

Sorry it took me so long to get this note to you about the Taxan display problem we had.

First symptoms of our failure were display blooming and loss of focus. This was followed by a loss of display.

We found a capacitor, C212 on our schematic to be defective. This component is messy to replace because it is under the shield in the horizontal section of the circuit board.

Two of our three displays had this failure.

Hope this is helpful to other owners of the Taxan unit. Still think it is a fine display.

PRODUCT LINE RECOMMENDATION

SERGE MATOVIC, of INCON Electronics Inc., 762 Damien Way, Mississauga, Ontario, Canada L5C 3H2, (416) 273-4499, has been keeping us posted on his company's products. These include a PROGRAMMER/EMULATOR, a SIMULATOR, and a PROGRAMMABLE CONTROLLER. The EMULATOR can be used to emulate the SYM.

While we have not actually tested the products (Serge offered a loan, but we had to decline because of time pressures), we have studied the detailed spec sheets and the photographs he sent, and these equipments are the kinds of "tools" we would want to have in a research or industrial environment.

We suggest that anyone interested in this class of products phone or write Serge for additional information, including price and delivery schedules.

FUTURE PLANS

As of this date there is no word as to who will be "carrying-on" the SYM-1 product line, although Synertek is still negotiating with several possible individuals and groups. It appears likely that Synertek will continue manufacturing SYMs as long as the demand remains at its present level, but not the KTM-2 series.

We will be traveling in Europe (and will try to contact or visit as many SYMmers as possible, especially those who have visited us here in Chico) from 9 April through 16 May, 1984. We have been invited to present a talk/seminar for the Department of Electrical Engineering Science of the University of Essex, by Nigel Helsby and Ian Dillworth, and we are looking forward to this, and to finally meeting them in person. We'll then spend two weeks visiting with some of our (U.S.) East Coast SYMmers.

During the months of April and May of 1984 no telephone or mail orders will be accepted, nor will inquiries or requests for help be handled. After 1 June 1984, the Users' Group will again be available for help, and as a source of software and documentation, and we will continue to be a source for Synertek's proprietary chips and spares.

SYM-PHYSIS 17-47

W65SC816 Microprocessor Op Code Matrix

T					T			LS	<u>.</u>					$\neg \neg$	-		
Ì	٥	٠, ا	2	3	4	5	6	7	٠.	9	A	8	С	0	E	F	
0	BRK s	ORA(d.x) 2 6	COP s 2 8	ORA ST	TSB d 2°5	0RA d 2 3	ASL d 2 5	ORA(31) 2 * 6	PHP s 1 3	ORA imm 2 2	ASL acc	PHD 5 1 4	158 a 3 ° 6	ORA a	ASL a 3 6	ORA at	0
1	BPL r 2 2	0RA(d).y	ORA (d)	ORA(sr).y	TRB d 2 • 5	ORA d.x	ASL d.x	ORA(di).y	CLC imp	ORA a y	INC acc	TCS imp	TRB a 3 ° 6	ORA a,x	ASL 2.x 3 7	ORA al ±	1
2	JSR a 3 6	AND(d.x) 2 6	JSL at	AND sr 2*4	BIT d 2 3	AND d 2 3	ROL 4	AND(di)	PLP s	AND IMM	AOL acc	PLD s 1°5	BIT a 3 4	AND a	ROL a	AND at	2
3	BM (2 2	AND(d).y	AND(d) 2°5	AND(sr).y 2 * 7	BIT d.x 2 4	AND d.x ? 4	ROL d x 2 6	AND(dl).y	SEC imp 1 2	AND a.y	DEC acc	TSC imp 1* 2	BIT a.x 3 ° 4	AND a.x	AOL a x	AND al.x	3
4	ATI s	EOR(d.x)	WDM Reserved	EOR SI	MVP xyc 3 * 7	EOR d 2 3	LSR d 2 5	EOR(d1) 2 * 6	PHA s 1 3	EOR imm 2 2	LSR acc	PHK s	JMP a	EOR a	LSR a	EOR at	4
5	8VC +	EOR(a) y 2 5	EGR (d) 2 5	EOR(sr).y 2*7	MVN xyc 3 * 7	EOR d.x	LSR d.x 2 6	EOR(di) y	CLI imp 1 2	EOR a,y	PHY s	TCO imp	JMP al	EOR a.x	LSR a.a	EOR al.x	5
6	915 s	ADC(d.s) 2 6	PER 5	ADC sr 2 * 4	512 d 2 ° 3	ADC d 2 3	80R d 2 5	AOC(di)	PLA S	ADC imm 2 2	1 2	ATL s	JMP (a) 3 5	ADC a	ROR a	ADC at	٠
7 MSD	BVS :	ADC(d).y	ADC(d)	ADC(sr).y	51Z d.x 2 4	ADC d.x 2 4	RO9 d,s	ADC(dl) y 2 * 6	\$ELIMP	ADC a.y	PLY s	TDC imp	JMP(a.x)	ADC a.x	ROR a.x	APC al.x	,
	BRA r	STA(d.x) 2 6	8AL rl 3 * 3	STA sr 2*4	STY d 2 3	STA d 2 3	SIX o	STA(di) 2*6	DEY imp	BIT imm 2 * 2	1 2	1 4 3	3 4	STA a	STX a	STA at	•
9	8CC /	STA(d).y	STA (d) 2 • 5	STA(sr).y 2*7	STY d.x 2 4	STA d.x 2 4	STX d.y	STA(dl).y 2 * 6	TYA imp	3 5	1 2	1* 2	3°4	STA a.x	STZ a.u	STA al.x	,
A	LDY imm	LDA(d,x)	LDX imm 2 2	LDA sr 2* 4	LDY d	LDA d 2 3	LDX d 2 3	LDA(dI) 2 6	TAY imp	2 2	1 2	PLB s	3 4	LDA s	LOX a	LDA al	^
В	8CS r	LDA(d).y	LDA(d) 2 * 5	LOA(\$1).y	LDY d.s	LDA d.x	LDX d.y	LDA(dily	CLV imp	3 4	1 2	1*2	LDY a.x	LDA a.x	LDX a.y	LDA at,s	В
С	CPY IMIT	CMP(d.x 2 6	REP imm 2 * 3	CMP sr 2 * 4	CPY d 2 3	S 3	DEC d 2 5	CMP(dI)	INY imp	2 2	1 2	1*3	CPY a	CMP a	DEC a	CMP at	c
D	BNE 1	CMP(d).1	2 ° 5	CMP(81).) 2# 7	PEI s 2*8	CMP d.x	DEC 6.1	2 4 6	CLD im	3 4	1.3	STP imp 1*3	3*6	3 4	3 7	4*5	0
E	CPX imm	SBC(d.z	SEP ima 2 * 3	SBC sr 2 * 4	LPX d	SBC 6	INC d	SBC(dl) 2 6	INX imp	2 2	1 2	1*3	3 4	SBC a	INC a	SBC at	£
F	BEQ r	SBC(d).1	SBC (d)	SBC(sr).)	PEA 1	SBC d.x	INC d.x	SBC(dl).1	SED IM		PLX 3	XCE imp	JSA(a.s	SBC a.E	INC a.s	SBC al.	<u>'</u>

* New W65SC816 Op Codes

W65SC02 Op Codes

Op Code Matrix Legend

INSTRUCTION MNEMONIC	(COMMENT)	ADDRESSING MODE
BASE NO. BYTES	(170	BASE NO. CYCLES

Note A complete assembler syntax description is available upon request.

The final data sheet will contain the assembler syntax mnemonics.

THE SYM-1/VIC-1541 CONNECTION

Part of the reason for the lateness of this final issue is the fun we were having with our Commodore Systems. We justified our lateness, to ourselves, at least, by telling ourselves that we must delay publication until the SYM-1/VIC-1541 Connection was available. Fortunately, Ron Jordan advised us that we should be getting the prototype for test and announcement this week. We thus hurriedly finished the first 48 pages today, so that they could go to the printer immanediately, and will publish Ron's material as a four page "quick-printed" supplement as soon as it arrives:

THE SYM-1/VIC 1541 CONNECTION

Our long awaited SYM-1/VIC 1541 Connection Package arrived today. We haven't yet tried it because the object code as supplied (at \$7000) conflicts with both our CODOS and FODS systems. Ron is using FDC-1 at \$9000. so he does not have the conflict. Since Ron supplied us the RAE source, we'll relocate the code to \$9000, and install it first on our CODOS system to download all our MTU graphics. Then we'll move it to our FODS/FDC-1 system at both \$7000 and \$9000. so that it can co-operate with either of these systems. Imagine, a triple-DOS SYM! The unit merely plugs on the A-connector, with an additional lead to the RST line, and the 1541 Drive cord just plugs directly into the unit. How simple, how elegant, how easily transportable, how inexpensive (the 1541 drives are now selling for less than \$250 in the US)! Ron has been working closely with Don Lewis, who has developed an AIM-65 version of the system; you can contact Jordan and Associates for either the SYM or AIM versions.

SYM-1 DISK OPERATING SYSTEM FOR THE COMMODORE

1541 DISK DRIVE

MONITOR LINKS

RAE LINKS

BAS LINKS

COPYRIGHT (C) 1983 by Ronald A. Jordan

Distributed by

JORDAN & ASSOCIATES

2611 Madrono Drive

Ann Arbor, MI 48103

INTRODUCTION

The SYM-1 DOS for the Commodore 1541 disk drive greatly expands the capability and compatibility of the SYM-1. Although several disk systems are available for the SYM-1, all are relatively expensive. In addition, each offers its own unique disk formating, which prevents disk interchangeability and greatly limits access to commercial and public software. The SYM-1 1541 DOS helps to fill this gap by using the Commodore 1541 disk drive to create Commodore compatible disks. Since the Commodore 1541 has the DOS built into it, the SYM-1 DOS can take advantage of the Commodore DOS features and reside in RAM or EPROM very compactly (approx. 2K). With the installation of SYM-1 1541 DOS the SYM-1 can become a much more powerful little computer that is easier and more enjoyable to use.

Functionally, the SYM-1 1541 DOS consists of four modules: the primitive routines, the MONITOR link, the RAE link, and the BAS link. The primitives include all of the low level routines needed to communicate with the Commodore 1541 disk drive over the serial bus. The SYM-1 has several different VIA ports that could be connected to the serial bus. However, the primitive interface routines are dependent on the selected bus configuration on the VIA. The standard VIA port configuration uses VIA #1 (Port A) on the A-connector. Other configurations are available upon request at a nominal fee. The MONITOR link interfaces with SYM-PHYSIS 17-49 SUPERMON. All commands are vectored through the unrecognized syntax vector (URSVEC) and may be easily enhanced or altered as desired. The commands include load and save memory to disk with the option for a relocated load. Other commands allow easy display of the disk directory, reading the error channel, changing the device number to another drive, and sending Commodore 1541 DOS commands. The assembler editor (RAE) link includes the monitor disk commands which are implemented through the DC command. The load and save commands use special forms of the PUT and GET commands. The load command will load RAE source files with the option for an append and the save will save the source files. Files may also be assembled from disk. To enter RAE. a simple monitor jump command is used which then completely configures the file parameters for a 28K (or whatever desired) system. The monitor may be reentered with a control C and all of the monitor commands are still available. To start BASIC a simple monitor jump command is also used, which configures BASIC for a 28K system with 80 columns and then patches in the new command processor using INVEC and OUTVEC. The disk commands are implemented through DUTVEC so that future commands may be added easily and used under program control. Examples might be OPEN and CLOSE commands which could enable writing data to disk. Numerous enhancements and utilities for all links will be available (see Utilities and Enhancements). Currently, BASIC load and save to disk commands are supported. The other disk commands are also available in BASIC. BASIC may be exited with a control C and then may be warm started with . θ without the loss of the BASIC text. Normal cassette I/O is functional in BASIC, RAE, and the monitor. With some precautions, the SYM-1 1541 DOS can function concurrently with the FDC-1 disk system.

The SYM-1 1541 DOS system includes the following:

- 1. Hardware interface module for the serial bus connection to the SYM-1. VIA #1. Port A. (optional configurations available)
- Complete source listing for the primitives, MONITOR, RAE, and BAS links with Cross Referenced Label Listing
- 3. Cassette tape with object code. (normal start address \$7000, but others available at no charge)
- 4. SYM-1 1541 DOS manual.
- 5. EPROM with object code for primitives and MONITOR links. (optional)
- 6. Source files on disk or cassette. (optional)

COMMAND SUMMARY

MONITOR LINK:

- 1. S2 xxxx,yyyy/FILENAME save memory to disk with the name
- 2. L2 /FILENAME load memory L2 xxxx/FILENAME relocated memory load
- 3. SC #x change device number
 - SC ! read error channel
 - SC ? list directory
 - SC .DISKCOMMAND send disk command
- 4. JØ cold start BASIC

J5 cold start RAE

RAE LINK:

- 1. PUT/FILENAME save source file
- 2. GET/FILENAME load source file

GET/FILENAME A append to source file

- 3. DC #x change device number
 - DC ! read error channel
 - DC ? list directory
 - DC .DISKCOMMAND send disk command
- 4. CT FILENAME continue on disk

BAS LINK:

- 1. CONTROL C exit to monitor
- 2. #SP "FILENAME" save program to disk
- 3. #LP "FILENAME" load program from disk
- 4. #DC "#x" (same as RAE LINK)
 - #DC "!" #DC "?"
 - #DC ".DISKCOMMAND"

UTILITIES AND ENHANCEMENTS

The basic SYM-1 1541 DOS provides the foundation on which future commands may be added. Several commands have already been written, such as append BASIC programs, a RUN command for BASIC to load and run a program, and OPEN and CLOSE commands to write data to disk. Some utilities are also available such as a disk copy program and a disk sector read/write program, but many more are planned. It is hoped many new enhancements and utilities may be provided as they become available at a very reasonable cost.

All prices include shipping and handling unless otherwise stated. Please allow 4-6 weeks for delivery. Overseas orders add \$10.00.

- (1) SYM-1541 DOS \$95.00
- (2) DOS Special I/O config. (add \$25.00)
- (3) EPROM option (add \$15.00)
- (4) Source files on disk or cassette (add \$25.00)

Address mail orders to the address above. For additional information, telephone on weekdays, 6:00 PM-9:00 PM EST, or weekends, 9:00 AM-6:00 PM EST, at (313) 663-6374.

A FINAL MESSAGE FROM DICK ALBERS

March 5,1984

Dear Lux,

I hope this reaches you before publication of the last issue of SYM-PHYSIS (SYM-PHYZILE?). I have been meaning to write for a long time now, but must plead preoccupation; I have been learning a new system - Radio Shack's Color Computer with the FLEX and OS-9 DOSes. It is an easy way to use up much more time than I really should. I recommend the CoCo to anyone who wants experience with a powerful operating system without expensive or complex hardware.

Thank you for publishing my programs. The latest ones in issue 15 caused Phil Kohl to suspect an ommission (see #16-39 bottom of page). I had the pleasure of visiting his home late last year (1983) and we discussed that (and many, many other things). Phil has modified MON on his SYM; we assume that is the reason he had trouble. It does point out a possible pitfall: if you modify a system, be prepared for incompatibilities.

The programs have an unusual history. Way back when, before I got RAE, I needed an editor and attempted to write my own. Although it was never finished, I learned a lot about writing programs. One of the things I learned was that hand assembly is hard and frustrating work. Efficient code is a must; the fewer bytes to key in by hand, the better.

That's where the CMP #\$ØD went; it's included in INCHR so I didn't put it in my code. Another lesson was that an assembler is a necessity for SYM-PHYSIS 17-51

serious programming. After I had RAE I didn't need my own editor, so work on it ceased. However, I couldn't have all that time and effort wasted so I salvaged these two subroutines and converted them to stand alone. They are very handy when I need their functions.

I have a tip for other programmers. Some time ago you published an example of RAE's conditional assembly capabilities. I can't find it in my library so I must rely on my memory and I can't refer to the issue, but I think it was written by our guru, Lux. This tip could be considered "self-defensive programming".

This should work with assemblers other than RAE, so it may be useful on other systems too. The source for a program may be assembled into two or more versions depending on the value of specific flags. The problem is remembering to properly set those flags before waiting a considerable length of time for an assembly to complete, only to find that Murphy has struck again.

Assume a program that can be assembled for either tape or disk but not both, and if neither flag is set the result is incomplete. In your permanent source leave both flags clear and include the first two of the conditionals shown below:

DE Ø ;Tape flag TAPE 9199 ;Disk flag DISK .DE Ø 0110 Ø13Ø TAPE+DISK ; Test for both clear IFE 6146 Ø15ØERROR NEED TAPE OR DISK FLAG SET *** Ø16Ø TAPE+DISK-1 : Test for both set IFN 6170 Ø18ØERROR TAPE AND DISK FLAGS BOTH SET *** Ø19Ø IFN TAPE Ø2ØØ Ø210; Tape version unique source *** Ø22Ø DISK IFN Ø23Ø 0240; Disk version unique source *** 0260; Source common to both versions .EN **627**0

A flag-setting error will cause RAE to attempt to assemble the meaningless "code" within one of the conditionals, which will cause an error message (even if listing is turned off with .LC) and assembly will stop early. This example used only two flags so only two Boolean tests are required; more flags and more complex relationships between them will require more complex tests.

Did you know that a "^Z" (control-Z) will work in place of "//" to exit RAE's auto-number mode? It will work anywhere on the input line, not just at the beginning, and any text on that line is ignored.

Finally I want to thank you and Jean for forming and continuing S.U.G. and all those who contributed their efforts. Without SYM-PHYSIS I would not have been able to learn nearly as much about programing and certainly would not have had as much fun doing so. Thank you all.

Very sincerely, Richard Albers

AND ONE FROM JEAN

Even though this is our last published contact with the SYM users community, I hope it will not be our last contact. From the very first day that Lux and I began this (ad)venture, we have made many hundreds of not just customers, but friends. Thanks to all of you, and especially to so many who very quickly turned an ordinary business call into a friendly personal one. It has been lots of fun —— let's keep in touch.

As ever, SYM-cerely yours,

Jean