

THE SYM-1 USERS' GROUP NEWSLETTER

VOLUME II, NUMBER 2 (ISSUE NO. 8) - SUMMER 1981 (AFR/MAY/JUN)

SYM-PHYSIS is a quarterly publication of the SYM-1 Users' Group, P. O. Box 315, Chico, CA 95927. SYM-PHYSIS and the SYM-1 Users' Group (SUG) are in no way associated with Symertek Systems Corporation (SSC), and SSC has no responsibility for the contents of SYM-PHYSIS. SYM is a registered trademark of SSC. SYM-PHYSIS, from the Greek, means the state of growing together, to make grow; to bring forth.

We welcome for publication all articles dealing with any aspect of the SYM-1, and its very close relatives. Authors retain all commercial congrights. Portions of SYM-FHYSIS may be reproduced by clubs and educational institutions, and adaptations of programs for other computers may be freely published, with full credit given and complimentary copies Provided to SYM-FHYSIS and the original author(s). Please include a self-addressed stamped envelope with all correspondence.

> Editor/Publisher: H. R. "Lux" Luxenbers Rusiness/Circulation: Jean Luxenbers Rennis Hall: Jack Brown Associate Editors: Jack Gierwic

SUBSCRIPTION RATES (1981):

USA/Canada - \$10.00 for a volume of four issues. Elsewhere - \$13.50. Make checks ragable in US dollars to "SYM-1 Users' Group", F. O. Box 315, Chico, CA 95927, Telephone (916) 895-8751.

Issue #0, the Introductors Issue (1979), and Issues 1 through 6 (1980), are available, as a mackage, for \$12,00, US/Canada, and \$16,00, First Class/Airmail, elsewhere.

COMMENTS & REMARKS

We started the Users' Group, and its newsletter, because no one else had. We feel that the main reason we were first is because we were among the fortunate few to receive a preproduction release of RAE-1 (on cassette), and were early able to recognize SYM/RAF's true potential. We immediately used RAE's editor for report writing. That's why we justified getting a personal computer in the first place (the educational value was pure bonus). From report writing to newsletter publishing was a natural step.

RAE's Editor has been enhanced as a word processor by SWP-1, which we have ungraded, to perhaps a SWF-1.4. There may be a SWF-2 released one day soon, but, since the source code is 'unprotected', most users have done their own customization. The fine Label Sort program by Cyr is a nice enhancement to RAE's Assembler section.

In this issue we sublish what we feel is one of the most useful utilities ever, a symbolic DISAssembler into RAE. The DISARAE combination makes an extremely powerful development tool.

We also publish a "beginners" level article on using the Hex Keypad as an ASCII input device. There is far more power available in SUPERMON

	0010	;		"HEXTOASCII"	
			TO U	SE THE HEXPAD FOR	ASCII INPUT'
	0030		RY	MATT WILSON, 137	ROSE STREET
	0050			YAGOONA NSW 2199,	
	0060				
			AND	ANNOTATED BY LUX	
	0080				
				patches INVEC to e Hex Keypad on t	
	0110	FINAUC Tru	THE CIT	e uex veakad ou c	ne sin-1.
		The SCOPE	dri	ver program publi	shed in the
	0130	fSYM-1 Ref	eren	ce Manual can be	patched through
				ou extend its pub	
				ter set, and trea	
				non-printing, yo: hirty-two charact	
				ns display. The	
				th (the enhanced)	
				alphanumeric ter	
					INYBASIC, or 2KSA,
	0220	footh of w	hich	work well, even	with only 4K.
		HEXTDASCII	. RA	\$0100	GOOD FOR UTILITIES
	0250			\$0F00	RAE USES PAGE 01,
	0260		.08	,	SO USE RAE'S BUFFER
	0270				
	0280	, SUPE	KMUN	SUBROUTINES	
		SAVER	, TIF	\$8188	
		GETKEY		\$88AF	
	0320	NOLABEL	.DE	GETKEY+\$0A	
		INCHR		\$8A1B	
		OUTCHR		\$8A47	
	0350	ACCESS	+ DE	\$8886	
	0370	; s	YSTE	1 RAM	
	0380				
		INVEC	· DE	\$A660	
0100- 20 86 8B	0400	DATON THIS	ICD	ACCECC	TO UNFROTECT SYSRAM
0100- 50 89 88	0410	FATCH. INVC	JSK	ACCESS	ID UNFRUIELT STSKAM
0103- A9 OE	0430		LDA	#L,HEX.ASCII	TO RESET INVEC JUMP
0105- A0 01	0440		LDY	#H,HEX.ASCII	
0107- 8D 61 A6	0450			INVEC+1	
010A- 8C 62 A6	0460			INVEC+2	
010D- 60	0470 0480		RTS		
		Note in t	he Fi	rogram below that	GET.ASCII must be
					noush used only once.
					aram main-line because
					ESXAF (which is built-
				are designed to	work together. The
	0550	761USFSHILL	13 UE	contact asea nere	23 WOLDII SOUGSINS!
010E- 20 15 01		HEX.ASCII	JSR	GET.ASCII	
0111- 20 47 8A	0570			OUTCHR	FULL DUPLEX NEEDS ECHO
0114- 60	0580		RTS	•	
0115- 20 88 81	0590	GET.ASCII	198	SAVER	NEEDED MAINLY FOR RETURN
0118- 4C B9 88	0610	ULI FROUIS		NOLABEL	RETURN IS VIA JMP RESXAF
	0620				

0630

.EN

COMMENTS & REMARKS (continued from 8:1)

than is documented in the manual, perhaps much more than even its creator(s) realized!

When we first started there was very little software for the SYM. Now there is far more coming in than we can possibly publish. One basis for selection for publication is the User Community's interests and hardware capabilities. We publish no FDRTH, tiny-c, FOCAL, XPLO programs, for example, since language groups constitute, in general, separate communities. We publish no Visible Memory or ColorMate graphics programs, because these would benefit only a small percentage of the readers.

Even so, however, a large number of excellent general interest software cannot be published because of space (and time) limitations. Most readers asked for fully commented source listings over disassemblies or object code listings, fully realizing the reduction in number of published programs this would mean. And now we feel guilty about withholding all the fine software being made available. So we ask your agreement on the following proposal:

As before, copyrights remain with the author; we ask only first publication rights, if published in SYM-PHYSIS, or one-time rights, if published as part of a general collection of six or more items, to be sold on a non-periodical basis. Authors would receive a complementary copy of the volume(s) containing their contribution(s).

SYMPHYSIS caries no advertising, hence revenue is from subscription only. Publication will remain 40 single-spaced pages (70% reduction). We will mention sources of interesting 'soodies' for the SYM - but, in deneral, no prices. We will recommend only those products we have personally evaluated and liked. If we like them enough and can pass on a price savings to our readers, we will market them through the Users' Group.

We have been asked by several sources to publish full descriptions, specifications, and price lists for their entire product lines as a service to our readers! We will be pleased to insert such materials with future issues as paid advertising. Contact us for rates. Each issue reaches over 1400 subscribers, many of whom share their copies.

A DEDUCTIVE STORY (FART II)

There is no need to continue this series because of a very welcome development. The May '81 issue of MICRO contains an excellent tutorial by Greg Paris, "How Microsoft BASIC Works", which is so comprehensive that we refer you to it instead.

An endnote states that the author 'has been doing postdoctoral research in neurobiology, and hopes to program microcomputer-based instrumentation for a living.' How many others are migrating from the biological to the computer sciences for economic reasons? We see this student (and faculty) trend on our own campus as well.

One correction: MICRO's editor notes that 'Integer variables are not supported by OSI and SYM BASIC'. He is only half-right (or is it half-wrong?). While OSI's BASIC does not support integer variables, giving an error for LET AX \pm 2.5, BAS-1 fully supports the 'X' suffix to variable names. For LET TESTX \pm 2.5, PRINT TESTX will return the correct value '2'.

(NOTE: We could only check out OSI's lower-precision version of Microsoft for failure to support '%', but we believe this may be true for the 9-digit version as well.)

SYM-PHYSIS 8:3

RAM VS ROM: HOW MUCH OF EACH?

A selected few SYMmers need no help in expanding their systems, particularly those who are disk-based. They are disassembling, re-"source"ing, enhancing, and relocating their RAEs, BASes, MONs, and BOSes, and moving their I/Os clear up to the top, to permit the maximum possible amount of contiguous RAM for their applications programs and data, as well as for their operating systems (which need not necessarily be contiguous).

RAE and BAS are reassembled to reside in the same BK block (since they are never co-resident), stored on disk, and recalled to RAM as needed. MON, too, lives on the disk, and could even be considered as merely a support to the IOS, since initial POR (Power-On Reset) is to the DOS BOOT. The original ROMs are removed and stored, and their address spaces are filled with RAM. The only ROM needed is for the DOS BOOT (the BOOTs for FODS and CODOS are well under 256 bytes). All of the VIAs and the RIOT (the 6532 with its RAM, I/O, and TIMER) so into the top one-half K of memory space.

Since they have the know-how to do all this, they need not worry about software compatibility, having the skills to adapt any programs they wish, not to mention the ability to write their own, with no help.

On the other hand, those of us with cassettes want a larger proportion of ROM, and are burning EPROMS to fill all available memory gaps! Cassettes have a real value for mass storage (we used them to back up our disk-based mailing lists until we provided a back-up disk system), but having RAE and BAS in ROM does save lots of time. We know, because our first RAE was provided us on cassette, and it does take time to read in two 4K blocks! Of course, that was part of the game, to help debug it before casting it permanently in silicon. And, for many months, till we got our EPROMmer going, we had to boot FODS on power-on or system crash (while designing the RAE/FODS and BAS/FODS linkages) from the cassette.

To summarize, a cassette based system needs lots of ROM support; a disk based system very little; on the other hand, a disk based system may not need as much RAM as might be expected, because an experienced programmer can "chain" and/or overlay programs and data, or invoke "virtual" memory.

Speaking of "virtual" memory, we are testing Jack Browh's SYM/FODS-FORTH designed for a 32K disk based system. Eight "screens" are resident, 104 additional are virtual; fetched as requested. Only the whirring and clicking of the disk drives lets you know of the fetch. Incidentally a screen is a FORTH text file of 16 64-character lines.

Only where time is truly of the essence, as in high res-olution animation graphics, or in real-time high frequency signal processing, can one never have enough RAM. Actually, when working with the computer in an interactive mode, we don't like being kept waiting for long periods, but the second or two necessary for a virtual memory access actually provides a "breathing spell" and can relax some of the tension!

Answay, we have never felt constrained personally by the 32K "ceiling" imposed on the RAM contiguity by the location of SUPERMON at \$8000, and feel that the "transportability" of software between SYMs is a far more important factor than RAM contiguity. We therefore leave MON in ROM, put our DOS(es) at \$6000-\$7FFF, and have the 24K contiguous RAM from \$0000-\$5FFF for applications. In one system we have installed the ColorMate at \$9000-\$9FFF, and in another we have filled this gap with utilities in RAM.

SYM-PHYSIS 8:4

SYSTEM EXPANSION SUGGESTIONS

The RAE-1 SEt defaults are appropriate for a 4K SYM, and BAS-1 can be useful even within only 4K. What we are saying is that the SYM-1 can be useful with NO off-board expansion. RAE-1 is greatly enhanced by the addition of SWP-1, and BAS-1 is made much more responsive by the addition of BBE-1. Both of these software packages require a minimum of BK, i. e., at least a 4K expansion.

A 4K expansion is very inexpensively provided by merely "piddy-backing" a second set of 2114's onto the existing set (they will cling together, or you may solder them, if you prefer), bending "free" their chip select pins (#8) and wiring the already decoded 10, 14, 18, 10 (all active low) lines directly to these pins in pairs.

Alternatively, you may use the Blalock 4K RAM Board to hold the added chips, but this will hide the Synertek logo! Also, it will cost you for 10 18-pin sockets, a pair of capacitors, a pair of short 16-wire flat jumper cables with 16-pin dip pluss on both ends, and a pair of 16-pin sockets.

A 4K SYM is nice, an 8K SYM is nicer, and a 16K, or 32K, or 64K, or 128K (see, it can be done with memory banking) would be even nicer. Here are some of the approaches we have tried for memory expansion, and our (definitely subjective) opinions.

MOTHERBOARDS: These were necessary in the days of expensive 4K boards; of which you needed many. Now with 32K on a single board, a simple (short — less than two inches in length) cable or special socket is all you need for interconnection. A good example is the 32K Beta DRAM Roard (Yes) you can intermix static and dynamic RAMS in a single system).

A second argument for the motherboard approach, was that you could then add RS-232C, 20 mA loop, cassette interface, printer interface, assorted parallel and serial I/O interfaces, timers, etc., via plus in boards. But, ALL OF THESE ARE ALREADY ON THE SYM! By tradition, motherboards are buffered, but tradition has not insisted that the bus be properly terminated, and this can lead to troubles. Also, on most motherboards some fancy rewiring is necessary to permit part of a 4K block to reside on the SYM and another part to be on a plus—in board. This makes it very difficult to make efficient use of the 3K block assigned to only three VIAs on the SYM.

We see no need for the KIM-4 bus conceived by MOS Technology for the KIM-1, and orphaned almost immediately by Commodore Rusiness Machines, in order to push the PET over KIM! If someone gave us a free boxful of S-100 boards we might consider setting a KIM to S-100 motherboard converter, not just to be able to use them, but to explore the idea of adding Z-80 CP/M power to the system. On second thought, we'd give up the idea, and donate the boards to a worthy cause. We'd rather explore the 6809/FLEX possibilities; we think the 6809 is perhaps the ultimate in 8 bit micros.

SINGLE BOARD EXPANSION: We like the idea of a single 4°x6° 32K DRAM cand plugging directly onto the SYM at the expansion connector, and hiding modestly underneath it. The Beta board is an example of this approach. The edge connector on the Beta board is designed to fit the "S-44" bus. This bus has a unique "anti-symmetric" pin assignment which, when used with 4K or 8K RAM boards, is indifferent to which way the board is inserted. Very safe, and no socket "key" needed. Fortunately the Beta designers also provided 44 holes on the card into which a right angled socket can be fitted from EITHER side. Depending on which side is selected, the board will extend out from, or tuck under, the SYM. (Note: We use the terms card and board interchangeably here)

We have dubbed this arrangement, in which the board can carry a socket which pluss directly onto the SYM Expansion Connector, the Reverse-KIM bus. Another example of such a card is the ColorMate. It has edge fingers for the Reverse-KIM bus. To use such a card (alone), either solder two 44-pin connectors together, back-to-back, mount the pair on the SYM fingers and insert the ColorMate in the free socket, or solder the luss of a 44-pin connector onto the ColorMate, and mount the socket onto the SYM's edge fingers.

DISK EXPANSION: If your memory expansion is motherboardless, you can still easily add a disk controller. We like the 4*x6" HDE controller, which happens to use the KIM-4 bus. We mounted the controller card to the bottom of SYM with strips of Velcro (tm) material, right beside the Beta board. We put 44-pin connectors on both boards and wired a "conversion" cable Joining the S-44 bus to the KIM-4 bus. The SYM with the two underslung add-on boards is now mounted atop a pair of 5 1/4" disk drives, and is "his" system, while the original VIM system is "hers". Jean and I can now work together, side by side, each at our very own computer, without having to resolve priorities, or resort to interrupts:

"CARD CAGE" EXPANSION: While the card case seems to resemble an enclosed motherboard approach, it differs in one very significant aspect. The motherboard contains no buffers, in fact no active or passive elements of any kind; it is a very simple two sided printed circuit board, serving merely to wire five 44-pin edge connectors in parallel. The distance from the SYM socket to the furthest socket is 3 1/4". We will discuss this approach in a separate article in this issue.

COLOR FOR THE SYN

Perhaps the strongest selling point for the Apple over the TRS-80 and the PET was its color graphics. We would like to remind you of Dick Turpin's ColorMate (see previous issues for reviews of this and other "MicroMate" products, and write for his new brochure). We were mildly disappointed that the highest resolution (6C and 6R) modes of the Motorola MC6847 Video Display Generator were not implemented in the ColorMate, since the resolution was then only half that of the Apple.

The reason for this limitation is best understood by examining the RAM requirements for the 3C and 3R modes. The "3" implies that 3K of RAM are required to support these modes. In addition, a "Control Register" is required. The 3K of RAM and the Control Register are assigned a full 4K address block. To implement the 6C and 6R graphics modes in this same direct manner would require an inconvenient 7K address block.

MicroMate now supplies the ColorMate Plus as a 3K RAM 'piddy-back' add-on for the ColorMate. The extra 3K are 'bank-switched' to permit 6K of RAM and the Control Redister to support 6C and 6R graphics in only 4K of SYM space. Also two 'pades' for 3C and 3R! We use \$9000-\$9FFF.

MicroMate also has a ROM Bank SwitchMate for the SYM which permits six ROMS and/or EPROMS to reside in sockets P1, P2, and P3. This could permit (we think, since we have not yet received ours) patches to RAE-1 (e.s., SWP-1) to co-reside in BAS-1 space, and BAS-1 enhancements to co-exist in RAE-1 space, with bank switching under program control.

We have seen cories of the ColorMate Users' Group Newsletter, published by MicroMate to provide customer support. Dick is to be commended for providing so much application software for his hardware products. And, speaking of newsletters and passing out commendations, let us mention Rockwell International's excellent support of the AIM-65 with their INTERACT, and Saturn Software's (Jack Brown) SOFTNEWS for SYM-FORTH and Extended SYM-RASIC.

SYM-PHYSIS 8:5

SYM-PHYSIS 8:6

MORE COLOR FOR THE SYM

We are now dealers for RCA products, having established an excellent Dunn & Bradstreet rating during our first year! We have had on order, for nearly five weeks now (six weeks was promised), the VP-3301. This unit offers an interesting alternative to the KTM-2 as an RS-232 terminal for the SYM-1; for those wishing color graphics and rather good single voice music capabilities. We are very much impressed with the published specifications, and will review its performance in Issue No. 9.

It permits either 24 rows of 40 characters (including lower case with descenders - better than the Apple!) or 12 rows of 20 characters (useful for those with impaired vision), and, with a set of 128 user defined characters (ahead of the KTM-2), provides interesting graphics, if the illustrations in their brochure are for-real. We will have to try it on the SYM durselves before we can comment further.

The VP-3303 is the deluxe model, with built-in RF Modulator (with sound subcarrier). If you are interested in either unit, write or shone RCA for literature, and contact us for delivery (slow) and prices (mildly discounted).

We plan to use ours mostly as a display, using the KTM-2/80 for "serious" terminal 1/0 because of its more "classical" keyboard.

ANOTHER WAY TO GO

When we bought our KIM-1, so many years ago, we bought a Micro Technology Unlimited (MTU) power supply to drive it. After reading Hal Chamberlin's now-classic article on computer music, we purchased the MTU DAC (Digital to Anglog Converter) Board and the Advanced Music Software Package to drive it. We have since gone Stereo-DAC, and are thrilled by the new Musical Instrument Synthesis Software Package (more on this elsewhere).

When we wanted high resolution graphics we ordered the MTU Visible Memory 8K RAM and its associated software. When we needed additional memory to bring the 8K on-board and 8K Visible Memory up to 32K, we purchased the now-discontinued 16K DRAM board, together with the MTU "Card File" for the three boards, or cards, one of which, the SYM, fits into the top slot. The system was totally reliable, even with no buffering on the little motherboard.

MTU decided not to set on the KIM-4 bandwason, since KIM-4, by definition, includes buffering, and to make the edge connector pinout essentially identical with that on the KIM (also now SYM and AIM). Be advised that KIM-4 boards do not, in seneral, fit the Card File. However the HDE Disk Controller (KIM-4), and all other 4°x6° cards of any pin-out, do fit into unwired 44-pin conhectors on the application connector side of the File, and are easily wired to the motherboard side or to the application connector socket.

We have described above our first 32K MTU/SYM expansion, but pointed out that the old 16K DRAM board has been discontinued. Since we are installing our old 16K board in the SYM at the school's Microprocessor Lab for student use, we needed some type of replacement. Our decision was to replace the old board with MTU's dual purpose 15 3/4 K RAM/Disk Controller Card. The 'missing' 1/4 K is occupied by a 256 byte 800TSTRAP ROM (which itself surrenders 8 bytes to serve as control redisters for the disk controller. For awhile we'll be using it purely as a RAM board. The only inconvenience is that the upper half of the memory is write-protected on reset, and must be unprotected by writing to one of the control registers. We will just add this little task to our standard log-on utility patch.

SYM-PHYSIS 8:7

AND MORE ON DISK SYSTEMS

With the MTU Disk Controller Card described above comes complete documentation and software (on an 8° disk) for the MTU CODOS (Channel Oriented Disk Operatins System). All you need add is one or more single or double density, single or double sided, 8° disk drives, power supplies, and interconnecting cables and you will have lots of on-line mass storage. Each SIDE of a double density, double sided disk holds 500 Kbytes. We will be adding one or more such drives this summer.

We have been studying COBOS, and find it to be very powerful, and fast, because of the DMA approach. We think we will like it. CODOS is already patched to RAE-1, and we will be generating the links to BAS-1. We will in the future support both CODOS and FODS. In fact, we have made arrangements with MTU to adapt and market SYM versions of all MTU software, since the KIM and AIM versions are not ready-to-so for the SYM.

We still like the 5 1/4° FODS system for personal use. It is much more compact, and 5 1/4° drives rotate only when accessed. The larger drives run continuously, and we find the noise distracting. So why the need for an 8° system? Because our subscription list of 1400 names spreads over three 5 1/4° diskettes, and to do a search or a sort requires shuffling and dealing diskettes like a deck of playing cards. That's why! Based on both personal and business experience, we feel that an 8° system is "overkill" for personal use, and that a 5 1/4° system requires too much manual disk handling for even a small business. We will, of course support both, because we purselves need both.

AN ABSOLUTELY ZERO-COST ASCII KEYBOARD

Was up in front of this issue, on page 8:2, to be specific, we give each of our readers an ABSOLUTELY FREE ASCII KEYBOARD. Actually, you already received it as a hidden bonus with your SYM. We're just telling you how to use it. Certainly we all knew that you could enter ASCII characters, at the cost of four keystrokes per character, by using the SHIFT and ASCII keys, followed by the two hex digit code. But you really need only two keystrokes per character.

Enter the published patch at \$0100 to change INVEC; it will fit the very minimum SYM. Then G 100 $\langle cr \rangle$. You can now input all MON commands by their ASCII hexcodes. For example, to input G 200 $\langle cr \rangle$, enter the sequence 47 32 30 30 0D (don't enter the spaces). Try using the M command to modify the memory. Use 4D instead of M, 20 (space) instead of the right arrow, to advance, and OD instead of CR to terminate a command. You may use either 2D (-) or 2C (,) as the delimiter between parameters. Instead of LD 2 $\langle cr \rangle$ (actually L2 $\langle cr \rangle$), use 4C 32 OD, etc.

We had fun usins this, relocated out of harm's way, up in the unused scope buffer, with BASIC and RAE, usins the video monitor on the KTM-2 as our display. With RAE you must NOP the echo in line 570, since RAE handles TECHO in its own way. Of course, we prefer the full terminal, but if you implement the approach followed by Len Green on page 2-21, scrolling alphanumerics slowly along the six seven-segment displays, you will have full alphanumeric capability at zero cost. And if you expand the character generator for the scope output program to include the full set of alphanumerics and control codes, you will have a 32-character horizontal scrolling display, analogous to the ticker-tape hard copy in use before roll paper was added-on to the old TTY, back in the good old days (remember the old newsreels of the ticker-tape parades?). We can also consider the scope display as "free", since you buy a scope as test gear, not as an I/O unit! This could be lots of fun with Tiny BASIC.

Now let's give credit where it is due; the idea is not ours. It was (continued on page 8:20) SYM-PHYSIS 8:8

```
0010 ; HISSINK'S SYMBOLIC DISASSEMBLER
                                                                                                       0670
                 0020
                                                                                                       0880
                                                                                      3013- E8
                                                                                                                        INX
                 0030
                                  .BA $3000
                                                                                      3014- 86 E5
                                                                                                       0690
                                                                                                                        STX *PARTIAL
                 0040
                                  .08
                                                                                      3016- BD 01 34
                                                                                                       0700 MSG3
                                                                                                                        LDA MESS3+X
                 0050
                                  , ES
                                                                                      3019- F0 06
                                                                                                       0710
                                                                                                                        BEQ FIN.3
                 0060
                                                                                      301B- 20 63 A6
                                                                                                       0720
                                                                                                                        JSR OUTVEC
                 0070 ;
                               DATA LOCATION DECLARATIONS
                                                                                      301E- E8
                                                                                                       0730
                                                                                                                        INX
                 0080
                                                                                      301F- DO F5
                                                                                                       0740
                                                                                                                        BNE MSG3
                 0090 STEP
                                  .DE $5
                                                                                      3021- 20 IB 8A
                                                                                                       0750 FIN.3
                                                                                                                        JSR INCHR
                                  .DE $D3
                 0100 PGM.FTR-
                                                                                                                        CMP #'D
                                                                                      3024- C9 44
                                                                                                       0760
                 0110 LBL.PTR
                                  .DE $D5
                                                                                      3026- FO 1E
                                                                                                                        BER CONT
                                                                                                       0770
                 0120 PARTIAL
                                  .DE $E5
                                                                                      3028- C9 4C
                                                                                                                        CMP #1L
                                                                                                       0780
                 0130 PTR.STRT
                                  .DE $E6
                                                                                      302A- DO 06
                                                                                                                        BNE GO.RAE
                                                                                                       0790
                 0140 RUN.NU
                                  .DE $E8
                                                                                      302C- A0 80
                                                                                                       0800
                                                                                                                        LBY #$80
                 0150 END
                                  .DE $E9
                                                                                      302E- 84 E5
                                                                                                       0810
                                                                                                                        STY *PARTIAL
                 0160 FORMAT
                                  .DE $EB
                                                                                      3030- DO 14
                                                                                                                        BNE CONT
                                                                                                       0820
                 0170 LENGTH
                                  .DE $EC
                                                                                                       0830
                                  .DE $ED
                 0180 LMNEM
                                                                                                       0840 GO.RAE
                                                                                      3032- 4C DE 30
                                                                                                                        JMP RAE RTN
                 0190 RMNEM
                                  · DE SEE
                                                                                                       0850
                 0200 YSAVE
                                  .DE $EF
                                                                                     3035- A2 00
                                                                                                       0860 PASS2
                                                                                                                       LIX #0
                 0210 PCL
                                  . DE $FO
                                                                                     3037- BD 3B 34
                                                                                                       0870 MSG.4
                                                                                                                        LDA MESS4,X
                 0220 PCH
                                  .DE $F1
                                                                                      303A- F0 06
                                                                                                       0880
                                                                                                                        BEQ FIN.4
                 0230 LBL.IDX
                                  .DE $F2
                                                                                                                        JSR OUTVEC
                                                                                     303C- 20 63 A6
                                                                                                       0890
                 0240 TEMP
                                  .DE $F4
                                                                                     303F- E8
                                                                                                       0900
                                                                                                                        INX
                 0250 INVALID
                                  .DE $F5
                                                                                     3040- DO F5
                                                                                                       0910
                                                                                                                       BNE MSG.4
                 0260 LINE.NU
                                  .DE $F6
                                                                                     3042- A0 40
                                                                                                       0920 FIN.4
                                                                                                                       LIY #$40
                 0270 TXT.LOW
                                  .DE $100
                                                                                                                       STY *PARTIAL
                                                                                     3044- 84 E5
                                                                                                       0930
                 0280 LBL.LDW
                                  .DE $104
                                                                                                       0940
                 0290
                                                                                     3046- A2 00
                                                                                                       0950 CONT
                                                                                                                       LDX #0
                 0300 ;
                               SYM ROUTINES USED
                                                                                     3048- BD DD 33
                                                                                                      0960 MSG1
                                                                                                                       LDA MESS1,X
                 0310
                                                                                     304B- FO 06
                                                                                                                       BEQ FIN.1
                                                                                                       0970
                 0320 INBYTE
                                  .DE $81D9
                                                                                                                       JSR DUTVEC
                                                                                     304D- 20 63 A6
                                                                                                      0980
                 0330 NIBASC
                                  .DE $8309
                                                                                                       0990
                                                                                                                       INX
                                                                                     3050- E8
                 0340 INCHR
                                  .DE $8A1B
                                                                                     3051- DO F5
                                                                                                                       BNE MSG1
                                                                                                       1000
                 0350 ACCESS
                                  .DE $8B86
                                                                                     3053- 20 D9 81
                                                                                                      1010 FIN.1
                                                                                                                        JSR INBYTE
                 0360 TECHO
                                  .DE $A653
                                                                                     3056- 85 E7
                                                                                                       1020
                                                                                                                       STA *PTR.STRT+1
                 0370 OUTVEC
                                  .DE $A663
                                                                                     3058- 20 D9 81
                                                                                                                        JSR INBYTE
                                                                                                      1030
                 0380 RAE.WARM
                                  .DE $8003
                                                                                     305B- 85 E6
                                                                                                                       STA *PTR.STRT
                                                                                                       1040
                 0390
                                                                                     305D- A2 00
                                                                                                                       LIX #0
                                                                                                       1050
                 0400 ;
                              MACRO DEF'NS
                                                                                     305F- BD FO 33
                                                                                                      1060 MSG2
                                                                                                                       LDA MESS2,X
                 0410
                                                                                     3062- F0 06
                                                                                                      1070
                                                                                                                       BEQ FIN.2
                 0420 !!!SZ
                                  .MD (ADR.1 ADR.2) #SET ADR - Z PAGE
                                                                                     3064- 20 63 A6
                                                                                                                       JSR OUTVEC
                                                                                                      1080
                 0430
                                  LDA *ADR.1
                                                                                     3067- E8
                                                                                                       1090
                                                                                                                       INX
                 0440
                                  STA *ADR.2
                                                                                     3068- DO F5
                                                                                                       1100
                                                                                                                       BNE MSG2
                 0450
                                  LDA *ADR.1+1
                                                                                                                        JSR INBYTE
                                                                                     306A- 20 D9 81 1110 FIN.2
                 0460
                                  STA *ADR.2+1
                                                                                                                       STA *END+1
                                                                                     306D- 85 EA
                                                                                                      1120
                 0470
                                  . ME
                                                                                     306F- 20 D9 81
                                                                                                      1130
                                                                                                                       JSR INBYTE
                 0480
                                                                                                                       STA *END
                                                                                     3072- 85 E9
                                                                                                      1140
                 0490 !!!SA
                                  .MD (ADR.1 ADR.2) ;SET ADR - MEM TO Z PAGE
                                                                                                      1150
                 0500
                                  LDA ADR.1
                                                                                     3074- 24 E5
                                                                                                      1160
                                                                                                                       BIT *FARTIAL
                 0510
                                  STA *ADR.2
                                                                                     3076- 50 07
                                                                                                      1170
                                                                                                                       BVC PA.1
                 0520
                                  LDA ADR.1+1
                                                                                     3078- Á9 00
                                                                                                      1180
                                                                                                                       LDA #0
                 0530
                                  STA *ADR.2+1
                                                                                     307A- 85 E5
                                                                                                                       STA *PARTIAL
                                                                                                      1190
                 0540
                                  . ME
                                                                                                                       JMP PA.2
                                                                                     307C- 4C C3 30
                                                                                                      1200
                 0550
                                                                                                      1210
                0560 ;
                              GET START AND END ADDRESSES
                                                                                                      1220
                                                                                                                    DIS PROGRAM
                 0570
                                                                                                      1230
3000- 20 44 34
                                  JSR TOGGLE
                0580
                                               TURN ON ECHO
                                                                                                      1240 PA.1
                                                                                                                       SA (LBL.LOW PGM.PTR)
                0590
                                 LDA #0
                0600
                                 STA *RUN.NU ;ZERO BIT 7
                                                                                     307F- AD 04 01
                                 STA *INVALID
                0610
                                                                 SYM-PHYSIS 8:9
                                                                                     3082- 85 D3
                                                                                                                                                       SYM-PHYSIS 8:10
                0620
                                 LDX #$12
                                                                                     3084- AD 05 01
                0630 MOVE1
                                 LDA *$E5,X
                                                                                     3087- 85 D4
3000- 90 50 34
                                 STA Z.STORE+1,X
                                                        JSAVE ZERO PAGE
                0640
                0650
                                 DEX
                                                                                                                                    JÁLWAYS - FIRST RUN TO SET UP LELS
                                                                                     3089- DO 16
                                                                                                      1250
                                                                                                                       BNE DIS.AS
```

3003- A9 00

3005-85 E8

3007- 85 F5

3009- A2 12

300B- B5 E5

3010- CA

3011- 10 FB

0660

BFL MOVE1

	1260 START	SA (TXT.LOW FGM.FTR)	3101- 69 00 1740		: # 0	
			3103- 85 F7 1750 DI		*LINE,NU+	- 1
308B- AD 00 01			3105- 20 B9 32 1760	JSR	A.STORE	
308E- 85 D3			3108- D8 1770	CLI		
3090- AD 01 01			3109- A5 F4 1780	LDA	*TEMP	
3093 85 D4			310B- C9 60 1790	CMF	#\$60	₹RTS?
			310D- F0 08 1800	BEG	COMMENT	
3095- A9 95	1270	LDA #\$95 SET START LINE NUMBER	310F- C9 4C 1810	CMF	#\$4C	FUMP?
3097 85 F6	1280	STA *LINE.NU	3111- F0 04 1820	BEG	COMMENT	
3099~ A9 00	1290	LDA #0	3113- C9 6C 1830	CMF	#\$6C	;(JMP)?
309B- 85 F5	1300	STA *INVALID	3115- DO OD 1840		CK+LBL	
309D- 85 F7	1310	STA *LINE.NU+1	3117- A5 F5 1850 Ct		*INVALID	
309F- 85 F4	1320	STA *TEMP	3119- DO 09 1860			; IN DATA MODE
3071 03 14	1330 DIS.AS	SZ (PTR.STRT PCL)	311B- A9 BB 1870			; ';'
	1021 2131111		311D- 20 B9 32 1880		A.STORE	
30A1~ A5 E6			3120- 85 F4 1890		*TEMP	
30A3~ 85 F0			3122- DO CE 1900		INC.LINE	
			1910	2.112	211012112	
30A5- A5 E7			and the second s	v (5) 100	LABEL	CHECK IF LABEL REQUIRED
30A7- 85 F1			3124- 20 CB 32 1920 CM 3127- BO 13 1930			INO
	4740 EGVEL	JSR INST.DIS ;DISASSEM AND DSPLY INSTR			#'L	7110
	1340 DSMBL		3129- A9 4C 1940			
30AC- 20 8B 32		JSR PCADJ	312B- 20 B9 32 1950		A.STORE	
30AF- 85 F0	1360	STA *PCL ;UPDATE PCL,H TO NEXT INSTR	312E- A5 F1 1960		*PCH	•
30B1- 84 F1	1370	STY *FCH	3130- 20 A0 32 1970		ASC.STORE	
3083- C4 EA	1380	CPY *END+1	3133- A5 F0 1980		*PCL	-
3085 90 F2	1390	BCC DSMBL	3135- 20 A0 32 1990		ASC.STORE	
30B7- DO 06	1400	BNE SET.RUN #PCH=END+1	3138- A9 00 2000		#0	
30B9- A5 E9	1410	LDA *END	313A- 85 F5 2010		*INVALID	
30BB- C5 F0	1420	CMP *PCL	313C - A9 20 2020 NO		#\$20	
30BD- BO EA	1430	BCS DSMBL	313E- 20 B9 32 2030		A.STORE	
30BF- 24 E8	1440 SET.RUN	BIT *RUN.NU ; CHECK BIT 7 FOR RUN *	3141- A5 F5 2040 OF		*INVAL.II	
3001- 30 13	1450	BMI FINISH	3143- DO 22 2050		ERR	
	1460 PA+2	SZ (PGM.FTR LBL.PTR) FSET END LABEL FILE	3145- A2 00 2060		#0	
			3147- A1 FO 2070	L, I) A	(FCL+X)	GET OPCODE
3003- A5 D3			3149- A8 2080	TAY		
30C5- 85 D5			314A- 4A 2090	LSR	Α	;EVEN/ODD TEST
3007- A5 D4			314B- 90 OB 2100	BCC	IEVEN	
3009- 85 D6			314D- 4A 2110	LSR		FTEST BIT 1.
			314E- BO 17 2120	BCS	ERR	;XXXXXX11 INSTR INVALID
30CB- A9 80	1470	LDA #\$80	3150- C9 22 2130	CMF	#\$22	
30CD- 85 E8	1480	STA *RUN.NU	3152- FO 13 2140	BEG		;10001001 INSTR INVALID
30CF- A5 E5	1490	LDA *PARTIAL	3154- 29 07 2150	ANI	#\$07	MASK 3 BITS FOR ADDRESS MODE &
30D1- FO B8	1500	BEQ START	3156- 09 80 2160	ORA	#\$80	FADD INDEXING OFFSET
30D3- 4C 35 30	1510	JMP PASS2	3158- 4A 2170 IE			FLSB INTO CARRY FOR
0020 10 00	1520		3159- AA 2180			GHT TEST BELOW
30D6- 20 A0 32		JSR ASCISTORE #MOVE POINTER UP 2	315A- BD FF 32 2190			FINDEX INTO ADDRESS MODE TABLE
3009- A9 00	1540	LDA #0	315D- BO 04 2200			FIF CARRY SET USE LSD FOR
30bs- 20 B9 32		JSR A.STORE ; MARK END OF TEXT	315F- 4A 2210	LSR		FRINT FORMAT INDEX
	1560 RAE RTN	LDX #\$12	3160- 4A 2220	LSF		
30DE- A2 12	1570 MOVE2	LDA Z.STORE+1,X ; RESTORE ZERO PAGE	3161- 4A 2230	LSR		; IF CARRY CLEAR, USE MSD
		STA *\$E5;X	3162 4A 2240	LSF		
30E3- 95 E5	1580 1590	DEX	3163- 4H 2240 3163- 29 OF 2250 RI			; MASK FOR 4-BIT INDEX
30E5- CA		BPL MOVE2	3165- DO 04 2260			;\$0 FOR INVALID OF CODES
30E6- 10 F8	1600	JSR TOGGLE FRESTORE TÉCHO		i contract of the contract of		SUBSTITUTE \$80 FOR INVALID OF
30E8- 20 44 34						SET PRINT FORMAT INDEX TO 0
30EB- 4C 03 B0		JMP RAE.WARM	3169- A9 00 2280 3168- AA 2290 GE			FOULTHAM LONDING TOREN TO V
	1630	ETT ACIDA MI		C. I F T T T T T T T T T T T T T T T T T T	MODERLY	FINDEX TO PRINT FORMAT TABLE
30EE∸ 24 E8	1640 INST.DIS	BIT ARUNARU	316C- BD 43 33 2300	LUF	I HUDEETA . WENDMAT	SAVE FOR ADDRESS FIELD FORMAT
30F0- 10 4F	1650	BPL OF CODE FRIT 7 = 0	316F- 85 EB 2310			FASK 2-BIT LENGTH 0=1-BYTE
30F2- 18	1660 INC.LINE	CLC	3171- 29 03 2320			;1=2-BYTE, 2=3-BYTE
30F3 F8	1670	SED	3173- 85 EC 2330			
30F4- A5 F6	1680	LDA *LINE.NU	3175- 98 2340	1.11	JOF CODE	
30F6- 69 05	1690	ADC #STEP	3176- 29 8F 2350		#\$8F	; MASK IT FOR 1XXX1010 TEST
30F8- 85 F6	1700	STA *LINE.NU	3178- AA 2360		SAVE IT	
	1710	JSR A.STORE	3179- 98 2370			E TO 'A' AGAIN
30FD- A5 F7	1720	LDA *LINE.NU+1 SYM-FHYSIS B:11	317A- AO 03 2380		#\$03	SYM-PHYSIS 8:12
30FF- 90 02	1730	BCC DIS.A	317C- EO 8A 2390	CF:X	#\$8A	51n-rn1313 0+14

```
INC *FCL
                                 BEQ MNNDX3
                                                                                     31F6- E6 F0
                                                                                                      3060
317E- FO OB
                 2400
                                                                                     31F8- DO 02
                                                                                                      3070
                                                                                                                       BNE =+3
3180- 4A
                 2410 MNNDX1
                                 LSR A
                                                                                                                       INC *FCH
                                               FORM INDEX INTO MNEMONIC TABLE
                                                                                     31FA- E6 F1
                                                                                                      3080
3181- 90 08
                 2420
                                 BCC MNNDX3
                                                                                                                       JSR LABEL
                                                                                     31FC- 20 CB 32
                                                                                                      3090
3183- 4A
                 2430
                                 LSR A
                                                                                                                       DEC *PCL
                                                                                     31FF- C6 F0
                                                                                                      3100
                                               ;1XXX1010 -> 00101XXX
3184- 4A
                 2440 MNNDX2
                                 LSR A
                                                                                                      3110
                                                                                                                       LDA *YSAVE
3185- 09 20
                                                                                     3201- A5 EF
                                 DRA #$20
                                               ;XXXYYY01 -> 00111XXX
                 2450
                                                                                                                       STA *PCH
                                                                                     3203-85 F1
                                                                                                      3120
3187- 88
                                 DEY
                                      ;XXXYYY10 -> 00110XXX
                 2460
                                                                                                                       BCS END.NMEM
                                                                                     3205- BO OE
                                                                                                      3130
                                              *XXXYY100 -> 00100XXX
                                     MNNDX2
3188- DO FA
                 2470
                                                                                                                       SEC
                                                                                     3207- 38
                                                                                                      3140
318A- C8
                 2480
                                  INY
                                      *XXXXX000 -> 000XXXXX
                                                                                                                       LDA *PGM.PTR
                                                                                     3208- A5 D3
                                                                                                      3150
318B- 88
                 2490 MNNDX3
                                 DEY
                                                                                                                       SBC #4
                                                                                     320A- E9 04
                                                                                                      3160
318C- DO F2
                                 BNE MNNDX1
                 2500
                                                                                                                       STA *PGM.FTR
                                                                                     320C- 85 D3
                                                                                                      3170
                                 LDX #$03
                                               CHAR COUNT FOR MNEMONIC PRINT
318E- A2 03
                 2510
                                                                                     320E- BO 02
                                                                                                                       RCS =+3
                                                                                                      3180
3190- A8
                 2520
                                 TAY
                                                                                                                       DEC *FGM.PTR+1
                                                                                     3210- C6 D4
                                                                                                      3190
3191- B9 5D 33
                 2530
                                 LDA MNEML,Y
                                                                                                                       JMP ERR
                                                                                     3212- 4C 67 31
                                                                                                      3200
                                 STA *LMNEM
                                               FETCH 3-CHAR MNEMONIC
3194- 85 ED
                 2540
                                                                                                      3210
                                 LDA MNEMR,Y
                                               (PACKED IN TWO BYTES)
3196- B9 9D 33
                 2550
                                                                                                                                     COUNT FOR 6 PRINT FORMAT BITS
                                                                                     3215- A2 06
                                                                                                      3220 END.NMEM
                                                                                                                       LIX #$06
3199- 85 EE
                                 STA *RMNEM
                 2560
                                                                                     3217- E0 03
                                                                                                      3230 PRADR1
                                                                                                                       CPX #$03
                                 BIT *RUN.NU
319B- 24 E8
                 2570
                                                                                                                                     FIF X=3 THEN PRINT ADDRESS VAL
                                                                                                                       BNE PRADR3
                                                                                     3219- b0 21
                                                                                                      3240
                                 BEL ENDINHEM
3190- 10 76
                 2580
                                                                                                                       LDY *LENGTH
                                                                                     321B- A4 EC
                                                                                                      3250
319F- A9 00
                 2590 PRMN1
                                 LDA #$00
                                                                                                                       BER PRADRS
                                                                                                                                     IND PRINT IF LENGTH = 0
                                                                                     321D- FO 1D
                                                                                                      3260
31A1- A0 05
                 2600
                                 LBY #$05
                                                                                                                       LDA *FORMAT
                                                                                     321F- A5 EB
3221- C9 E8
                                                                                                      3270
31A3- 06 EE
                                 ASL *RMNEM
                 2610 PRMN2
                                                                                                                                     HANDLE REL ADDRESSING MODE
                                                                                                                       CMP #$E8
                                               SHIFT 5 BITS OF CHAR INTO 'A'
                                                                                                      3280
31A5- 26 ED
                                 ROL *LMNEM
                 2620
                                                                                                                                     FFRINT TARGET ADDRESS
                                                                                                                       BCS RELADE
                                                                                     3223- BO 47
                                                                                                      3290
                                               (CLEAR CARRY)
31A7- 2A
                                 ROL A
                 2630
                                                                                                                       1 DA # 1L
                                                                                     3225- A9 4C
                                                                                                      3300
31A8- 88
                                 DEY
                 2640
                                                                                                                       CFY #2
                                                                                     3227- CO 02
                                                                                                      3310
31A9- DO F8
                                  BNE PRMN2
                 2650
                                                                                                                       BEQ PRADR2
                                               JADD '?' OFFSET
                                                                                     3229- FO 06
                                                                                                      3320
31AB- 69 3F
                 2660
                                 ADC #$3F
                                                                                                                       BIT *RUN.NU
                                                                                     322B- 24 E8
                                                                                                      3330
31AD- C9 3F
                 2670
                                 CMF #$3F
                                                                                                                       BPL CK.REL
31AF- DO 04
                                                                                     322D- 10 37
                                                                                                      3340
                 2680
                                 BNE =+5
                                                                                                                       LDA #'$
                                                                                                      3350
                                 LDA #1
                                                                                     322F- A9 24
3181- A9 2E
                 2690
                                                                                                                       JSR A.STORE
                                                                                     3231- 20 B9 32
                                                                                                      3360 PRADR2
                                 STA *INVALID
3183- 85 F5
                 2700
                                                                                     3234- B1 F0
                                                                                                      3370 BYTE2
                                                                                                                       LDA (PCL) Y
31B5- 20 B9 32
                                  JSR A.STORE FOUTPUT A CHAR OF MNEMONIC
                 2710
                                                                                     3236- 20 A0 32
                                                                                                      3380
                                                                                                                       JSR ASC.STORE
31B8- CA
                 2720
                                                                                                                       DEY FMORE SIGNIFICANT BYTE FIRST
                                                                                                      3390
                                                                                     3239- 88
3189- DO E4
                                 BNE PRMN1
                 2730
                                                                                                                       BNE BYTE2
                                                                                     323A- DO F8
                                                                                                      3400
                 2740
                                                                                                                       BIT *RUN.NU
                                                                                                      3410 PRADR3
                                 LDA (PCL+X)
                                                                                     323C- 24 E8
31BB- A1 F0
                 2750
                                                                                                                       BPL PRADR4
                                                                                     323E- 10 1D
                                                                                                      3420
                                 STA *TEMP
31BD- 85 F4
                 2760
                                                                                                                       LDA *FORMAT
                                                                                     3240- A5 EB
                                                                                                      3430
                 2770
                                                                                                                       CMP ##01
                                                                                                                                     SEE CORRECTION ON PAGE 8:34
                                                                                     4242 C9 01
                                                                                                      3440
31BF- A9 20
                 2780
                                 LBA #$20
                                                                                     3244 DO 05
                                                                                                                       DNE NZERO
                                                                                                      3450
31C1- 20 B9 32
                2790
                                  JSR AISTORE
                                                                                     3246- A9 2A
                                                                                                                       LDA #'*
                                                                                                      3460
                 2800
                                                                                                                       JSR A.STORE
                                                                                     3248- 20 B9 32
                                                                                                      3470
                                 LDA *INVALID
31C4- A5 F5
                 2810
                                                                                                                       ASL *FORMAT
                                                                                                                                    FIEST NEXT PRINT FORMAT BIT
                                                                                     324B- 06 EB
                                                                                                      3480 NZERO
                                 BEQ CK.BIT
31C6- F0 24
                 2820
                                                                                     324D- 90 OE
                                                                                                                       BCC PRADR4
                                                                                                                                     FIF OF DONT PRINT
31C8- A9 24
                                 LDA #/$
                                               TYES, OUTPUT AS DATA BYTE
                                                                                                      3490
                 2830
                                                                                                                                             ; CORRESPONDING CHAR
                                                                                                                       LDA CHAR1-1,X
                                                                                     324F- BD 50 33
                                                                                                      3500
31CA- 20 B9 32
                2840
                                  JSR A.STORE
                                                                                                                       JSR A.STORE FOUTPUT 1 OR 2 CHARS
                                                                                     3252- 20 B9 32
3100- A1 F0
                                 LDA (FCL,X)
                                                                                                      3510
                 2850
                                                                                                                                            (IF CHAR FROM CHAR2 IS 0,
                                                                                     3255- BD 56 33
                                                                                                                       LDA CHAR2-1,X
                                                                                                      3520
31CF- 48
                 2860
                                 PHA
                                                                                                                                    FOON'T PRINT IT)
                                                                                                                       BEQ PRADR4
                                  JSR ASC.STORE
                                                                                     3258- FO 03
                                                                                                      3530
31D0- 20 A0 32
                2870
                                                                                     325A- 20 B9 32
                                                                                                      3540
                                                                                                                       JSR A.STORE
                                 PLA
3103- 68
                 2880
                                                                                     325D- CA
                                                                                                      3550 PRADR4
                                                                                                                       DEX
31D4- 29 7F
                                 AND #$7F
                 2890
                                                                                                                       BNE PRADRI
                                                                                     325E- DO B7
                                                                                                      3560
31D6- C9 20
                                 CMP #$20
                 2900
                                                                                                                       BIT *RUN.NU
                                                                                     3260- 24 E8
                                                                                                      3570
31D8- 90 OF
                                 BCC X.END
                 2910
                                                                                                                       BPL RTS1
                                                                                     3262- 10 35
                                                                                                      3580
31DA- 48
                                 FHA
                 2920
                                                                                                                       BMI END.LINE
                                                                                     3264- 30 34
                                                                                                      3590
31DB- A9 20
                 2930
                                 LDA #$20
                                                                                                                       LDA *FORMAT
                                                                                     3266- AS EB
                                                                                                      3600 CK.REL
31DD- 20 B9 32
                 2940
                                  JSR A.STORE
                                                                                                                       CMP #$10
                                                                                     3268- C9 1D
                                                                                                      3610
31E0- A9 3B
                 2950
                                 LDA #/;
                                                                                                                       BNE RTS1
                                                                                                      3620
31E2- 20 B9 32
                                 JSR A.STORE
                                                                                     326A- DO 2D
                2960
                                                                                                                       LDA (PCL),Y
                                                                                     326C- B1 F0
31E5- 68
                                                                                                      3630 RELADR
                 2970
                                 FLA
                                                                                                                                     #FCL+H + DISPL + 1 TO 'A','Y'
                                                                                                                       JSR FCADJ2
                                  JSR A.STORE
                                                                                     326E- 20 BE 32
                                                                                                      3640
31E6- 20 B9 32
                 2980
                                                                                     3271- AA
                                                                                                      3650
                                                                                                                       TAX
                                  JMP ENDILINE
31E9- 4C 9A 32
                2990 X.END
                                                                                                                       INX
                                                                                     3272- E8
                                                                                                      3660
                 3000 ;
                                                                                                                       BNE PRNTYX ; +1 TO 'X', 'Y'
31EC- A1 F0
                                 LDA (PCL)X)
                                                                                     3273- DO 01
                                                                                                      3670
                 3010 CK.BIT
                                                                                                                       INY
31EE- C9 2C
                                 CMP #$20
                                               FRIT?
                                                                                     3275- C8
                                                                                                      3680
                 3020
                                                                                                      3690 FRNTYX
                                                                                                                       TYA
31F0- D0 23
                                 BNE END NMEM
                                                                                     3276- 98
                 3030
                                                                                                      3700 FRNTAX
                                                                                                                       F'HA
                                                                                     3277- 48
31F2- A5 F1
                 3040
                                 LDA *PCH
                                                                                                                                                     SYM-PHYSIS 8:14
                                                              SYM-PHYSIS 8:13
                                                                                                                       LDA #'L
                                                                                     3278- A9 40
                                                                                                      3710
31F4- 85 EF
                 3050
                                 STA *YSAVE
```

327D- 68	3720 3730	JSR A.STÖRE PLA	32E0- 88 32E1- D0 F7	4320 NO.INC 4330	DEY BNE NXT.CHR
327E- 20 A0 32		JSR ASCISTORE FRINT TRGT ADDS OF BRANCH	32E3- A5 F1	4340	LDA *FCH
3281~ 8A	3750 PRNTX	TXA JAND RETURN	32E5- D1 F2	4350	CMP (LBL.IDX),Y
3282- 20 A0 32		JSR ASCISTORE	32E7- DO 09	4360	BNE CK.END
3285- 24 E8	3770	BIT *RUN.NU	32E9- C8	4370	INY
3287 10 10	3780	BPL RTS1	32EA- A5 F0	4380	LDA *PCL
3289- 30 OF	3790	BMI END.LINE	32EC- D1 F2	4390	CMP (LBL.IDX),Y
328B- A5 EC	3800 FCADJ	LDA *LENGTH ;0=1-BYTE; 1=2-BYTE; 2=3-BYTE	32EE- DO 02	4400	BNE CK.END
328D- 3 8	3810	SEC	32F0- 18	4410	CLC FLABEL MATCH FOUND
328E- A4 F1	3820 PCADU2	LDY *FCH	32F1- 60	4420	RTS
3290- AA	3830	TAX ;TEST DISPL SIGN (FOR REL BPL PCADJ3 ;BRANCH). EXTEND NEG	32F2- A5 F2	4430 CK.END	LDA *LBL.IDX CMF *LBL.FTR
3291 10 01 3293 88	3840 3850	DEY BY DECREMENTING FCH	32F4- C5 D5 32F6- 90 E0	4440 4450	BCC NXT/LBL #ACC < MEM FOR BR
3294 85 FO	3860 FCADJ3	ADC *PCL	32F8- A5 F3	4460	LDA *LBL.IDX+1
3296- 90 01	3870	BCC RTS1	32FA- C5 D6	4470	CMP *LBL.FTR+1
3298- C8	3880	INY CARRY INTO 'Y' (FCH)	32FC- 90 DA	4480	BCC NXT.LBL
3299- 60	3890 RTS1	RTS	32FE- 60	4490	RTS FCARRY SET FOR RETURN WITHOUT MATCH
	3900			4500	
329A- A9 A0	3910 ENDILINE	LDA #\$AO FMARK EOL		4510 j	THE TABLES FOLLOW
3290- 20 89 32	3920	JSR A.STORE		4520	
329F 60	3930	ŔTS	32FF- 40 02 45	4530 MODE	.BY \$40 \$02 \$45 \$03 \$D0 \$08 \$40 \$09 \$30
***	3940	646	3302- 03 D0 08		
12A0- 08	3950 ASC.STORE		3305- 40 09 30	4E 40 .	VVVVVZA THETEHETTONE
32A1- 24 E8 32A3- 10 15	3960 3970	BIT *RUN.NU BFL A.STORE+1	3308- 22 45 33	4540 ; 4550	XXXXXXZO INSTRUCTIONS BY \$22 \$45 \$33 \$D0 \$08 \$40 \$09 \$40 \$02 \$45
32A5- 10 15 32A5- 48	3980	PHA	3308- 22 43 33 3308- DO 08 40	-1000	TEL TEE TIE TEE TEE TOO TEE TOO TO TO TO TOE TOE
32A6- 4A	3990	LSR A	330E- 09 40 02		
32A7- 4A	4000	LSR A	3311- 45		
32A8- 4A	4010	LSR A		4560 #	Z=O, LEFT HALF BYTE
32A9- 4A	4020	LSR A		4570 j	Z=1, RIGHT HALF BYTE
32AA- 20 09 83	4030	JSR NIBASC	3312- 33 DO 08	4580	.BY \$33 \$DO \$08 \$40 \$09 \$40 \$02 \$45 \$B3 \$DO
32AD÷ 20 B9 32	4040	JSR A.STORE	3315- 40 09 40		
32B0- 68	4050	FLA	3318- 02 45 B3		•
32B1- 20 09 83	4060	JSR NIBASC	331B- DO		
32B4- 20 B9 32	4070	USR AASTORE	331C- 08 40 09	4590	BY \$08 \$40 \$09 \$00 \$22 \$44 \$33 \$DO \$8C \$44
32B7- 28	4080	PLP	331F- 00 22 44		
12B8- 60	4090	RTS	3322- 33 DO 8C		
rana ob	41.00	PHP	3325- 44	4/00	.BY \$00 \$11 \$22 \$44 \$33 \$D0 \$8C \$44 \$9A \$10
3289- 08 328A- 84 EF	4110 A.STORE 4120	STY *YSAVE	3326- 00 11 22 3329- 44 33 D0	4600	.p; \$00 \$11 \$22 \$44 \$55 \$56 \$44 \$10
32BC- AO OO	4130	LDÝ #0	332C- 8C 44 9A		
32BE- 91 D3	4140	STA (PGM.PTR),Y	332F- 10		
3200- 18	4150	CLC	3330- 22 44 33	4610	.RY \$22 \$44 \$33 \$DO \$08 \$40 \$09 \$10 \$22 \$44
32C1- E6 D3	4160	INC *PGM.FTR	3333- DO 08 40		
3203- DO 02	4170	BNE FG.RTN	3336- 09 10 22		
32C5- E6 D4	4180	INC *FGM.FTR+1	3339- 44		
3207- 28	4190 PG.RTN	FLF	333A- 33 DO 08	4620	.BY \$33 \$DO \$08 \$40 \$09 \$62
12C8- A4 EF	4200	LDY *YSAVE	333b- 40 09 62		
32CA- 60	4210	RTS .		4630 ;	YYXXXZ01 INSTRUCTIONS
	4220	ADDUTTUE LABOR DETUDING DADDY OLDAD TO MATCH	3340- 13 78 A9		.BY \$13 \$78 \$A9
	4230 ; St 4240	JBROUTINE LABEL, RETURNS CARRY CLEAR IF MATCH	3343- 00	4650 MODE2	.BY \$00
	4250 LABEL	SA (LBL.LOW LRL.IDX)	3344~ 21 3345~ 01	4660 4670	.BY \$01
	4230 LHDEL	SH (EBELEOW EBELIDA)	3346- 02	4680	.BY \$02 ;ABS
32CB- AD 04 01			3347- 00	4690	.BY \$00 FIMPL
32CE- 85 F2			3348- 80	4700	.BY \$80 FACC
3200- AD 05 01	•		3349- 59	4710	,BY \$59 ; (Z-FAG,X)
3203- 85 F3			334A- 4D	4720	.BY \$4D ; (Z-FAG);Y
			334B- 11	4730	.BY \$11
205- AO 01	4260	LDY #1 FSKIP "L"	3340- 12	4740	.BY \$12 FABS/X
STID- HO OT	4270	.RY \$2C	3340- 06	4750	.BY \$06 ;ABS,Y
2D7- 2C	4280 NXT, LBL	LDY #3 FSKIP 2ND PART OF ADDR & "L"	334E- 4A	4760	.BY \$4A (ABS)
32D7- 2C 32D8- AO 03	ACCO NIVE CHO	INC *LBL.IDX	334F- 05	4770	.BY \$05 ;Z-PAG,Y
2D7- 2C 32D8- AO 03 32DA- E6 F2	4290 NXT, CHR		3350- 1D	4780	.BY \$1D ;REL
32D7- 2C 32D8- AO 03	4300 4310	BNE NO.INC INC *LBL:IDX+1 SYM-PHYSIS 8:15	3351- 20 29 20		.BY \$2C \$29 \$2C \$23 \$28 \$41 SYM-PHYSIS 8:16

3354- 23 28 41		***
3357- 59 00 58 335A- 00 00 00	4800 CHAR2	.BY \$59 \$00 \$58 \$00 \$00 \$00
335A- 00 00 00	4810 ;	XXXXX000 INSTRUCTIONS
335D- 1C 8A 1C	4820 MNEML	XXXXX000 INSTRUCTIONS .BY \$1C \$8A \$1E \$23 \$5D \$8B \$1B \$A1 \$9D
3360- 23 5P 8B		
3363- 1B A1 9D	4830	.BY \$8A \$1D \$23 \$9D \$8B \$1D \$A1 \$00 \$29 \$19
3366- 8A 1D 23 3369- 9D 8B 1D	4830	(D) \$0H \$1D \$25 \$7D \$0D \$1D \$11 \$111 \$00 \$27
336C- A1 00 29		
336F- 19		
3370- AE 69 AB	4840	.BY \$AE \$69 \$A8 \$19 \$23 \$24 \$53 \$1B \$23
3373- 19 23 24		
3376- 53 1B 23 3379- 24 53 19	4850	.BY \$24 \$53 \$19 \$A1 \$00
3370- A1 00	4030	1D1 424 400 417 4H1 400
0070 770 00		XXXYY100 INSTRUCTIONS
337E- 1A 5B 5B	4870 🦿 .	.BY \$1A \$5B \$5B \$A5 \$69 \$24 \$24
3381- A5 69 24	= ;	-
3384- 24		XXX1010 INSTRUCTIONS
3385- AE AE A8	4890	BY \$AE \$AE \$AB \$AD \$29 \$00 \$7C \$00
3388- AD 29 00	10,0	
338B- 7C 00		
	4900 ;	XXXYYY10 INSTRUCTIONS
3380- 15 9C 6D 3390- 9C A5 69	4910	.BY \$15 \$9C \$6D \$9C \$A5 \$69 \$29 \$53
3393- 29 53		
3373 27 30	4920 ;	XXXYY01 INSTRUCTIONS
3395- 84 13 34	4930	.BY \$84 \$13 \$34 \$11 \$A5 \$69 \$23 \$A0
3398- 11 A5 69		
339B- 23 A0	4040 :	XXXXX000 INSTRUCTIONS
339D- D8 62 5A		
33A0- 48 26 62	.,	
33A3- 94 88		
33A5- 54 44 C8	4960	.BY \$54 \$44 \$C8 \$54 \$68 \$44 \$EB)\$94 \$F4 \$B4
33A8- 54 68 44		
33AB- E8 94 F4 33AE- B4		
33AF- 08 84 74	4970	.RY \$08 \$84 \$74 \$B4 \$28 \$6E \$74 \$F4 \$CC \$4A
33B2- B4 28 6E		
3385- 74 F4 CC		·
33B8- 4A 33B9- 72 F2 A4	4980	.BY \$72 \$F2 \$A4 \$8A
33BC- 8A	4700	101 172 112 1H4 1000
0000	4990 ;	XXXYY100 INSTRUCTIONS
33BD- F4 AA A2	5000	BY \$F4 \$AA \$A2 \$A2 \$74 \$74 \$74 \$72
3300- A2 74 74		
3303- 74 72	5010 :	1XXX1010 INSTRUCTIONS
3305- 44 68 B2	5020	.BY \$44 \$68 \$B2 \$32 \$B2 \$F4 \$22 \$F4
33C8- 32 B2 F4		
33CB- 22 F4		
	and the second s	XXXYYY10 INSTRUCTIONS .BY \$1A \$1A \$26 \$26 \$72 \$72 \$88 \$C8
33CD- 1A 1A 26 33D0- 26 72 72	5040	'B! #14 #14 #50 #50 #75 #75 #00 #60
33D3- 88 C8		
0000	5050 ;	XXXYYY01 INSTRUCTIONS
33D5- C4 CA 26	5060	.BY \$C4 \$CA \$26 \$48 \$44 \$44 \$A2 \$C8
3308~ 48 44 44		
33DB- A2 C8	5070	
33DD- OD OA 53	5080 MESS1	BY \$0D \$0A 'START ADDRESS =\$' \$00
33E0- 54 41 52		
33E3- 54 20 41		SYM-PHYSIS 8:17

							1 <)		
33E6-							1		
33E9-									
33EC-		31)	24						
33EF-									ARUN ARRESON -A/ AAA
33F0-				5090	ME552	·BY	\$OTI \$	VA	'END ADDRESS =\$' \$00
33F3-									
33F6-									
33F9-									
33FC-			30						
33FF-									ARTOLOGOUPLE LABELD EIDET/
3401-				5100	MESS3	' BA	\$0D \$0	OA	'DISASSEMBLE, LABÉLS FIRST'
3404-									
3407-									
340A-									
340D-									
3410~									
3413-									
3416-									
3419- 3410-				5110		ĐΥ	4 A Tr 4 A	۸۸	OR RETURN TO RAE (D.L OR R)?' \$00
3416-				JIIO	4	+ 15 1	*OD *	Vn	ON RETORN TO MILE VETE ON MY.
3422-									
3422-									
3428-									
3428-									
342E-									
3431-									
3434-									
3437-									
343A-									
343B-		AΟ	50	5120	MESS4	. BY	\$0D \$0	0A	'PASS 2' \$00
343E-									
3441-	20	32	00						
				5130					
3444-	20	86	88	5140	TOGGLE	JSR	ACCES!	S	JECHO CONTROL
3447-	ΑD	53	A6	5150		LDA	TECHO		
344A-	09	80		5160		ORA	#\$80		
344C-	80	53	A6	5170			TECHO		
344F-	60				Z.STORE	RTS			
				5190					
				5200		.EN			
ucc	٥r	711	C D.T.	CACCE	MDIED /DTG1				

USE OF THE DISASSEMBLER (DIS)

With RAE, assemble DIS at any appropriate address, say XXXX, and store the object code on mass storage for future use.

When you wish to use DIS, enter its object code from mass storage. Enter RAE at its cold start (\$B000), and modify the default SEt parameters to meet your needs (more on this below). The object code to be disassembled should also be in RAM, or in ROM, if you want to work on MON, BAS, or RAE!

Next enter RUN \$XXXX, and when DIS sives you your choice of entering D, L, or R, enter L to set the Label File set up. When prompted to enter the starting and ending address of the file to be disassembled, ENTER ONLY FOUR HEX DIGITS AND DO NOT HIT RETURN. If you enter any digits in error there is no way to erase. You must abort and begin again. For this first pass, enter the address limits of the object code, and DIS will build up the complete Label File.

For PASS2 you are once again asked for starting and ending addresses. You may enter partial ranges for the object code, depending on how large a block is available for the 'source code' to be generated by DIS. You will soon get the knack of how much source code area should be allocated for each 1K or 4K block of object code.

SYM-PHYSIS 8:18

The following example, in which DIS is asked to disassemble itself, will illustrate the disassembler's use (a 24K system is assumed):

The object code is located at \$3000-\$344F, so when RAE is entered, SET \$0200 \$2FFD \$3500 \$3FFD, to allow plents of room for the source code without "clobbering" the object code. Then enter RUN \$3000 to call DIS. For this example enter 3000 and 344F (for both passes) when the limits are requested. REMEMBER - NO COMMAS, CARRIAGE RETURNS, OR ERRORS PERMITTED.

When RAE's '>' prompt reappears, type PRint <cr>
to see the source code listing. You would need add only a .BA \$xxxx at the beginning, and a .EN at the end, to be able to ASsemble your program, if there were no external references (including pages 0 and 1). Since there are, you need only replace the 'L' for these labels with a '\$', or use .DE pseudo-ops. The latter is preferable, since 'meaningful' labels, or more more may then be substituted more easily.

Now you are prepared to study, comment, enhance, relocate, modify, EPROM or whatever you wish to do with the program.

A rartial listing of DIS's output of DIS follows, so that you may see how it handles rotential 'problem' areas. Note the ';' line following RTS and JMP instructions; these are to flag possible tables. Note how the .BY's are used to indicate non-opcodes, and how the ASCII values are given as 'comments' to aid in locating embedded text. Note that there are still a few areas where DIS shows that your brainpower is still needed occasionally by SYM. But what a perfect SYM-biosis!

PARTIAL	DISASSEMBLY	ΠE	RIS	RY	TITS

0100		JSR L3444		2155	L330D	RTI	
0105		LDA #\$00		2160		DRA #\$40	
0110		STA *\$E8		2165		.BY \$02	
0115		STA *\$F5		2166	iLines	2170 3285 delete	d
0120		LBX #\$12		3290	L3401	ORA L440A	
0125	L300B	LDA \$E5,X		3295		EOR #\$53	
0130		STA L3450,X		3300		EOR (\$53,X)	
0136	FLines 135	to 205 delete	ed	3305		.BY \$53	; S
0210		STY *\$E5		3310		.BY \$45	ŧΕ
0215		BNE L3046		3315		.BY \$4D	7 M
0220	L3032	JMF L30DE		3320		.BY \$42	; B
0225	ŷ			3325		.BY \$4C	ŧL
0230	L3035	LIX #\$00		3330		.BY \$45	ŧΕ
0235	L3037	LDA L343B,X		3335		.BY \$2C	; ,
0240		BEQ L3042		3336 -	flines	3340 3520 delete	ď
0241	#Lines 245	to 2065 delet	ced	3525		.BY \$4F	; O
2070		BCC L32D8		3530		.BY \$52	; R
2075		RTS		3535		.BY \$20	ĵ
2080	;			3540		.BY \$52	į R
2085	L32FF	ŔŦĨ		3545		.BY \$29	;)
2090		.BY \$02		3550		.BY \$3F	97
2095		.BY \$45	ŧΕ	3555		.BY \$00	
2100		.BY \$03		3560	L.343B	ORA L500A	
2105		.BY \$DO	∮P	3565		EOR (\$53,X)	
2110		.BY \$08		3570		.BY \$53	; S
2115		.BY \$40	÷ @	3575		.BY \$20	÷
2120		.BY \$09		3580		.BY \$32	9.2
2125		.BY \$30	; 0	3585		.BY \$00	
2130		.BY \$22	; •	3590	L3444	JSR L8#86	
2135		.BY \$45	ŧΕ	3595		LDA LA653	
2140		.BY \$33	; 3	3600		DRA #\$80	
2145		.BY \$DO	\$ F	3605		STA LA653	
2150		.BY \$0B		3610		RTS	


SYM-PHYSIS 8:19

(continued from page 8:8)

submitted by Matt Wilson, whose address is in the program listing. He also sent along a copy of an overlay he places on the keypad to assist in determining the proper numeric codes to use with each letter or symbol. Note that this program supports lower case, also.

SYM PRINTER GRAPHICS

Jack Giervic has sent us a number of staphics programs for the SYM Visible Memory System, including one to draw the figure shown here. Jack is one-up on us in having a graphic printer. The original of the figure was copied from the Visible Memory bit image with the Paper Tiser 445 with graphics option. quote Jack directly, "This printer (or one



like it) is an excellent addition to the 'perfect' system, which includes MTU's Visible Memors. I'll also be trying MPI's 886 printer so I'll be able to do a comparision.

WILL THERE BE A VOLUME 3?

We know of no computer newsletters which have survived past their third year as originally conceived. Eric Rehnke's KIM-1/6502 User Notes (later renamed 6502 User Notes), a bimonthly, made it only through No. 17, and that issue was many, many months late! All subscribers received copies of the first issue of the new masazine COMPUTE, in lidu of the never issued No. 18. COMPUTE, itself, is actually the successor to the 'late' Pet Gazette, VIPER, for the RCA VIP, completed only two volumes, and only after a long interval did Vol. 3 begin to appear, under a new editor.

Donald Clem, editor of The TARGET, an AIM65 newsletter, apologizes for the several month delay of the most recent issue of the bimonthly. We curselves had to prepare a double issue last sear to fill a sap, and cut down from a bimonthly to a quarterly, to make the pain not less intense, just less frequent. On the other hand, MICRO and COMPUTE. Went from bimonthlies to monthlies during the past year.

Just what is the "Viability Factor"? It would appear to be a raid, not "volunteer", multi-person staff, which obviously means revenue other than from subscriptions, such as advertisins, software, hardware, other publications, etc. We would never have some into the second year, had there not been the rotential of hardware/software sales to pay for Jean's time. She now has two part-time employees to help in filling orders.

On the editorial side, however, we have had no help until now. The phone calls keep us so busy that we cannot possibly keep up with the correspondence, including written requests for urgent help.

The diskettes, cassettes, and hard copy manuscripts containing items for publication and/or sale are back-logging. These include Campbell's "SARGON II for the SYM", Vrtis' "Tiny Pilot for SYM", Holt's "TECO for SYM", to list Just a few examples. There is far more quality software ALMOST AVAILABLE for the SYM then we would ever have thought possible a year ago.

SYM-PHYSIS 8:20

Fublishing untested programs, however, or marketing undebugged, undocumented, software would immediately release a flood of letters and phone calls full of wrath and duestions. Far better to polish the items first, and det letters and calls full of thanks and praise. Incidentally, thanks for all of the ego-building letters; we have received only one critical letter since we started, and when we pointed out that the writer had somehow forgotten to read the instructions, he wrote a very nice apology.

Next sear we will be travelins much of the time, thanks to a sabbatical leave, and have wondered how or even whether to continue with Volume 3, but that problem is being resolved. Benny Hall has joined us as an associate editor with this issue. He is a psychologist by training, bought an Apple to learn on, and is another migrant into the computer field for economic reasons. He is building up speed on the SYM very quickly, will handle all correspondence and letters for help, and will review and edit all software submissions.

He will be preparing a "SYM-1 User's Manual", which will be designed to help new dwners with no previous electronics background to get the most from their SYMs. This manual will make the SYM a much more appropriate entry-level system for a much broader class of potential users, and will help sell more SYMs, and get more software development going, and so on and on. We feel that neither Commodore (KIM), nor Synertek (SYM) ever realized the potential of this vast market. While Commodore is going after one segment of the educational market with PET, we feel that SYM can also fill the hardware segment of the educational market. We intend to pursue this area further.

With Denny aboard we can fulfill some of the above objectives, look forward to a Volume 3, and rerhaps even a return to a bimonthly publication.

SOME COMMENTS FROM DAVE KEMP

Here are some extracts from a letter from Dave which you may find of interest:

Dear Lux,

I enjoyed Hugh Campbell's letter in issue 5/6. The November or December issue of Softalk (an Apple magazine) had a good article on program protection which said, in effect, that 'to some people, protecting a piece of software with anti-copying code is like waving a red flag in front of a bull.' I couldn't agree more. I rarely actually use commercial software but copying it is loads of funthere is nothing more satisfying than outwitting a fellow programmer.

A while back you asked in what format software should be published in SYM-physis. Of the three possible formats - hex dump, disassembly, and commented source, - the disassembly is the worst. It takes up lots of space on the page but contains no more information than a hex dump. I wish you would publish the software you now distribute on cassette in hex format and let us readers type it in and do our own disassembly. You could still offer cassettes for those who don't like to type, but I suspect that your copying workload would drop considerably.

Regards.

Dave

David P. Kemp

"FAIL-SAFEING" THE VIAS ON RESET

In a very brief note. Philip Kohl taught us two very important facts about the SYM, one involving the use of the VIAs, the other concerning BASIC. We'll expand on both of his lessons in this issue. Both were based on his study of the Gieryic EPROM Programmer described in Issue No. 5/6

The specs for the 6522 point out that RESET sets most internal registers to zero, and sets both the A and R ports to the INPUT state. This is supposed to ensure that no spurious outputs are generated, meaning no outputs not under computer control. So why do the relays in Jack's PROM Burner reset to the closed condition, applying 45 V, and 425 V to the EFROM socket, an obviously 'risky' condition? One should not insert a chip with power-on, nor should one leave an EFROM sitting around indefinitely with an unnecessary +25 V applied.

The answer is obvious once you figure out the reason for the FF's when you enter a $\cdot V$ A800 after RESET. You get the following:

ABOO FF FF 00 00 XX YY FF FF,ZZ

The 00's indicate that the ports are set as inputs, all right, but the FF's at \$A800 and \$A801 indicate that all ones are being input. *Floating* input lines tend high, signaling ones. These floating input lines going to the relaw-driving 7404 from 3PB3 and 3PB4 are treated as if they were high outputs, and the relaws close.

The solution is to "unfloat" the lines to a low state, thus allowing the relays to "float" open. Phil suggests a 1 K resistor to ground at each of the 7404 inputs. Very simple, eh? (as many of our Canadian friends would express it!). With a non-inverting buffer this problem would not occur, but it still might be safer to actually tie the line high, rather than to depend on the up-float.

We recommend installing a back biased diode across each relay coil to shunt the current which the coil inductance keeps flowing after switch-off back into itself until it reacefully decays.

Phil also replaced the 25 V relaw driven by 3PB5 with a SPDT type (Magnecraft W172 DIP-1, or equivalent). He connected the 2CB2 signal (AA-5) to the normally closed contact and the ± 25 V supply to the normally open contact.

He indicated also how to modify the Eircuit to handle 2732's, by using 3PB3 to carry the All signal to pin 21, and using 3PB4 and 3PB5 to drive the two relays. The required software changes should be obvious, on studying the program.

SPEEDING UP BASIC PROGRAMS

Phil Kohl reports that it takes Jack Gierwic's EPROM Burner Program some O4m26s to program a complete 2716 (somehow it always seems so much longer at our place!). The actual "burning" time is O1m40s (nominal). Thus the BASIC "overhead" time is O2m46s. By replacing the constants within the program with predefined variables (which need be computed only once), he reduced the total running time to O3m26s; the overhead time is now only O1m46s, a large percentage reduction.

One minute seems like a long, long, time when burning an EFROM, since there is absolutely no sign of any action, except for the flashing red LED we installed to warn us of power-on. The saving is not only in time, but in the anxiety and uncertainty of waiting, waiting, waiting..... So, before we burn our next EFROM, we'll first burn out all our constants! We can then save TWO minutes when we start burning 2732/5!

ON .CT AND THE USE OF THE DISK VECTORS

RAE-1 has three "undocumented" commands intended for disk system linkage. If you have no disks you may use them for other purposes. As a matter of fact, to correct a "bus" in RAE which does not permit .CT to work as it should (see section 10.0 of the Reference Manual) one of the disk vectors (associated with LOad) is used to vector to a patch.

The 'fix' consists of setting the dassette/disk flag at \$EE to 01 (to indicate disk), which vectors the program through the DISC.IN vector at \$F6,\$F7 to the patch and then back to RAE's cassette input program. The purpose of the patch is to force the reading of the programs on the cassette in sequence no matter what the ID may be. The patch may not be needed (have not verified this) if the last PUt or GET left a 00 ID at \$0100. If the patch is present GET will always read the next file on the cassette.

If you have the third printing of the manual the patch as presented may be in the middle of your source code if you change SEt. Use the following instead:

Set \$EE to 01 Set \$F6,\$F7 to A0 00 Set \$A0-\$A7 to A9 00 8D 10 01 4C 68 EF

A TAPE DIRECTORY SYSTEM

What else can you do with the disk vectors if you don't have disks? Let Bill Wharrie tell you. We didn't have time to try this ourselves, but the idea looks good. The source can be assembled, with .CT (see above!), in a 16K system. As noted below, our checksum after assembly did not agree with the one given by Bill.

0010	A Tame Directory System
0020	Bill Wharrie
0030	272 Erb St. W.
0040	Waterloo, Ont.
0050	Canada N2L 3G1
0060	Dec. 1980
0070	
0080	The system described below uses the RAE commands
0090	>DC+ >EN and >LO to implement a cassette tape
0100	directory. The command >DC becomes Directory Command
0110	and supports six sub-commands as detailed below.
0120	
0130	COMMAND DESCRIPTION
0140	>DC C Fin name - Create file with #nn and NAME name
0150	>DC D Fnn Delete file ≢nn
0160	>DC G Get directory from tage
0170	>DC I Initialize (clear) directory
0180	DC L List directors
0190	>DC F date Fut directory to take with optional
0200	date code.
0210	The system assigns space on the cassette tape in
0220	a straightforward manner all files begin at
0230	multiples of 15 on the tape counter. It is up to
0240	the operator to correctly position the tape. The
0250	DIRECTORY file is arbitrarily assigned file #00
0260	and cassette counter 0000. The user should position
0270	the tape some distance in from the leader (I use
0280	10 counts), stop the take, zero the take counter,
0290	and then write the directory file. This can serve
0300	as a zero reference when using the tape later

```
0310 Just load the tame, type >DC G (cr) (cr), start
 0320 the tare, and zero the counter when the sync search
 0330 indicator extinguishes. The Create sub-command
 0340 checks to see if the file# is already in use; and
 0350 Puts the file in the first available space, if found.
 0360 File names may be up to 13 characters in length --
 0370 longer names will be truncated. The directory file
      structure uses 16 bytes for each file -- 1 byte for
 0390 the file #, two bytes for the tage counter and 13
 0400 for the name. Space is provided for 16 files, including
0410 the directory.
0420
 0430 The syntax for the ENter and LOad commands is as follows:
0440
0450
                   ENter (write) file #nn to tape
0460
        >L0 Fnn
                   LOad (read) file #nn from tape
0470
0480 The file number MUST be surrlied.
0490 Each command searches the
0500 directory for the specified file #. If it finds the file,
0510 it prints the directors line and then prompts the user
0520 as follows:
0530
0540 CUE TAPE TO nonn
0550 THEN HIT RTRN.
0560
      NOTE: I am not using remote control of my cassette.
0570
0580 Therefore the routines that prompt the user DO NOT turn
0590
      on the remote control.
0800
0610
        ERROR MESSAGES
0620
0630 The following error codes are used by the system
0640 The commands that may return these errors are given
0650 in parentheses following the description
0660
0670 30 Illesal sub-command (DC)
0680 31
         Sub-command missing (DC)
          "F" missing before file# (EN, LO, DC C, DC D)
0700 33 Directory full (DC C)
0710
      34 File# in use (DC C)
0720
     35 File# missins (EN, LO)
0730 36 File not found (DC D, EN, LO)
0740
0750
         USING THE SYSTEM
0760
0770 The object code occupies 3 pages of
0780 memory and the directory itself one page. The
0790 object code loads to $1800 to $1DFE and the
0800 directory is from $1E00 to $1EFF.
     The checksum for .V 1800/1DFE is $3854.
     (EDITOR'S NOTE: OUR CHECKSUM WHEN ASSEMBLED WAS $384E!)
     Load a cassette in the recorder, advance the
     tape some distance past the leader, and zero the counter.
0840
0850 Enter >DC I (cr), then >DC P (cr).
0860 After the prompt press record and play
     on the recorder and hit return -- this will mark your
0880 zero point on the tape.
0890 As you add files to the tape, use >\!\!\!\! DC C to add them
0900 to the directors. Before you remove the tape from
0910 the recorder, write the undated directory to the tape
0920 with >DC P date(cr).
```

```
CASSETTE TAPE DIRECTORY SYSTEM
                                                                                   1B2E- 4C CD 1B
                                                                                                   0660
                                                                                                                     JMP INIT
                          WRITTEN BY BILL WHARRIE
                                                                                   1B31- C9 43
                                                                                                                    CMP #/C
                  0030 ;
                          AUGUST 1980.
                                                                                   1B33- DO 03
                                                                                                    0680
                                                                                                                     BNE =+4
                  0040 ;
                                                                                   1B35- 4C 59 1B
                                                                                                   0690
                                                                                                                     JMP CREATE
                  0050 #
                          USES RAE'S DC, EN AND LO COMMANDS
                                                                                   1838~ C9 4C
                                                                                                    0700
                                                                                                                    CMP #'L
                  0040 #
                          DC LOOKS AFTER THE DIRECTORY
                                                                                   183A- DO 03
                                                                                                    0710
                                                                                                                    BNE =+4
                  0070 ;
                         EN DOES A "FUT"
                                                                                   183C- 4C F4 1B
                                                                                                   0720
                                                                                                                    JMP LIST
                 0080 ; LO DOES A "GET"
                                                                                   1B3F- C9 50
                                                                                                    0730
                                                                                                                    CMP #'P
                  0090 #
                                                                                   1B41- DO 03
                                                                                                    0740
                                                                                                                    BNE =+4
                 0100 ;
                              SYM MONITOR ROUTINES
                                                                                   1B43- 4C 5B 1C
                                                                                                   0750
                                                                                                                    JMP PUTD
                 0110 ACCESS
                                  .DE $8886
                                                                                   1B46- C9 47
                                                                                                   0760
                                                                                                                    CMP #'6
                 0120 ASCNIB
                                  .DE $8275
                                                                                   1848- DO 03
                                                                                                   0770
                                                                                                                    BNE =+4
                 0130 DUTXAH
                                  .DE $82F4
                                                                                   184A- 4C DC 1C
                                                                                                   0780
                                                                                                                    JMP GETD
                 0140 DUTBYT
                                  .DE $82FA
                                                                                   1B4D- C9 44
                                                                                                   0790
                                                                                                                    CMP #'D
                 0150 NIBASC
                                  .DE $8309
                                                                                  1B4F- DO 03
                                                                                                   0800
                                                                                                                    BNE =+4
                 0160 CRLF
                                  .DE $834D
                                                                                  1851- 4C 06 1D
                                                                                                   0810
                                                                                                                    JMP DELETE
                 0170 INCHR
                                  .DE $8A1B
                                                                                  1B54- A2 30
                                                                                                   0820
                                                                                                                    LDX #$30
                 0180 DUTCHR
                                  .DE $8A47
                                                                                  1B56- 6C OE BO
                                                                                                   0830
                                                                                                                    JMP (ERROR)
                 0190 LOADT
                                  .DE $8C78
                                                                                                   0840 ; >DC C Fnn
                 0200 DUMPT
                                  .DE $8E87
                                                                                                   0850 ;
                                                                                                           CREATE FILE #nn
                 0210 ;
                           SYM VARIABLES
                                                                                  1859- C8
                                                                                                   0860 CREATE
                                                                                                                    INY
                 0220 TAPDEL
                                  *DE $A630
                                                                                  185A- C8
                                                                                                   0870
                                                                                                                    INY FOINT TO ARGUMENTS
                 0230 TEMP
                                  .DE $A647
                                                                                  1B5B- B9 35 01
                                                                                                   0880
                                                                                                                    LDA CRT+Y
                 0240 P1L
                                  .DE $A64E
                                                                                  1B5E- C9 46
                                                                                                   0890
                                                                                                                    CMP #'F
                                                                                                                                  FILE# PRECEDED BY 'F'
                 0250 F2L
                                  .DE $A640
                                                                                  1B60- F0 05
                                                                                                   0900
                                                                                                                    BEQ CR1
                 0260 P3L
                                  . DE $A64A
                                                                                  1862- A2 32
                                                                                                   0910
                                                                                                                    LDX #$32
                 0270 ;
                           RAE REFERENCES
                                                                                  1B64- 6C OE BO
                                                                                                   0920
                                                                                                                    JMP (ERROR) ; "F" NOT FOUND
                 0280 ERROR
                                  .DE $BOOK
                                                                                  1867- C8
                                                                                                   0930 CR1
                                                                                                                    INY FOINT TO FILE #
                 0290 RAE.HOT
                                  .DE $BOSE
                                                                                  1868- A2 OA
                                                                                                   0940
                                                                                                                    LDX #$A
                 0300 NXTPARM
                                  .DE $B502
                                                                                  1B6A- 20 E6 B2
                                                                                                   0950
                                                                                                                    JSR GETBYT
                 0310 RAE.PUT
                                  .DE $EF95
                                                                                  186D- AD OA 01
                                                                                                   0960
                                                                                                                    LDA $10A
                 0320 DCVEC
                                  .DE $EC
                                                                                  1B70~ 48
                                                                                                   0970 CR2
                                                                                                                    PHA | SAVE FILE #
                 0330 ENVEC
                                  .DE $FO
                                                                                  1B71- 20 A7 1B
                                                                                                   0980
                                                                                                                    JSR FINDFILE
                                                                                                                                          ISEARCH DIRECTORY
                 0340 LOVEC
                                  .DE $F2
                                                                                  1B74- 90 04
                                                                                                   0990
                                                                                                                    BCC CR3
                                                                                                                                 FCARRY CLEAR IF OK
                 0350 GETBYT
                                  .DE $B2E6
                                                                                  1876- AA
                                                                                                   1000
                                                                                                                    TAX
                 0360 GETBUF
                                  .DE $86A0
                                                                                  1877- 6C OE BO
                                                                                                   1010
                                                                                                                    JMP (ERROR)
                 0370 DOCMD
                                  · DE $B6AE
                                                                                  187A- 68
                                                                                                   1020 CR3
                                                                                                                    PLA FRECOVER FILE #
                0380 CRT
                                  .DE $135
                                                                                  1878- 9D 00 1E
                                                                                                   1030
                                                                                                                    STA DRCTRY, X !X POINTS TO NEXT FREE SPACE
                0390 ;
                                                                                  187E- E8
                                                                                                   1040
                                                                                                                   TNX
                0400
                                  .BA $1800
                                                                                  187F- E8
                                                                                                   1050
                                                                                                                   INX FOINT TO LO HALF OF COUNTER
                0410
                                  .05
                                                                                  1B80- 18
                                                                                                   1060
                                                                                                                   CLC
                0420 } SET UP RAE VECTORS
                                                                                  1881- F8
                                                                                                   1070
1800- A9 1B
                0430 PATCH
                                 LDA #L.DC
                                                                                  1882- BD FO 1D
                                                                                                  1080
                                                                                                                   LDA DRCTRY-16.X !GET CNTR# OF PREVIOUS FILE
1B02- 85 EC
                0440
                                 STA *DOVEC
                                                                                  1885~ 69 15
                                                                                                   1090
                                                                                                                   ADC #$15
                                                                                                                               FALLOW COUNT OF 15 BTWN FILES
1B04- A9 1B
                0450
                                 LDA #H+DC
                                                                                  1887- 9D 00 1E
                                                                                                  1100
                                                                                                                   STA DRCTRY, X
                                                                                                                                         #STORE NEW CNTR#
1806- 85 FT
                0460
                                 STA *DCVEC+1
                                                                                  188A- CA
                                                                                                   1110
                                                                                                                   DEX
1B08- A9 46
                0470
                                 LDA #L,ENT
                                                                                  1888- BD FO 1D
                                                                                                  1120
                                                                                                                   LDA DRCTRY-16,X
180A- 85 FO
                0480
                                 STA *ENVEC
                                                                                  188E- 69 00
                                                                                                  1130
                                                                                                                   ADC #0
                                                                                                                                 FPROPAGATE CARRY
180C- A9 1D
                0490
                                 LDA #H, ENT
                                                                                  1890- 9D 00 1E
                                                                                                 1140
                                                                                                                   STA DRCTRY,X
1B0E- 85 F1
                0500
                                 STA *ENVEC+1
                                                                                  1893- D8
                                                                                                  1150
                                                                                                                   CLD
1810- A9 82
                0510
                                 LDA #L,LOAD
                                                                                  1B94- E8
                                                                                                  1160
                                                                                                                   INX
1812- 8D F2 00
                0520
                                 STA LOVEC
                                                                                 1B95- E8
                                                                                                  1170
                                                                                                                   INX
                                                                                                                        FPOINT TO FILE NAME
1815- A9 1D
                0530
                                 LDA #H,LOAD
                                                                                 1896- C8
                                                                                                  1180
                                                                                                                   INY
                                                                                                                        FROINT TO FILE NAME IN BUFFER
1817- 8D F3 00
                0540
                                 STA LOVEC+1
                                                                                 1B97- B9 35 01 1190 FNLOOP
                                                                                                                   LDA CRT,Y
                                                                                                                                 FMOVE FILE NAME FROM BUFFER...
1B1A- 60
                0550
                                 RTS
                                                                                 1B9A- 9D 00 1E 1200
                                                                                                                   STA DRCTRY,X
                                                                                                                                         ; TO DIRECTORY
                0560 ; DC MAIN ROUTINE
                                                                                 189D- C8
                                                                                                  1210
                                                                                                                   INY
                0570 #
                         READ SUB-COMMAND AND JUMP
                                                                                 189E- E8
                                                                                                  1220
                                                                                                                   INX
1818- 20 86 8B
                0580 DC
                                 JSR ACCESS
                                                                                 1B9F- 8A
                                                                                                  1230
                                                                                                                   TXA
1B1E- C0 50
                0590
                                 CFY #$50
                                                                                 1BAO- 29 OF
                                                                                                  1240
                                                                                                                   AND #$F
                                                                                                                                 FDO UNTIL X IS A
1B20- DO 05
                0600
                                 BNE DC1
                                               FSUE-CMD MISSING IF Y=50
                                                                                 1BA2- DO F3
                                                                                                  1250
                                                                                                                   BNE FNLOOP
                                                                                                                                 FMULTIFLE OF 10
1B22- A2 31
                0610
                                 LDX #$31
                                                                                 1BA4- 4C 5E BO
                                                                                                  1260
                                                                                                                   JMP RAE.HOT FRETURN TO RAE
1824- 6C OE BO
                0620
                                 JMP (ERROR)
                                                                                                         LOOK FOR FREE SPACE IN DIRECTORY
                                                                                                  1270
1P27- B9 35 01
                0630 DC1
                                LDA CRT,Y
                                                                                 1BA7- 20 2F 1B
                                                                                                 1280 FINDFILE
                                                                                                                  JSR LOOKUP
1F2A- C9 49
                0640
                                 CMP #'I
                                                                                 1BAA- 90 19
                                                                                                  1290
                                                                                                                   BCC ERROR34
1B2C- DO 03
                0850
                                 BNE =+4
                                                                                 1BAC- A2 00
                                                                                                  1300
                                                                                                                   LDX #0
                                                        SYM-PHYSIS 8:25
                                                                                                                                               SYM-PHYSIS 8:26
```

1BAE- BD 00 1E	1310 FL00F2	LDA DRCTRY•X	1COD- C9 FF	0430	CMP #\$FF
1881- C9 FE	1320	CMP #\$FE	1COF- FO 11	0440	BEQ ENDLIST
1883- FO OD	1330	BEQ OKEXIT FOUND FREE ENTRY	1C11- 20 25 1C	0450	JSR PRTLINE ; TYPE CURRENT DIRECTORY LINE
1885- C9 FF	1340	CMP #\$FF	1C14- E0 00	0460 L2	CPX #0
1BB7- FO 09	1350	BEQ OKEXIT FINSERT AT END OF DIRECTORY	1016- FO OA	0470	BEQ ENDLIST
1BB9- 8A	1360	TXA	1C18- DO EC	0480	BNE LOOP2
1BBA- 18	1370	CLC	1C1A- 8A	0490 LSKIP	TXA
1BBB- 69 10	1380	ADC #\$10	1C1B- 18	0500	CLC
188D- BO OA	1390	BCS ERROR33	1C1C- 69 10	0510	ADC #\$10
1BBF- AA	1400	TAX	1C1E- AA	0520	TAX
1BCO- DO EC	1410	BNE FLOOP2 #ALWAYS	1C1F- 4C 14 1C	0530	JMP L2
1BC2- 18	1420 OKEXIT	CLC	1C22- 4C 5E BO	0540 ENDLIST	JMP RAE.HOT
1BC3- 90 07	1430	BCC FEXIT		0550 ; PRINT	
1BC5- A9 34	1440 ERROR34	LDA #\$34	1025- 20 4D 83	0560 PRTLINE	JSR CRLF
1BC7- DO 02	1450	BNE =+3	1C28- A9 46	0570	LDÅ #/F
1BC9- A9 33	1460 ERROR33	LDA #\$33	1C2A- 20 47 BA	0580	JSR OUTCHR #TYPE "F"
1BCB- 38	1470	SEC	1C2D- BD 00 1E	0590	LDA DRCTRY,X
1BCC- 60	1480 FEXIT	RTS	1030- 20 FA 82	0600	JSR OUTBYT JTYPE FILE NUMBER
IBCC- GO	1490 ;	KT W	1033- A9 20	0610	LDA #'
	1500	CT F2	1C35- 20 47 8A	0620	JSR OUTCHR
	1500	101 12	1C38- E8	0630	INX
			1039- BD 00 1E	0640	LDA DRCTRY,X
	0010 ; TAPE I	DIRECTORY - FILE 2	1C3C- 20 FA 82	0650	JSR OUTBYT FTYPE CASSETTE COUNTER
	0020 ;		1C3F- E8	0660	INX
		INITIALIZE DIRECTORY	1C40- BD 00 1E	0670	LDA DRCTRY,X
		L DIRECTORY FILE WITH SPACES	1C43- 20 FA 82	0880	JSR OUTBYT
		FIRST LINE	1C46- A9 20	0690	LDA #'
1BCD- A2 00	OOGO INIT	LDX #0	1C48- 20 47 8A	0700	JSR OUTCHR
1BCF- A9 20	0070	LDA #'	1C4B- E8	0710 PRTLOOP	INX
1BD1- 9D 00 1E	0080 ILDOP1	STA DRCTRY+X	1C4C- 8A	0720	TXA
1BD4- E8	0090	INX	1C4D- 29 OF	0730	AND #\$OF ;DO UNTIL X IS A
1BD5- DO FA	0100	BNE ILOOP1 FFILL WITH SPACES	1C4F- FO 09	0740	BEQ PRTEXIT ; MULTIPLE OF 16
	0110 ;		1C51- BD 00 1E	0750	LDA DRCTRY,X
19D7- A2 10	0120	LDX #\$10	1C54- 20 47 8A	0760	JSR OUTCHR
1BD9- A9 FF	0130 IL00P2	LDA ##FF	1C57- 4C 4B 1C	0770	JMP PRTLOOP
1BDB- 9D 00 1E	0140	STA DRCTRY,X ; MARK END-OF-DIRECTORY	1C5A- 60	0780 PRTEXIT	RTS
1BDE- BA	0150	TXA			date WRITE (PUT) DIRECTORY TO TAPE
1BDF- 18	0160	CLC			date TO HEADER IF SUPPLIED
1BEO- 69 10	0170	ADC #\$10 #MARK EVERY 16TH LOCATION	1C5B- C8	OBIO PUTD	INY
1BE2- AA	0180	TAX	1C5C- 20 02 B5	0820	JSR \$8502 FOINT TO NEXT NON-SPACE IN BUFFER
1BE3 DO F4	0190	BNE ILOOP2	105F- GO 50	0830	CPY #\$50
	0200 ;		1C61- FO 12	0840	BEQ P1 ; NO DATE ENTERED
18E5- A2 OB	0210	LDX #11	1C63- A2 00	0850	LDX #0
18E7- BD D3 1D	0220 ILOOP3	LDA FILEO,X SET FIRST LINE	1C65- B9 35 01	0860 PL00P1	LDA CRT,Y ;MOVE DATE INFO TO HEADER
1BEA- 9D 00 1E	0230	STA DRCTRY,X	1C68- C9 20	0870	CMP #' #END IF SPACE READ
IRED- CA	0240	DEX	1C6A- FO 09	0880	BEQ P1
1BEE- 10 F7	0250	BPL ILOOP3	1C6C- 9D OC 1E	0890	STA DRCTRY+12,X
1BF0- 18	0260	CLC	1C6F- C8	0900	ÍNY
1BF1- 4C 5E BO	0270	JMP RAE,HOT	1C70- E8	0910	INX
	0280 ;	•	1071- EO 04	0920	CPX #4
		LIST DIRECTORY	1073- DO FO	0930	BNE PLOOP1
	0300 ;		1C75- A2 00	0940 F1	LDX #0 #FOINT TO FILE O
1BF4- 20 4D 83	0310 LIST	JSR CRLF	1C77- 20 A8 1C	0950	JSR CUE #PROMPT USER
1BF7- A2 00	0320	LDX #0		0960 # SET UP	PARAMETERS FOR SYM SAVE
1BF9- BD BC 1D	0330 LOOF1	LDA HEADER,X ; TYPE HEADER	1C7A- A9 00	0970	LDA #O #FILE NUMBER O
1BFC- 30 06	0340	BMI LSTART ##FF MARKS END-OF-MESSAGE	1C7C- 8D 4E A6	0980	STA PIL
1BFE- 20 47 8A	0350	JSR OUTCHR	1C7F- 8D 4F A6	0990	STA P1L+1
1C01- E8	0360	INX	1C82- A9 00	1000	LDA #L,DRCTRY
1002- DO F5	0370	BNE LOOP1 JALWAYS	1C84- 8D 4C A6	1010	STA F2L
	0380 #		1C87- A9 1E	1020	LDA #H, DRCTRY
1004- A2 00	0390 LSTART	LIX #0	1C89- 8D 4D A6	1030	STA P2L+1
1C06- BD 00 1E	0400 L00F2	LDA DRCTRY,X	1C8C- A9 00	1040	LDA #L, ENDADD
1009- C9 FE	0410	CMP #\$FE	108E- 8D 4A A&	1050	STA: P3L
100B- FO OD	0420	BEQ LSKIP FSKIP OVER DELETED ENTRIES	1091- A9 1F	1060	LDA #H, ENDADD
			1C93- 8D 4B A6	1070	STA P3L+1 SYM-PHYSIS 8:28
		SYM-FHYSIS B:27	1673" OD 40 HO	10/0	214 13E11 214-FH1313 0120

```
1096- A9 04
                                                                                       1D07- C8
                 1080
                                                                                                        0560
                                                                                                                        INY FOINT TO FILE NUMBER
                                 LDA #4
1C98- 8D 30 A6
                                                                                       1D08- B9 35 01
                                                                                                       0570
                                                                                                                        LDA CRT,Y
                1090
                                 STA TAPDEL
                                               FLONG SYNC
109B- A0 80
                 1100
                                                                                       1DOB- C9 46
                                                                                                       0580
                                                                                                                        CMP #/F
                                 LDY #$80
1C9D- 20 87 8E
                1110
                                 JSR DUMPT
                                                                                       1DOD- FO 05
                                                                                                       0590
                                                                                                                        BEQ D1
1CA0- A9 01
                1120
                                 LDA #1
                                                                                       1D0F- A2 32
                                                                                                       0600 DE1
                                                                                                                        LDX #$32
1CA2- BD 30 A6
                1130
                                 STA TAPDEL
                                                                                       1D11- 6C OE BO
                                                                                                       0610
                                                                                                                        JMP (ERROR) ; F NOT FOUND
1CA5- 4C 5E BO
                                                                                       1D14- C8
                1140
                                 JMP RAE HOT
                                                                                                       0620 B1
                                                                                                                        INY
                                                                                       1015- A2 0A
                                                                                                       0630
                                                                                                                        LIIX #$A
                1150 #
                                                                                       1D17- 20 E6 B2
                                                                                                                        JSR GETBYT
                                                                                                       0640
                                                                                                                                     JGET BYTE FROM BUFFER
                1160
                                 ·CT F3
                                                                                       101A- AD OA O1
                                                                                                                        LDA $10A
                                                                                                       0.650
                 0010 ; CASSETTE TAPE DIRECTORY - FILE 3
                                                                                       1010- 20 2F 1D
                                                                                                                        JSR LOOKUP
                                                                                                                                     #LOOK UP FILE#
                                                                                                       0660
                 0020 # CUE
                                                                                       1D20~ BO OB
                                                                                                       0670
                                                                                                                        BCS NOTFOUND
                 0030 ; TYPE DIRECTORY LINE,
                                                                                       1D22- A9 FE
                                                                                                       0880
                                                                                                                        LDA #$FE
                                                                                                                                      JOVERWRITE FILE NUMBER
                 0040 ; THEN TYPE USER PROMPT,
                                                                                       1D24- 9D 00 1E
                                                                                                       0690
                                                                                                                        STA DRCTRY X
                                                                                                                                              #X POINTS TO ENTRY
                 0050 ; WAIT FOR USER.
                                                                                       1027- 4C 5E BO
                                                                                                       0700
                                                                                                                        JMP RAE.HOT
1CA8- 20 25 1C
                0060 CUE
                                 JSR PRILINE FTYPE DIRECTORY LINE
                                                                                                       0710 NOTFOUND
                                                                                       102A- A2 36
                                                                                                                        LDX #$36
1CAB- 20 4D 83
                0070
                                 JSR CRLF
                                                                                       1D2C- 6C OE BO
                                                                                                       0720
                                                                                                                        JMP (ERROR) | FILE NOT FOUND
1CAE- BA
                 0080
                                 TXA
                                                                                                       0730 ;
1CAF- 38
                 0090
                                 SEC
                                                                                                       0740 6
                                                                                                                 LOOK UP FILE # IN DIRECTORY
1CBO- E9 10
                 0100
                                 SBC #$10
                                               FRESET LINE POINTER
                                                                                                                 · CARRY SET IF FILE NOT FOUND
                                                                                                       0750 ;
1CB2- AA
                 0110
                                 TAX
                                                                                                       0760 £
                                                                                                                   CARRY CLEAR IF FILE FOUND AND
1CB3- E8
                 0120
                                 INX
                                      FOINT TO CASSETTE COUNTER
                                                                                                       0770 #
                                                                                                                     X POINTS TO LINE IN DIRECTORY FILE
1CB4- E8
                0130
                                 INX
                                                                                       1D2F- A2 00
                                                                                                       0780 LOOKUP
                                                                                                                        LDX #0
1CB5- A0 03
                0140
                                 LDY #3
                                                                                       1031- DD 00 1E
                                               EXFER COUNTER TO MESSAGE BUFFER
                                                                                                       0790 EKLDOP
                                                                                                                        CMP DRCTRY X
1CB7- BD 00 1E
                0150 FILLOOP
                                 LDA DRCTRY,X
                                                       FGET HEX BYTE
                                                                                       1034- FO OC
                                                                                                       0800
                                                                                                                        BEG FNDFILE
1CBA- 20 09 83 0180
                                 JSR NIBASC | CONVERT LO NIBBLE
                                                                                       1036- 48
                                                                                                       0810
                                                                                                                            #SAVE FILE # BEING SEARCHED FOR
1CBD- 99 EB 1D
                0170
                                 STA CUEMSG+12,Y
                                                                                       1D37- 8A
                                                                                                       0820
                                                                                                                        TXA
1CCO- 88
                0180
                                 DEY
                                                                                       1038- 18
                                                                                                                        CLC
                                                                                                       0830
1CC1- BD 00 1E
                0190
                                 LDA DRCTRY,X
                                                                                      1039- 69 10
                                                                                                       0840
                                                                                                                        ADC #$10
                                                                                                                                      POINT TO NEXT ENTRY
1CC4- 4A
                0200
                                 LSR A
                                                                                      1D3B- BO 07
                                                                                                       0850
                                                                                                                        BCS LRET
                                                                                                                                      FEND OF DIRECTORY
1CC5- 4A
                0210
                                 LSR A
                                                                                      103D- AA
                                                                                                       0860
                                                                                                                        TAX
1CC6- 4A
                0220
                                 LSR A
                                                                                       1D3E- 68
                                                                                                       0870
                                                                                                                        PLA
1CC7- 4A
                0230
                                 LSR A
                                                                                      1D3F- 4C 31 1D
                                                                                                       0880
                                                                                                                        JMP LKLOOP
1008- 20 09 83
                0240
                                 JSR NIBASC | CONVERT HI NIBBLE
                                                                                      1042- 18
                                                                                                       0890 FNDFILE
                                                                                                                        CLC
1CCB- 99 EB 1D
               0250
                                 STA CUEMSG+12,Y
                                                                                      1043- 60
                                                                                                       0900
                                                                                                                        RTS
100E- CA
                0260
                                 DEX
                                                                                      11/44- 68
                                                                                                                        PLA
                                                                                                       0910 LRET
1CCF- 88
                0270
                                 DEY
                                                                                      1045- 60
                                                                                                       0920
                                                                                                                        RTS
1CD0- 10 E5
                0280
                                 BPL FILLOOP
                                                                                                       0930
                                                                                                                        ·CT F4
1CD2- 20 F5 1C
                0290
                                 JSR MSG
                                               FTYPE PROMPT MESSAGE
                                                                                                       0010 j
                                                                                                               CASSETTE TAPE DIRECTORY - FILE 4
                                 JSR INCHR
1CD5- 20 1B 8A
                0300
                                               WAIT FOR USER INFUT
                                                                                                       0020 ;
1CD8- 20 4D 83
                0310
                                 JSR CRLF
                                               JECHO CRLF TO ANY CHAR ENTERED
                                                                                                                 ENTER COMMAND
                                                                                                       0030 ;
1CDB- 60
                0320
                                 RTS
                                                                                                       0040 ; LOOK UP FILE IN DIRECTORY
                0330 ;
                                                                                                       0050 ; CUE OPERATOR
                0340 ; >DC G -- GET DIRECTORY FROM TAPE
                                                                                                       0060 ; WRITE TO TAPE IN RAE FORMAT
1CDC- A2 00
                0350 GETD
                                 LDX #0
                                                                                                                        CPY #$50
                                                                                      1D46- CO 50
                                                                                                       0070 ENT
1CDE- 20 A8 1C
                0360
                                 JSR CUE
                                              FPROMPT USER
                                                                                                                        BCS ENERRI
                                                                                      1D48- BO 30
                                                                                                       0080
1CE1- A9 00
                0370
                                 LDA #0
                                                                                      1D4A- 20 A0 B6
                                                                                                       0090
                                                                                                                        JSR GETBUR
1CE3- 8D 4E A6
                0380
                                 STA P1L
                                              FILE 00
                                                                                      1D4D- C9 46
                                                                                                       0100
                                                                                                                        CMP #'F
1CE6- A0 80
                0390
                                 LDY #$80
                                                                                                                        BNE ENERR2
                                                                                      1D4F- DO 2D
                                                                                                       0110
1CE8- 20 78 8C
                0400
                                 JSR LOADT
                                                                                                                        INY
                                                                                      1D51- C8
                                                                                                       0120
1CEB- 90 05
                0410
                                 BCC OKLOAD
                                                                                                                       LDX #$A
                                                                                      1052- A2 0A
                                                                                                       0130
1CED- A2 17
                0420
                                 LDX #$17
                                                                                      1D54- 20 E6 B2
                                                                                                                                     JOET FILE* FROM RAE BUFFER
                                                                                                      0140
                                                                                                                        JSR GETBYT
1CEF- 6C 0E B0
                0430
                                 JMP (ERROR)
                                                                                      1D57- AD QA 01
                                                                                                       0150
                                                                                                                        LDA $10A
1CF2- 4C 5E BO
                0440 OKLOAD
                                 JMP RAE + HOT
                                                                                      105A- 20 2F 1B
                                                                                                      0160
                                                                                                                        JSR LOOKUP
                                                                                                                                     *SEARCH DIRECTORY FOR FILE
                0450 ;
                                                                                                                        BCC EN1
                                                                                      1D5D- 90 05
                                                                                                       0170
1CF5- 20 4D 83
                0460 MSG
                                 JSR CRLF
                                                                                      1D5F- A2 36
                                                                                                       0180
                                                                                                                       LDX #$36
1CF8- A2 00
                0470
                                 LDX #0
                                                                                                      0190 ENERR
                                                                                                                        JMP (ERROR)
                                                                                                                                     FILE NOT FOUND
                                                                                      1061- 6C OE BO
1CFA- BD DF ID
                0480 MSGLOOP
                                 LDA CUEMSG, X
                                                                                                                        JSR CUE
                                                                                      1D64- 20 A8 1C
                                                                                                      0200 EN1
1CFD- 30 06
                0490
                                 BMI MSGEXIT
                                                                                                                                     FRESET BUFFER POINTER
                                                                                      1D67- A0 00
                                                                                                       0210
                                                                                                                       LDY #0
1CFF- 20 47 8A
                0500
                                 JSR OUTCHR
                                                                                      1D69- A9 50
                                                                                                       0220
                                                                                                                       LDA #'P
1D02- E8
                0510
                                INX
                                                                                                                       STA CRT
                                                                                                                                     CHANGE INPUT BUFFER...
                                                                                      1D6B- 8D 35 01
                                                                                                      0230
1003- DO F5
                0520
                                 BNE MSGLOOP
                                                                                                                                     ; TO A 'FUT' COMMAND
                                                                                                                       LDA #'U
                                                                                      1D6E- A9 55
                                                                                                       0240
1005- 60
                0530 MSGEXIT
                                RTS
                                                                                                                       STA CRT+1
                                                                                      1D70~ 8D 36 01
                                                                                                      0250
                0540 ;
                                                                                                                                     FRESET X FOR COMMAND SEARCH
                                                                                      1073- A2 00
                                                                                                      0260
                                                                                                                       LDX #0
1D09- C8
                0550 DELETE
                                INY IDELETE FILE
                                                                                      1D75- 86 EF
                                                                                                       0270
                                                                                                                       STX *$EF
                                                                                                                                     CLEAR PUT FLAG
                                                              SYM-PHYSIS 8:29
                                                                                                                                                       SYM-PHYSIS 8:30
```

```
JMP DOCMD
                                              FLET RAE DO THE WORK
1077- 4C AE B6 0280
                0290 ENERR1
                                1 DX #$35
107A- A2 35
                                BNE ENERR
                                              FILE# MISSING
                0300
1070- DO E3
                0310 ENERR2
                                LDX #$32
1D7E- A2 32
                                BNE ENERR
                                              * F" NOT FOUND
1080- DO DF
                0320
                0330 ;
                        LOAD COMMAND
                0340 ;
                          GET FILE NUMBER FROM BUFFER
                0350 ;
                0360 #
                          PROMPT USER
                          READ (GET) FILE FROM TAPE
                0370 #
                0380 LOAD
                                CPY #$50
1082- CO 50
                                              *TEST FOR ARGUMENT
                                BCS LERRI
1084- BO 2E
                0390
                                              FGET NEXT CHAR FROM RAE
                                JSR GETBUF
1086- 20 AO B6
                0400
                                CMP #'F
1089- C9 46
                0410
                                              JIS IT AN "F"?
                                BNE LERR2
1088- DO 28
                0420
                                TNY
                0430
1080- C8
                                LDX #$A
108E- A2 0A
                0440
                                 JSR GETBYT
                                              FGET FILE NUMBER
1090- 20 E6 B2
                0450
                                LDA $10A
1D93- AD OA 01
                0460
                                              #I DOK UP FILE# IN DIRECTORY
                                 JSR LOOKUP
1096- 20 2F 1D
                0470
                                              *CARRY SET IF FILE NOT FOUND
                                RCC LO1
1099- 90 05
                0480
                                LDX #$36
                0490
1D9B- A2 36
                0500 LERR
                                 JMP (ERROR)
1D9D- 6C OE BO
                                              #PROMPT USER
                                JSR CUE
1DA0- 20 A8 1C
                0510 t.01
                                LDY #0
10A3- A0 00
                0520
                                LDX #0
1DA5-- A2 00
                0530
                                              CHANGE RAE BUFFER TO ...
                                LDA #'G
1DA7- A9 47
                0540
                                STA CRT
                                              ; A "GET" COMMAND.
                0550
1DA9- 8D 35 01
                                I DA # E
1DAC- A9 45
                0560
                                 STA CRT+1
1DAE- 8D 36 01
                0570
                                              ;LET RAE DO IT
                                 JMP DOCMD
1DB1- 4C AE B6
                0580
                0590 ;
                                LDX #$35
                0600 LERR1
1DB4- A2 35
                                BNE LERR
1DB6- DO E5
                0610
                                LEX #$32
1088- A2 32
                0620 LERR2
                                 BNE LERR
10BA- DO E1
                0630
                0640 #
                         MESSAGE BLOCKS
                0650 #
                0660 ;
                                 .RY 'FIL CNTR ----NAME----' $FF
                0670 HEADER
1DBC- 46 49 4C
1DBF- 20 43 4E
1DC2- 54 52 20
1DC5- 2D 2D 2D
1DC8- 2D 4E 41
1BCB- 4D 45 2D
1DCE- 2D 2D 2D
1001- 20 FF
1DD3- 00 00 00 0680 FILEO
                                 .BY O O O 'DIRECTORY'
1DD6- 44 49 52
1DD9- 45 43 54
1DDC- 4F 52 59
                                 .BY 'CUE TAPE TO 0000' $0D $0A
1DDF- 43 55 45 0690 CUEMSG
1DE2- 20 54 41
1DE5- 50 45 20
1DE8- 54 4F 20
1DEB- 30 30 30
1DEE- 30 OD 0A
               0700
                                 .BY 'THEN HIT RETN' $FF
1DF1- 54 48 45
1DF4- 4E 20 48
10F7- 49 54 20
1DFA- 52 45 54
                                    0710 ; DIRECTORY FILE IS HERE
1DFD- 4E FF
                                                     .BA $1E00
                                    0720
                                    0730 DRCTRY
                                                     .DS 256
                    1E00-
                                                     .DI =
                                    0740 ENDADD
                                                            SYM-PHYSIS 8:31
                                                     . EN
                                    0750
```

ARCADE TYPE GAMES

We have had numerous requests for "real-time" arcade sames, and have received several such programs, some for the KTM-2/80, and some for the MTU Visible Memory. There is not enough room available to print any one of them in toto, but we present below the instruction sheet which soes with Jack Gieryic's "HI-RES LASER GUN" same, JBP-6, to sive you an idea of the kinds of things which can be done with the Visible Memory.

from JACK BUILT PROGRAMS

This 1K machine language program presents the user with 8 targets traveling across the top of the screen and a movable laser gun on the bottom. Gun positioning and fire control is via the hex keypad on the SYM.

Hardware Requirements: 1K of RAM at \$1000
Micro Technology's 8K Visible Memory
General Instrument's Programmable Sound Generator
(AY-3-8910/8912) wired per PSG Demonstrator

No, this isn't just another entertaining same. I wrote this program to gain experience with MTU's Visible Memory. I wanted to see just how interactive the SYM could be and how close I could get to 'real time'. This program should be viewed as an idea generator rather than an amusement device.

First a note on the Visible Memory. This board provides 8K of additional RAM for your SYM and can be jumper selected at any 8K boundary. If you have Blalock's 4K memory expansion board on your SYM, then the Visible Memory will provide you with your next 8K of RAM. The VM board provides a composite video signal which can be fed into a monitor. The monitor display consists of 200 horizontal lines with each line consisting of 320 dots. That's 64,000 dots all under software control! Each dot can be turned on or off by simply changing a bit in memory. Each byte in the VM controls 8 consecutive dots. The first forty words on the memory represent the top line (left to right), the second 40, the 2nd line and so on down thru the 200th line. When any number of consecutive dots are turned on, the result is a solid white line on that part of the monitor. Changing the display is simply storing data into memory.

The Laser Gun Program has been assembled to load at location \$1000. Begin execution with G 1000 CR. To move the gun left(right) simply press the number 1(3) on the hex keypad. From any one position you may fire 10 shots and the gun becomes inactive. To reactivate it, just move the gun right or left. To fire the gun, press the number 4. Too heavy a hand will fire all 10 shots in a flash. To restart the program, press the number 7.

The PSG will let you hear the sun fire as well as provide an explosion when one of the targets is hit. It's interesting to observe how the addition of sound can change a normally silent video display. Sight is not the only sense which can be stimulated by your computer.

When an explosion occurs the entire monitor screen is inversed for an instant and then placed back in normal video. My 30MHz bandwidth, (continued on page 8:38)

SYM-PHYSIS 8:32

ANOTHER SOFTWARE SOURCE

Kin-Pins Kwok, Flat A, 10/F, 20-22 Tuns Choi St., Tat Mins Blds., Monskok, Kowloon, Hons Kons, several of whose ideas and programs have been published in earlier issues, sent us his version of a Dissassembler-into-RAE, with permission to publish freely, at just about the same time we were puttins the finishing touches on the Hissink version published in this issue.

His version contains one convenience feature not present in the Hissink version. If insufficient space has been allocated for the source code, the Kwok version stops to permit entry of a .CT, dumping to cassette, and resumption of disassembly from that point.

He has used his disassembler to prepare "relocatable source codes" for BASIC and RAE, and has sent us cassettes containing his results. These programs would be extremely useful for anyone wishing to replace the BAS-1 and RAE-1 ROMs with RAM, and reassemble both programs into the same address space. We reproduce below, that portion of his correspondence giving his prices. We highly recommend these programs; please write him directly for any additional information.

Dear Br. Luxenbers,

On the tare enclosed, there are four programs(each was recorded twice). They are programs related to the programs I sent you last time with the letter dated 4th Mayy81.

The first program on the tame is a RAE file with some necessary internal address definations for the reassemble of the SYM BASIC assemble listing. Documentation on the relocation of SYM BASIC is also enclosed.

The second program on the tage is the RASIC assembly listing senerator executed in \$299-\$DFF. The use of it is described in last letter.

The third program is the relocated SYM BASIC executed in \$1000-

The last program on tage is the RAE relocator. Documentation is also enclosed.

I would like to say assin that the programs can be obtained

RAE relocator including documentation — U.S.\$15.00. Commented source listing of the disassemble, object code and documentation(I sent you last time) — U.S.\$15.00

PASIC assembly listing generator including a file with necessary internal address defination, documentation and cross-reference --U.S.

Comments and sussestions are always welcome.

Yours sincerels,

Kin-pins Kwok

NEW FRODUCT - THE SPIKE SPIKER DELUXE POWER CONSOLE

We finally found what we had been looking for these many years, a way to "organize" the maze of 3-prong power cords coming from a collection of computer connected devices. This is the "Spike-Spiker" Deluxe Power Console, made by KALGO Electronics Co., Inc.

In addition to transient absorption and RF 'hash' filtering, this neat little 'black box' provides EIGHT individually-switched, 120 Volt, 60 Hertz, power outlets, a line fuse, a pilot light, and a master switch. We like it so much, that we have become dealers, and can offer it at a discount. See the addendum mailed with this issue for the price.

SYM-PHYSIS 8:33

CORRECTION TO THE DIS PROGRAM

We knew of one very minor bus to DIS, but prepared the copy for the printer anyway, Just in case. The fix arrived Just in time. Here 'tis: Delete lines 3440 and 3450 and insert the following lines instead:

3440	LSR A	FTEST FOR ZERO PAGE FORMAT
3445	BCC NZERO	FCODES 01,05,11
3450	CMF #\$09	FELIMINATE 21,59,40,10
3455	BCS NZERO	

After the disassembly is completed verify that the source file has been properly terminated. It should contain a \$00 byte at the end-of-file address + 2. The first number on the second line of the SEt message printed after disassembly is complete is the end-of file address. Then insert a .BA \$XXXX and a .CE at the front of the source and a .EN at the end, as enter AS. External address references will be flagged with error messages.

A USEFUL CASSETTE TIP

Here is a helpful suggestion from Dick Albers, Placentia, CA, followed by some additional comments from the editor:

"SYM-1's tare LOAD program uses the same memory locations as '.M' to keep track of 'current memory location' in which to store the next byte. If you have trouble loading a tare, after the 'ER XX' message, enter .M <cr>
last address loaded + 1. This can be used to adjust your volume and tone controls."

We sussest that you study, with simple examples, how RAE-1 and BAS-1 mark the ends of their files, and how and where the end pointers are set. Do this with a readable cassette. Then, when you find that you can read most, but not all, of a long cassette dump, you can use this knowledge, plus the tip above to set the pointer and end marker correctly, to rescue at least part of your cassette load.

This tip is also helpful for readable cassettes when you just want to know the ending address.

MISCELLANIA

TRI-TEK, 7808 N. 27th Ave., Phoenix, AZ 85021, lists and describes in their new catalos, the National Semiconductor complementary chip pair, the LM1871 Radio Control Encoder/Transmitter, and the LM1872 Radio Control Receiver/Decoder. The normal configuration for this pair permits the remote transfer of two analos and two binary (on/off) signals, but this may be modified. Price for each chip is \$7.45, for each spec sheet is \$0.40. Anyone tried them yet with the SYM?

MATT WILSON, author of "HEXTOASCII" on page 8:2, has designed an inexpensive (he cails it cheap) 625 line, 50 Hz video board for SYM. He will send plans to anyone interested.

DAVE KEMP, East Coast Micro Products, Odenton, MD (ESP-1 Speech Synthesizer), along with many others, has sent us versions of Apple SAVE and DUMP routines. We intend sublishing an integrated version combining the best features of all of the many programs we have received.

DON DEPEW, Sparton Electronics, Jackson, MI, suggests identifying each program you write with a unique identifier. An example might be \$106141645TITLE/LUX. The number indicates the year, month date, and time, and the title and author follow. This makes it easy to identify the version (is this the latest, how many have there been?) and allows several tass for organizing your programs.

FULLY COMMENTED SOURCE CODE FOR MICROSOFT BASIC?

Microsoft holds its source codes to be proprietary, and BAS-1 loss-on with a copyright notice, but presumably it is a legitimate research effort to analyze object code to determine its inner workings, and to generate, through one's own efforts, a recreation of source code. Such research could certainly also be a team effort. A purchaser would seem to be free to modify and enhance a purchased product, and indeed, to freely market such enhancements as a new product. If the "enhancements" are so "complete" that a purchaser of the enhancement need not also purchase the original product, that is another matter, indeed. We quote from a recent letter from John Hissink in this regard:

"I have been disassembling BAS-1 and have generated relocatable text. I would like to fully disassemble BAS-1 as part of a (small?) team effort, mainly out of interest in seeing how the language works, and learning the programming tricks used. It's quite well commented now, and I sit down every now and then with the printout and do some more, but it will take a year, unless I drop all other projects. Any interest with the guys in your neighborhood? If so, I'll send the latest version on a disk (it takes 33 tracks!) and we can start from that and exchange updates."

We know of a number of users who have pretty much annotated their printouts of BAS-1 disassemblies, but very few who have done so for "reassemblable" disassemblies. John, Steve Cole, and Arthur Richards have been working together to reorganize BAS, RAE, FODS, and MON (and everything else they can get their hands on) in order to create a really coherent system package.

Since each of these programs was developed independently, they have differing syntaxes. One uses spaces as delimiters, two use commas, one uses none. Command words also differ. For example, BASIC uses SAVE and LOAD for cassette operations (disk is not supported), while RAE-1 uses PUt and GEt for cassette, and ENter and LOad for disk. Since RAE was cast in ROM, while FODS was not, we replaced FODS' SAVE with ENTer for consistency.

Note that BASIC permits no abbreviations, FOIS requires three letter abbreviations, and RAE permits two letter abbreviations or even extensions of the word. In fact, what we called LOad above was called LOakup in the original RAE manual (no, this is not documented in the RAE-1 Reference Manual as issued by Synertek!).

Their system will be easier to learn and use than the "standard", but at the cost of program transportability. They are carrying the concept of a "personal" computer to its ultimate limit! In practice, however, the syntax and vocabulary differences mentioned above are no real problem. All good computerists must be multilingual, anyway.

But, to set back to the main point: If you are interested in Joining John's team (you will need FODS to participate), sign-on with him at 29 Knox Road, Havant, Hants, FO9, INP, England. The end result of your participation will be a fully commented source source code of a version of Microsoft BASIC into which you can incorporate any enhancements you wish. You'll also end up with the most powerful DISK BASIC available!

MORE ON FORTH

FORTH is fast becoming our own personal favorite computer language. We SYM-PHYSIS 8:35

have decided that we will become our University's resident FORTH "expert" while everyone else is setting into Pascal. We strongly recommend that you subscribe to Saturn Software, Ltd.'s (SSL) "Saturn Softnews", even if you have not yet some FORTH, as the best way of introducing yourself to the language.

In the first issue, Jack Brown publishes, and explains, in detail, the screens (the standard page-format for FORTH source code) necessary to convert the original fig-FORTH model to the new 79-STANDARD. He also provides screens for a real-time clock, sound-effects generation, KTM-2/80 graphics, and MTU Visible Memory graphics. We feel that the best way to become fluent in any language is by reading lots of well written material in that language, and Softnews provides that material.

We have been testing, with great pleasure; Saturn Software's latest FORTH product, a disk-based 79-STANDARD FORTH, with 8 "resident" screens, and 104 (!!!) "virtual-memory" disk-resident screens, all on-line at once, With diskette changes, the useful memory is unlimited. It's the renultimate system!

We will soon be receiving a still newer product, a fully disk-linked Extended SYM-BASIC (ESB-2), for evaluation, testing, and review. ESB-1 and ESB-2 will also be supported in Saturn Softnews. We wish Jack much, much success in his venture. SSL's address is 8246 - 116A St., Belta, B.C., Canada V4C 579.

ANOTHER RS-232 FORT FOR THE SYM

The SYM has a 20 mA current loop port which works at TTL level (+5 V), but you may need to add a 1 K resistor from the base of Q28 to ground, to improve the keyboard input reliability. We see no need ever to bring in a -Vn for current loop usage.

The so-called RS=232 port is actually an inverted TTL port, with 0 V representing a *1", and a \pm 5 V (nominal) representing a *0", as far as outputs so. From the input standpoint, the SYM will accept the full range of RS=232 levels, from < \pm 5 V to > \pm 5 V.

Most of the modern RS-232 equipments will accept the inverted TTL signals; for those that do not, you will need to bring in a -Vn and change some jumpers.

It is very simple to convert the 20 mA loop to a non-inverted TTL port by shunting the output to the printer with 150 to 250 ohm resistor (use the existing R110, 150 ohm resistor, for this purpose, by "local" rewiring). If you wish to invert the TTL signal to make this port RS-232 compatible, cut the appropriate traces and insert inverters in series. For your information, there are three unused inverters on the SYM which you are free to use for this, or any other purpose. These are to be found in the 74LSO4 at U9 (pins 3,4,5,6) and in the 74O4 at U2 (pins 1,2). In addition, pins 3 and 4 of the open-collector hex inverter 7416 at U38 are also free. If you purchased the early version of RAE-1 (with the A suffix), you are already using the inverter in U2, to correct for a masking error in the ROM CS (chip select) pin polarity.

MUSIC, MUSIC, MUSIC

We now have the MTU Musical Instrument Synthesis Sons Pack on our system, with over 40 selections. We have automated the system to re-boot itself after each selection (for some pieces, the instrument synthesis tables overlay, and destroy, the DOS) and ask the listener to enter the number of his desired selection. Our favorites include "Lara's Theme," "The Entertainer," "Maple Leaf Ras," and "Dueling BanJos," but there are some excellent Tchaikovsky, Bach, Handel, Chopin selections thrown in.

The little 150 mW (into 16 ohms) amplifiers on the two MTU DAC boards drive a large pair of 3-way speakers to room-filling volume, and it's hard to realize that you are not listening to real pianos, banjos, horns, guitars, balalaikas, etc.

For background, review the two BYTE Massazine articles by Hal Chamberlin:

- Sept 1977: A Samplind of Techniques for Computer Performance of Music
 Apr 1980: Advanced Real-Time Music Synthesis Techniques
- The MTU DAC Board comes with its hardware manual, and a cassette containing object code similar to that in the first article, and several melodies, suitable for a 4K system. All MTU music is four-voice harmony; with two DACs, the music is stereo.

The Advanced Music Software Package contains a source code · listing for all programs described in the first article and a cassette containing all object code. An 8K system is required.

Music produced by the techniques described in the first article is "adequate". Like the talking dos who had very little to say, but was amazing because it could talk at all! On the other hand the techniques described in the second article make the SYM into a true musical instrument, any instrument! It must be heard to be believed. A stered cassette (audio) is available of a lecture by Mr. Chamberlin, with a half-dozen selections.

At least 16K, preferably 32K is required for the Musical Instrument Synthesis Package, which contains source code listings, object code on cassette, and three selections on cassette, for 16K, 24K, and 32K systems.

And finally, for owners of the Musical Instrument Synthesis Package, the Sons Pack, on cassette or FODS diskette, is available. MTU and Hal have done an outstanding development job in the music area.

NOTE: All MTU products, including reprints of the BYTE articles, are available through the Users' Group. See latest addendum for prices.

MORE MISCELLANIA

JERRY AVINS, RCA, David Sarnoff Research Center, Princeton, NJ, sent us a pair of minature electromagnetic speakers, distributed by Star Micronics, Inc., 200 Park Ave., Suite 2308E, New York, NY 10017. These can be plugged into a standard DIP socket, if desired, and make excellent "BELL's for the KTH-2. Jerry explained how to get rid of the annoying noise when the bell is supposed to be "off". This noise is due to the variable TTL zero level signal. Merely adding a silicon diode in series will do the Job! If you wish to keep the DC component of the signal out of the speaker you can also add a capacitor in series, as well.

JOHN BLALOCK, whose address appears in many back issues, in connection, with his memory (RAM and ROM) expansion boards, sent us a copy of HIS "DISAssembler-into-RAE". It arrived too late to review, but John's programs are usually good (Not always, however! In one of his programs published in MICRO he omitted the 'mandatory' JSR ACCESS needed before writing to System RAM. He didn't realize the omission however, because like many others, he had cut the MM-45 write-protect jumper!). He will provide RAE source cassettes of his version for \$15.00 plus postage.

(It must be more than coincidence, it is the world's need, that at least four disassemblers-into-RAE were developed nearly simultaneously. In addition to the three mentioned in this issue, Bob Peck also described his version to us.)

SYM-PHYSIS 8:37

(continued from page 8:32)

tube-type monitor is unable to handle this situation. The image is severly distorted during this operation. However, my Leedex Video 100 monitor handles this situation like a champ. It remains rock solid!

I've added a box containing 8 switches (SPST momentary contact, normally open) in parallel with the hex keypad numbers 0 thru 7 per the diagram and wire list. It attaches to the Applications Connector (A). This makes the user interface a bit more fun as well as provide for future expansion. Switches 0, 1, 2 and 3 correspond to up, left, down and right. Up and down are not used by this program. The other four switches are available for other program functions. In this case S4 will fire the sun and S7 will restart the program.

If your VM is jumpered to begin at another 8K boundary other than \$2000 then change location \$1001 from \$20 to whatever you selected. To change the sound of the gun when it fires, thy changing location \$1EEB. Only values between \$01 and \$0F are allowed. The sound of the gun after all 10 shots are fired is controlled by location \$1F2C.




Figure 1 - SWITCH BOX LAYOUT




Figure 2 - SWITCH BOX SCHEMATIC

We tried the visual portion of this same, but not the audio, because our sound senerator is not set installed. As is usual with Jack's programs, the same is valuable not only for itself, but for the additional ideas it provides.

SYM-PHYSIS 8-38

STILL MORE MISCELLANIA

J. San St. 18 18

CARL MOSER, author of RAE-1, based on his previous ASSM/TED for the 6502, has long had available an ASSM/TED 6800; a cross-assembler from 6502 to 6800. He has been selling this to industrial users with full documentation and consulting support for \$500. Since RAE-1 users already have the essential documention, and since we have agreed to provide any required support, Carl has allowed the Users' Group to market ASSM/TED 6800 object code on diskette or cassette for \$75. We hope that Carl will soon have an ASSM/TED 6809 available. Since most SYM-1/69 users will also have a SYM-1 available, the cross-assembler approach should be acceptable.

TERRY TRIFFET, Engineering Dean, University of Arizona, has come up with an interesting concept, that of publishing books on cassettes, readable on any computer system with Microsoft Basic. Terry has written a text editor in BASIC to permit organizing the text and dumping it to cassette a page at a time. A typical full-length book could be contained on a single 60-90 minute cassette. When tapes are duplicated automatically, publishing costs are below those for hard copy editions. A second BASIC program permits the user to control the read-in and formatting of successive pages. The user specifies the terminal width (from 40 to 66) and the display is right-justified, with long words hyphenated, if required. Terry's first book is a novel, "The One-fold Way". We have read the first three charters and are anxious to read the rest. The formatter program and the complete novel are available directly from Terry, at 6935 Stardust Circle, Tucson AZ, 85718, for \$25. As a convenience to overseas subscribers who are ordering other items and would prefer to send only a single check, the Users' Group will handle overseas orders.

WILLI KUSCHE, Wilserv Industries, P. O. Box 456, Bellmawr, NJ 08031, sent us a copy of the User's Manual for KMMM (Kushe Magnetic Media Monitor), a 6502 system DOS (Disk Operating System). KMMM is written to be used with the SD Systems Versaflorpy I Florpy Disk Controller, which itself is designed to be used with the S-100 Bus. It was John Blalock who called our attention to KMMM by sending us a preprint of an article submitted to MICROCOMPUTING, describing his method of interfacing the SYM to the Versafloppy Controller. John has high praise for K-M cubed, and sent along copies of his links between PAS-1/RAE-1 and KMMM. He also sent along a schematic of a simple 6502 to S-100 bus signal converter to drive the Versaflorey FDC. Since MICROCOMPUTING has a long las time for articles, contact Willi for additional information, don't wait for the article. Our feelings about KMMM? It is a well conceived and well implemented DOS, and since it can read CP/M senerated disks, it should be possible to transfer ASCII text files to/from 8080/Z-80 based systems, using 8° drives.

PROTRONICS, 1516 E. Tropicana, Suite 7A815, Las Vedas, NV 89109, sent us a copy of the Owner's Manual for a 32K Dynamic RAM Board for the KIM-4 Bus. The board also includes four ROM/EPROM sockets. The 32K can be assigned either above or below \$8000, and individual 4K blocks can be disabled in case of address space conflicts. The ROM sockets will hold the 2-chip versions of BAS-1 and RAE-1/2 or 4 EPROMS. Contact PROTRONICS directly for additional information.

JOE HOBART, 3465 N. Andes Dr., Flasstaff, AZ 86001, has sent us for review a copy of PIRATE'S ADVENTURE, adapted from the TRS-80 Level II BASIC version printed in BYTE, December 1980. As the author, Scott Adams, of Adventure International (AI), points out (and as we have confirmed by testins), BASIC is far too slow, and requires lots of memory. Mr. Adams states that all current AI sames are written in assembly language, and save Joe authorization to distribute his BASIC version royalty-free. The same requires a FULL 32K system, really! Send Joe \$15 for a cassette copy.

LOG-OUT

Well, another issue will be ready to so to the printer's when these closing paragraphs are stored on disk (ENT LOG), the printer turned on (DC PON), and the hard copy prepared for publication (DC PUB).

We have published three programs, all in assembly language, one each at the beginning, intermediate, and advanced levels. This does not mean that we did not get enough BASIC programs, or that we are anti-BASIC. We like BASIC; we regard it as the lingua franca of the computer world, and feel it should be everyone's at least second language.

Actually, we did receive many more BASIC programs than we could find time to try, and Tom Gettys has given us a whole diskful. We think we have convinced Tom to compile the listings into a book, which we could call 'The First BASIC Book of SYM', and offer for sale in the next issue, and provide on cassette also. If you would be interested in spurring Tom on, write to him, in care of us. Our aim should be to build the SYM software availability up to where it will become the STRONGEST selling point for SYM.

In our next issue we will be publishing a neat BASIC utility program submitted by Jim Pengra, of Whitman College, Walla Walla, WA. This program searches a BASIC text file and picks out and lists all variable names. Unfortunately, it arrived too late for review and publication in this issue.

We hope also to find room for John Hissink's 9600 baud terminal patch program, which will practically seem to throw the data onto your CRT screen. Several readers, including Jean Paris, of Paris, France, who visited us last weekend, on a motorcycle trip through the western US and Canada, work at 9600 baud regularly, by simply having replaced the 1.0 MHz crystal with a 2.0 MHz one.

We restet to announce that the miniature ultra-violet lamp which forms the basis for our chear EPROM Eraser has been discontinued. We are contacting all possible places we can think of which may have some still in stock. Thanks to Bill Cramer; Altanta, GA, who found us a small batch, we still have a few Erasers available, but at a slightly increased price. See addendum for new price.

Our Microprocessor Fundamentals class at Chico State drew 26 students from as far away as Michisan, Utah, and Washinston State. In addition a number of Chico State's foreign students from Algeria and Saudi Arabia were resistered. Six of the students were previous "SYMmers". These included Phil Kohl, Dick Albers, Ken Kartchner, Larry Brisss, Joe Fierstein and Paul Walker. It was good to meet with these "old friends", and to be able to compare notes with them. There was quite a profitable interchange of ideas. In addition, they provided valuable guidance and inspiration to the raw beginners. We will be offering this course again at University of California, Davis (near Sacramento), on Sept 11-13. The fee is \$295, or \$495 with a SYM included. Call (916) 752-0880 for additional information.

We will be on a sabbatical leave from Chico State during the spring semester of 1982, and plan to spend several weeks each in Europe and the South Pacific area. If any of our readers associated with universities or technical schools would wish to have us as a "Visiting Professor" for a few days, in exchange for local travel and lodging expenses, please write. We look forward to meeting with many of our overseas readers during these trips.

We thank all who have submitted material, and apologize that so much had to be left out; it was not easy to decide, and there was more than enough for an 80-page issue.

SYM-PHYSIS 8-40